



ZEN

FOR
THE **AMSTRAD**
CPC464

© 1984 AVALON SOFTWARE

Kuma

ZEN

Z80 Assembly Language Programming System

for

the

AMSTRAD CPC 464 MICROCOMPUTER

(C) 1984 Avalon Software

(C) COPYRIGHT 1984 Avalon Software

ISBN 07457-0000-4

All rights reserved

No part of this manual or programming system may be reproduced by any means without prior written permission of the author or the publisher.

This programming system is supplied in the belief that it operates as specified, but Kuma Computers Ltd. (the company) shall not be liable in any circumstances whatsoever for any direct or indirect loss or damage to property incurred or suffered by the customer or any other person as a result of any fault or defect in goods or services supplied by the company and in no circumstances shall the Company be liable for consequential damage or loss of profits (whether or not the possibility thereof was separately advised to it or reasonably foreseeable) suffered as a result of any such fault or defect or which otherwise arises from the use or performance of such goods or services.

Published by:-

Kuma Computers Ltd.,
12 Horseshoe Park,
Pangbourne,
Berks RG8 7JW

Telex 849462 Tel 07357 4335

Introduction

Thank you for buying this copy of ZEN for the Amstrad CPC64. If you have any questions about ZEN then please feel free to write to Avalon Software. All high level languages have performance limitations, when you need the maximum in speed and flexibility the answer lies in Assembly Language programming. ZEN provides you with the tools to generate or analyse Z80 Assembly Language programs.

Starting up

Unlike BASIC, which is permanently available in ROM, you need to load ZEN from cassette. It is stored on the cassette as a binary file designed to run at address 4000H (16384 decimal). BASIC usually assumes that it has the whole of memory to itself. To ensure that BASIC and ZEN coexist peacefully it is necessary to change the top of memory before loading from cassette. The loading procedure is therefore as follows:

(1) Type MEMORY 16383(ENTER)

(2) Type LOAD"ZEN"(ENTER)

BASIC will then load ZEN into memory, displaying various prompts and messages as it does so. When loading is finished you are returned to BASIC's command level, any existing BASIC programs are unaffected. To transfer control to ZEN type CALL 16384(ENTER).

Command level

Whenever the prompt ZEN> is displayed you are at command level, you may execute any of the following commands:

A	Assemble	O	Out
B	Bye	P	Print
C	Copy	Q	Query
D	Down	R	Read
E	Enter	S	Sort
F	Fill	T	Target
G	Goto	U	Up
H	Howbig	W	Write
I	In	X	Xanine
K	Kill	Z	Zap
L	Locate	c	catalog
M	Modify	d	disassemble
N	New	u	unscramble

To select a given command type in the first letter of it's name, followed by a parameter if relevant, and then press the (ENTER) key. The DEL key can be used to backspace. The usage of command loop parameters is explained in greater detail in the next section, which examines each command in depth. If ZEN doesn't understand anything you've typed in it will display the error message HUH? The default command, just pressing (ENTER) on it's own will clear the screen.

Amstrad ZEN Reference Manual

Assemble The function of the assembler is to read a series of assembly language statements and to produce the corresponding Z80 machine code and listing. The ZEN editing commands are used to create a text file in memory which is the input to the assembler. Output of the machine code file, usually called the object file, is controlled by the LOAD operator (see under PSEUDO-OPS). The listing output is specified by you in response to the OPTION> prompt from the assembler. You may specify V(ENTER), E(ENTER) or (ENTER) for video, external or null list output. The null output option is much the fastest mode (the assembler is peripheral-bound) and should be used until all syntax errors are corrected. The text file is read beginning at the start-of-file and stopping when the END operator is found.

Bye This command gives a warm return to BASIC, any BASIC programs in memory are unaffected. You can do a warm return to ZEN by issuing the CALL 16384 statement as described previously. You can shuttle between ZEN and BASIC whenever you like without affecting any files or data in memory.

Copy This command moves a block of memory. You will be prompted for START>, STOP> and DESTINATION> parameters. Within ZEN's command structure a numeric parameter may be a decimal, hexadecimal or octal number. Hex numbers are 'H' postfixed and octal are 'O' postfixed. So if you wanted to move the block of memory from 200H to 2FFH up to 800H you would type 200H(ENTER), 2FFH(ENTER) and 8000H(ENTER).

Down This command moves the editor current line down by the number of lines specified in the command parameter. For example D37(ENTER) moves down thirty-seven lines. The default command parameter is one so D(ENTER) moves down one line. The editor in ZEN is line orientated as in BASIC but does not use explicit line numbers, instead you use various commands to move around the text file until you reach the required position. You then use the ENTER or ZAP commands to insert or delete lines of text. If the DOWN command bumps into the end-of-file then the message EOF will be displayed.

Enter This command enters lines of text into the text file. ZEN will display the current line number, type in your line of text then press (ENTER). This process will repeat until you type a full stop as the first character on the line, this returns you to command level. Your text is placed in the file at the current line, the old current and following lines are moved downwards towards EOF. Note that although line numbers are often displayed by ZEN these are dynamically computed and not stored in the text file.

Fill This command fills a block of memory, from START> to STOP> inclusive with a DATA> value. You will be prompted for all three parameters.

Goto This command loads the Z80 registers with the User Image and transfers control to the address specified in the command parameter. For example G0(ENTER) would perform a complete system cold start. If no command parameter is supplied then control is transferred to the address in the User Program Counter. You will then be prompted for a breakpoint address. If you respond with a valid address parameter then a breakpoint is set at that address. If you default, by just pressing (ENTER), then no breakpoint is set. A breakpoint is a way of stopping a running program. A RST 30H instruction (0F7H) is inserted into the program and a vector back to the ZEN trap handler is placed at 0030H. The trap handler will save all the Z80 registers in the User Image area and restore the code under the breakpoint before returning to the ZEN command loop. You can thus examine the state of the Z80 at the time of the breakpoint. You cannot set a breakpoint in ROM, ZEN will generate a MEMORY error message if the breakpoint has failed to set for this reason. You can continue execution by using the G(ENTER) command as the Program Counter is saved as part of the trap process.

Howbig This command displays, in hexadecimal, the start and end addresses of the text file and the top of memory. ZEN will allow the text file to grow up to this top limit but no further. You can change this limit if required (see ZEN listing, the LIMIT constant). It is presently set at AB7FH, the area from AB80H to BFFFH is used by the BASIC operating system. The area from C000H to FFFFH is the video memory.

In This command will display, in hexadecimal and binary, the data read from the I/O port specified by the command parameter. For example I83H(ENTER). The particular hardware configuration of the Amstrad CPC64 means that addresses up to FFFFH are valid.

Kill This command erases the text file, as with the NEW statement in BASIC. It is possible to recover an accidentally KILLED file as ZEN just makes the EOF pointer equal to the SOF pointer, the actual text will still be in memory. Find the address of the last text character, this will be an ASCII Carriage Return code (0DH). Increase this by one and use the MODIFY command to restore the EOF pointer (see ZEN listing, EOFP).

Locate This command is used to search the text file for a particular string of characters. The character string forms the command parameter. For example LB1T 7,A(ENTER) would find the first occurrence of the string BIT 7,A in the text file. The text file is searched from the line after the current line. If the string is found then that line is made the current line. If the search fails you are at end-of-file. There are no restrictions on the contents of the parameter string.

Modify This command allows you to examine and alter memory contents. The start address is specified by the command parameter. For example M7000H(ENTER) would cause the command to start at 7000H. If you supply no address parameter then the command continues from where it last finished. The byte at the address is displayed in hex and ZEN prompts for a data parameter from you. If you supply a parameter then it is stored at that address, if you default ZEN just steps onto the next address. To return to command level type a full stop.

Amstrad ZEN Reference Manual

New This command lets you modify the current line of the text file. The line is displayed with the cursor at the rightmost position. Change the line and press (ENTER) to restore the new line to the text file.

Out This command will output a data value to the I/O port specified by the command parameter. You will be prompted for the data parameter.

Print This command displays a number of lines from the text file on the screen. The number of lines is specified by the command parameter, for example P9(ENTER) would display nine lines. The default command parameter is one. The display commences with the current line and the last line displayed becomes the new current line.

Query This command displays sixty-four bytes of memory in hex and ASCII. The command parameter specifies the start address, for example Q4000H(ENTER) would display the start of ZEN. If you supply no address parameter then the display begins from where it last finished.

Read This command reads a file from cassette into memory, you will be prompted for a filename. There are two types of file which concern ZEN, text files and binary files. If the file is a text file then it is added to the end of any text already existing in memory. If the file becomes too large then the error message MEMORY is issued and reading terminates. If it is a binary file then it will be placed at its load address unless you have specified a load address as a command parameter. For example R7900H would load the file commencing at 7900H irrespective of its actual load address. The execution address of the binary file is placed in the User Program Counter. These two types of files are the same as the standard BASIC text and binary files. The type of a file is determined by a single byte in the file header. The following seem to be the normal types: BASIC = 00H, BASIC PROTECTED = 01H, BINARY = 02H, TEXT = 16H.

Sort This command will sort and display the symbol table produced during the last assembly. You will be prompted for an output option. Your possible responses are the same as for the Assembler list output. The output of this command is generated a page at a time as with list output. You can restrict the sort process to symbols beginning with a particular letter by entering that letter as a command parameter. For example SB(ENTER) would only produce the symbols beginning with the letter 'B'. Note that symbols are only sorted on the first letter and not the whole name.

Target This command will move you to any line in the text file and make it the current line. The command parameter specifies the line number, for example T1435(ENTER) would move you to line one thousand four hundred and thirty-five. The default command parameter, T(ENTER), moves you to the start-of-file.

Up This command moves you up the text file by the number of lines specified in the command parameter. The default parameter is one.

Write This command writes a text or binary file to cassette, you will be prompted for a file name. The command W(ENTER) writes the text file while the command WB(ENTER) writes an area of memory as a binary file. In this case you will be further prompted for START>, STOP> and EXEC> addresses. The area written is from start to stop inclusive, the execution address is merely placed in the file header for use in later reading.

Xamine This command displays the Z80 registers saved in the User Image. The top line shows the main registers and the lower line the Z80 alternate register set.

Zap This command removes a number of lines from the text file as specified by the command parameter. For example Z10B(ENTER) would remove one hundred and eight lines, commencing with the current line. The default command parameter is one.

catalog This command is identical to the BASIC cat command, it will verify and display all the files found on the cassette. File type indicators are: BASIC = \$, BASIC PROTECTED = %, BINARY = &, TEXT = *.

disassemble This command performs a symbolic disassembly on an area of memory and generates a text file or listing as output. You will be prompted for the START> and STOP> addresses of the area you wish to disassemble. You will then be asked the address which the program RUNS AT>. Sometimes you may have a program in memory at a different location to it's usual run-time location, the disassembler can relocate any addresses and labels in it's output to reflect this. If you default to the request for the run-time start address then ZEN assumes that the program is at it's normal run-time location. If you supply an actual address parameter then the output file will reflect this run-time address. You will then be asked, repeatedly, for the START> and STOP> addresses of any data areas within the disassembly region. These are areas which will not be decoded as instructions but as data bytes. To terminate this process type in a stop address of zero. There is a maximum of sixty-four separate data areas, if you exceed this number ZEN will generate the error message FULL. You will now be asked for an output OPTION>. You may specify V(ENTER) or E(ENTER) for listings to the video or external devices. If you default then ZEN will generate a text file and add it to the end of any text already in memory. If the text file grows up to the top of memory limit during disassembly then the error message MEMORY is issued and disassembly terminates. The only other error condition possible during disassembly is for the symbol table to fill up in which case the error message FULL is issued. Note that the disassembler uses the same symbol table as the assembler and so destroys any symbols there. This is only of relevance if you which to perform a later SORT operation. Any illegal opcodes encountered during disassembly are treated as data statements. Labels of the form Lnnnn (where nnnn is an address) will be generated at the appropriate positions.

unscramble This command is a simplified version of the disassembler. It will disassemble eight Z80 instructions beginning at the address specified by the command parameter. For example u41E0H will disassemble the start of ZEN's mainloop. If you default on the address parameter then the command continues from where it last finished. Any illegal opcodes encountered are displayed as data bytes. ZEN will try to make an intelligent guess about how to display eight bit numeric operands. Numbers less than ten are displayed as single digit decimals. Numbers from 41H to 5AH and 61H to 7AH are displayed as ASCII literal characters. Other numbers are displayed as hex values with a leading zero if necessary.

Further Information

List Output

The commands Assemble, Sort and disassemble can all generate large quantities of output to the video or external devices. With these commands the output will be generated a page at a time with a short pause between each page. Pressing any key will stop output at the end of the page, to restart press any key except 'Q'. This key will force the command to QUIT and return to the command loop.

The external device is assumed to be eighty characters wide by sixty-six lines long i.e a typical printer. You can change the page length by modifying the PAGE procedure (see ZEN listing). You can change the various field widths by modifying the group of constants COMWIDTH/SYMWIDHT (see ZEN listing). The external device is presumed to respond to the ASCII control characters Formfeed (0CH), Carriage Return (0DH) and Linefeed (0AH). ZEN issues a Formfeed followed by sixty-two lines of text for each page, each line being terminated by Carriage Return, Linefeed. The external device driver (see ZEN listing) will drive EPSON FX-80 type printers as it stands. If you have something unusual there is space in the driver to insert patches, to filter Linefeeds for example.

The video device is assumed to be forty characters wide. Note that line numbers are not generated on the video device for Assembler/disassembler listings because of this reduced width. The symbol, operand and comment fields of a Z80 statement may be of indefinite length. If necessary ZEN will truncate these fields to fit into the required format.

The Symbol Table

The symbol table is the area of memory used by ZEN to store symbols during Assembly/disassembly. It is situated between ZEN and the text file. If you wish to increase its size it is only necessary to change the start-of-file pointer to the required new value, here's how: (1) KILL the text file (2) Use MODIFY to change SOFP (3) KILL the text file again to copy SOFP into EOFP and CURRENT (4) Perform an ASSEMBLE to shut down the symbol table (5) Use WB to write the new version to cassette.

The External Environment

The Amstrad CPC64 has a complex memory map. When you first enter ZEN you will find that the Operating System and BASIC ROMs have been switched out and that RAM is contiguous from 0 to BFFFH, with the video RAM occupying the remaining space. To switch the ROMs back in is fairly easy. Enter the following keystrokes:

```
K(ENTER)
E(ENTER)
ORG 7000H(ENTER)
LOAD 7000H(ENTER)
CALL 0B900H(ENTER)
CALL 0B906H(ENTER)
JP 4000H(ENTER)
END(ENTER)
.(ENTER)
A(ENTER)
V(ENTER)
G7000H(ENTER)
(ENTER)
```

This short program calls two procedures in the Operating System interface to switch in the upper and lower ROMs. They can now be examined with the Query and unscramble/disassemble commands. For example if you Query around 660H you can see the export market names for the machine. Examination of the region around CC50H will reveal all the BASIC error messages.

ZEN will operate whatever condition the memory map is in. BASIC text files occupy low RAM just after the RESTART block and grow up towards HIMEM. The BASIC cassette operating system requires the use of two 2K buffers for read and write. When you first enter ZEN they are set to 3000H to 37FFH (Read) and 3800H to 3FFFH (Write). You can move these around by modifying the CRBUFF, CWBUFF pointer constants (see ZEN listing). They can occupy the same space if required as ZEN only uses one at a time.

Something you should be aware of when designing a program is the Amstrad's use of background interrupts. The interrupt handler is running constantly in order to scan the keyboard, etc. This interrupt handler expects to find certain information in the Z80 alternate registers. You should therefore never do an EXX instruction in your programs with interrupts enabled. If you have to look at the alternate registers for any reason then disable interrupts first. You should also be aware that any call to the Operating System jump block will turn interrupts back on and will consequently crash if you have the register sets exchanged.

Assembler Syntax

ZEN expects assembly language statements to be constructed according to the syntax defined in the ZILOG Z80 Assembly Language Programming Manual. ZEN deviates from the standard in one instance in that it expects EX AF,AF rather than EX AF,AF'. The section following this one contains an alphabetically sorted listing of the entire Z80 instruction set. Each assembly language statement may be divided into a maximum of four logical fields, they are:

- (1) Label
- (2) Operator
- (3) Operands
- (4) Comment

Label A label is a way of marking a statement so that other statements can refer to it. Line numbers serve the same purpose in BASIC, you would use GOTO 240 for example. Assembly Language allows you to use a symbolic name for a label. When you declare the label it must be postfix with a colon ':' so that the assembler knows that it's a label. A label must begin with a letter but may contain letters or digits after that. ZEN allows labels of any length with all characters being significant. The register and condition-code names may not be used as symbols as these are reserved identifiers. Any attempt to do so will result in an error message.

Operator There are sixty-seven operators in the Z80 Assembly Language. In addition ZEN supports seven PSEUDO-OOPS, they are:

END This pseudo-op terminates assembly, it MUST be used.

DS or DEFS Define Storage skips over the number of object locations specified by the operand.

DW or DEFW Define Word places the operand in the object file in reverse order as required by the Z80 word instructions.

DB or DEFB Define Byte(s) places the operand(s) in the object file at successive locations. Operands are delimited by commas, each operand may be an expression with value less than 256 or may be a literal string. Literal strings may be of any length but cannot form part of an expression.

EQU Equate assigns the value of the operand to a symbolic identifier. Any symbolic identifiers used in the operand expression must already be known to the assembler. This 'no forward reference' rule is designed to prevent circular referencing.

ORG Origin defines the start address of the object file. This pseudo-op can be used as often as needed to produce sections of code at different addresses. The 'no forward reference' rule applies to the operand.

LOAD Commences loading code into memory at the operand address. Use of a subsequent ORG pseudo-op will turn this process off, you are explicitly required to re-establish the loading process.

Operands The number of operands in a statement depends upon the operator. There are niladic, monadic and dyadic operators in the Z80 instruction set. These take zero, one and two operands respectively. There are three classes of operand:

- (1) Registers (A,B,C,D,E,H,L,I,R,HL,DE,BC,AF,IX,IY,SP)
- (2) Condition-codes (NZ,Z,NC,C,PO,PE,P,M)
- (3) Numeric expressions

A numeric expression is composed of one or more of the following elements delimited by the infix math operators:

- (1) A decimal, hex or octal number. Decimal is the default base with hex numbers being 'H' postfixed and octal '0' postfixed. Numbers must begin with a digit, a leading zero will be needed with some hex numbers.
- (2) A literal character enclosed in single or double quotes.
- (3) The \$ character. This variable mimics the program counter of the run-time program.
- (4) A symbolic name. The assembler will use the associated value in evaluating the expression.

The infix math operators are:

- + addition
- subtraction
- * multiplication
- / division
- & logical AND
- . logical OR

Expressions are evaluated STRICTLY LEFT TO RIGHT with no precedence ordering. Arithmetic is sixteen bit unsigned integer and overflow will be ignored.

Comments Comments are ignored by the assembler. They begin with a semi-colon ';' and are terminated by the end-of-line.

Assembler Error Handling

If the assembler finds a syntax error the following will happen:

- (1) Assembly terminates.
- (2) An error message is displayed.
- (3) The offending line is displayed and is made the editor current line.
- (4) The command loop is re-entered.

You can now correct the error and re-assemble. It is impossible to make a syntax error which will damage ZEN or anything in memory. The error messages are:

UNDEFINED You have used an undeclared symbol.

SYMBOL You have declared a zero length symbol or have forgotten the symbol needed with an EQU pseudo-op.

RESERVED You have tried to use a reserved word for a symbol.

FULL The symbol table is full.

DOUBLE SYMBOL You have declared the same symbol more than once.

EOF You have forgotten END and have hit end-of-file.

ORG! You have forgotten ORG.

HUH? The assembler is completely baffled.

OPERAND You have done something wrong with an operand, this covers a multitude of sins! Most types of syntax error will come under this heading as well as errors of magnitude. These occur when you try to offset too far with a relative jump or indexing instruction.

```

1 ; **** Z80 Instruction Set ****
2 ; * Z80 Instruction Set *
3 ; * **** Z80 Instruction Set ****
4
5 ORG 0
6
7
8 INDEX: EQU S ; IX,IY Index
9 NUMBER: EQU 0584H ; 16 BIT Operand
10 NUM: EQU 20H ; 8 BIT Operand
11
12 0000 8E ADC A,(HL)
13 0001 DD8E05 ADC A,(IX+INDEX)
14 0004 FD8E05 ADC A,(IY+INDEX)
15 0007 8F ADC A,A
16 0008 88 ADC A,B
17 0009 89 ADC A,C
18 000A 8A ADC A,D
19 000B 8B ADC A,E
20 000C 8C ADC A,H
21 000D 8D ADC A,L
22 000E CE20 ADC A,NUM
23 0010 ED4A ADC HL,BC
24 0012 ED5A ADC HL,DE
25 0014 ED6A ADC HL,HL
26 0016 ED7A ADC HL,SP
27 0018 86 ADD A,(HL)
28 0019 DD8605 ADD A,(IX+INDEX)
29 001C FD8605 ADD A,(IY+INDEX)
30 001F 87 ADD A,A
31 0020 80 ADD A,B
32 0021 81 ADD A,C
33 0022 82 ADD A,D
34 0023 83 ADD A,E
35 0024 84 ADD A,H
36 0025 85 ADD A,L
37 0026 C620 ADD A,NUM
38 0028 09 ADD HL,BC
39 0029 19 ADD HL,DE
40 002A 29 ADD HL,HL
41 002B 39 ADD HL,SP
42 002C DD09 ADD IX,BC
43 002E DD19 ADD IX,DE
44 0030 DD29 ADD IX,IX
45 0032 DD39 ADD IX,SP
46 0034 FD09 ADD IY,BC
47 0036 FD19 ADD IY,DE
48 0038 FD29 ADD IY,IY
49 003A FD39 ADD IY,SP
50 003C A6 AND (HL)
51 003D DDA605 AND (IX+INDEX)
52 0040 FDA605 AND (IY+INDEX)
53 0043 A7 AND A
54 0044 A0 AND B
55 0045 A1 AND C
56 0046 A2 AND D
57 0047 A3 AND E
58 0048 A4 AND H
59 0049 A5 AND L
60 004A E620 AND NUM

```

61	004C	CB46	BIT	0,(HL)
62	004E	DDCB0546	BIT	0,(IX+INDEX)
63	0052	FDCB0546	BIT	0,(IY+INDEX)
64	0056	CB47	BIT	0,A
65	0058	CB40	BIT	0,B
66	005A	CB41	BIT	0,C
67	005C	CB42	BIT	0,D
68	005E	CB43	BIT	0,E
69	0060	CB44	BIT	0,H
70	0062	CB45	BIT	0,L
71	0064	CB4E	BIT	1,(HL)
72	0066	DDCB054E	BIT	1,(IX+INDEX)
73	006A	FDCB054E	BIT	1,(IY+INDEX)
74	006E	CB4F	BIT	1,A
75	0070	CB48	BIT	1,B
76	0072	CB49	BIT	1,C
77	0074	CB4A	BIT	1,D
78	0076	CB4B	BIT	1,E
79	0078	CB4C	BIT	1,H
80	007A	CB4D	BIT	1,L
81	007C	CB56	BIT	2,(HL)
82	007E	DDCB0556	BIT	2,(IX+INDEX)
83	0082	FDCB0556	BIT	2,(IY+INDEX)
84	0086	CB57	BIT	2,A
85	0088	CB50	BIT	2,B
86	008A	CB51	BIT	2,C
87	008C	CB52	BIT	2,D
88	008E	CB53	BIT	2,E
89	0090	CB54	BIT	2,H
90	0092	CB55	BIT	2,L
91	0094	CB5E	BIT	3,(HL)
92	0096	DDCB055E	BIT	3,(IX+INDEX)
93	009A	FDCB055E	BIT	3,(IY+INDEX)
94	009E	CB5F	BIT	3,A
95	00A0	CB58	BIT	3,B
96	00A2	CB59	BIT	3,C
97	00A4	CB5A	BIT	3,D
98	00A6	CB5B	BIT	3,E
99	00A8	CB5C	BIT	3,H
100	00AA	CB5D	BIT	3,L
101	00AC	CB66	BIT	4,(HL)
102	00AE	DDCB0566	BIT	4,(IX+INDEX)
103	00B2	FDCB0566	BIT	4,(IY+INDEX)
104	00B6	CB67	BIT	4,A
105	00B8	CB60	BIT	4,B
106	00BA	CB61	BIT	4,C
107	00BC	CB62	BIT	4,D
108	00BE	CB63	BIT	4,E
109	00C0	CB64	BIT	4,H
110	00C2	CB65	BIT	4,L
111	00C4	CB6E	BIT	5,(HL)
112	00C6	DDCB056E	BIT	5,(IX+INDEX)
113	00CA	FDCB056E	BIT	5,(IY+INDEX)
114	00CE	CB6F	BIT	5,A
115	00D0	CB68	BIT	5,B
116	00D2	CB69	BIT	5,C
117	00D4	CB6A	BIT	5,D
118	00D6	CB6B	BIT	5,E
119	00D8	CB6C	BIT	5,H
120	00DA	CB6D	BIT	5,L

121	00DC	CB76	BIT	6,(HL)
122	00DE	DDCB0576	BIT	6,(IX+INDEX)
123	00E2	FDCE0576	BIT	6,(IY+INDEX)
124	00E6	CB77	BIT	6,A
125	00E8	CB70	BIT	6,B
126	00EA	CB71	BIT	6,C
127	00EC	CB72	BIT	6,D
128	00EE	CB73	BIT	6,E
129	00F0	CB74	BIT	6,H
130	00F2	CB75	BIT	6,L
131	00F4	CB7E	BIT	7,(HL)
132	00F6	DDCB057E	BIT	7,(IX+INDEX)
133	00FA	FDCE057E	BIT	7,(IY+INDEX)
134	00FE	CB7F	BIT	7,A
135	0100	CB78	BIT	7,B
136	0102	CB79	BIT	7,C
137	0104	CB7A	BIT	7,D
138	0106	CB7B	BIT	7,E
139	0108	CB7C	BIT	7,H
140	010A	CB7D	BIT	7,L
141	010C	DC8405	CALL	C,NUMBER
142	010F	FC8405	CALL	M,NUMBER
143	0112	D48405	CALL	NC,NUMBER
144	0115	CD8405	CALL	NUMBER
145	0118	C48405	CALL	NZ,NUMBER
146	011B	F48405	CALL	F,NUMBER
147	011E	EC8405	CALL	PE,NUMBER
148	0121	E48405	CALL	PO,NUMBER
149	0124	CC8405	CALL	Z,NUMBER
150	0127	3F	CCF	
151	0128	BE	CP	(HL)
152	0129	DDBE05	CP	(IX+INDEX)
153	012C	FDBE05	CP	(IY+INDEX)
154	012F	BF.	CP	A
155	0130	B8	CP	B
156	0131	B9	CP	C
157	0132	BA	CP	D
158	0133	BB	CP	E
159	0134	BC	CP	H
160	0135	BD	CP	L
161	0136	FE20	CP	NUM
162	0138	EDA9	CPD	
163	013A	EDB9	CPDR	
164	013C	EDA1	CPI	
165	013E	EDB1	CPIR	
166	0140	2F	CPL	
167	0141	27	DAA	
168	0142	35	DEC	(HL)
169	0143	DD3505	DEC	(IX+INDEX)
170	0146	FD3505	DEC	(IY+INDEX)
171	0149	3D	DEC	A
172	014A	05	DEC	B
173	014B	08	DEC	BC
174	014C	0D	DEC	C
175	014D	15	DEC	D
176	014E	1B	DEC	DE
177	014F	1D	DEC	E
178	0150	25	DEC	H
179	0151	2B	DEC	HL
180	0152	DD28	DEC	IX

181	0154	FD2B	DEC	IY
182	0156	2D	DEC	L
183	0157	3B	DEC	SP
184	0158	F3	DI	
185	0159	10FE	DJNZ	\$
186	015B	FB	EI	
187	015C	E3	EX	(SP),HL
188	015D	DDE3	EX	(SP),IX
189	015F	FDE3	EX	(SP),IY
190	0161	08	EX	AF,AF
191	0162	EB	EX	DE,HL
192	0163	D9	EXX	
193	0164	76	HALT	
194	0165	ED46	IM	0
195	0167	ED56	IM	1
196	0169	ED5E	IM	2
197	016B	ED78	IN	A,(C)
198	016D	DB20	IN	A,(NUM)
199	016F	ED40	IN	B,(C)
200	0171	ED48	IN	C,(C)
201	0173	ED50	IN	D,(C)
202	0175	ED58	IN	E,(C)
203	0177	ED60	IN	H,(C)
204	0179	ED68	IN	L,(C)
205	017B	34	INC	(HL)
206	017C	DD3405	INC	(IX+INDEX)
207	017F	FD3405	INC	(IY+INDEX)
208	0182	3C	INC	A
209	0183	04	INC	B
210	0184	03	INC	BC
211	0185	0C	INC	C
212	0186	14	INC	D
213	0187	13	INC	DE
214	0188	1C	INC	E
215	0189	24	INC	H
216	018A	23	INC	HL
217	018B	DD23	INC	IX
218	018D	FD23	INC	IY
219	018F	2C	INC	L
220	0190	33	INC	SP
221	0191	EDAA	IND	
222	0193	EDBA	INDR	
223	0195	EDA2	INI	
224	0197	ED82	INIR	
225	0199	E9	JP	(HL)
226	019A	DDE9	JP	(IX)
227	019C	FDE9	JP	(IY)
228	019E	DA8405	JP	C,NUMBER
229	01A1	FA8405	JP	M,NUMBER
230	01A4	D28405	JP	NC,NUMBER
231	01A7	C28405	JP	NUMBER
232	01AA	C28405	JP	NZ,NUMBER
233	01AD	F28405	JP	P,NUMBER
234	01B0	EA8405	JP	PE,NUMBER
235	01B3	E28405	JP	PO,NUMBER
236	01B6	CA8405	JP	Z,NUMBER
237	01B9	38FE	JR	C,\$
238	01BB	18FE	JR	\$
239	01BD	30FE	JR	NC,\$
240	01BF	20FE	JR	NZ,\$

241	01C1	28FE	JR	Z,\$
242	01C3	02	LD	(BC),A
243	01C4	12	LD	(DE),A
244	01C5	77	LD	(HL),A
245	01C6	70	LD	(HL),B
246	01C7	71	LD	(HL),C
247	01C8	72	LD	(HL),D
248	01C9	73	LD	(HL),E
249	01CA	74	LD	(HL),H
250	01CB	75	LD	(HL),L
251	01CC	3620	LD	(HL),NUM
252	01CE	DD7705	LD	(IX+INDEX),A
253	01D1	DD7005	LD	(IX+INDEX),B
254	01D4	DD7105	LD	(IX+INDEX),C
255	01D7	DD7205	LD	(IX+INDEX),D
256	01DA	DD7305	LD	(IX+INDEX),E
257	01DD	DD7405	LD	(IX+INDEX),H
258	01E0	DD7505	LD	(IX+INDEX),L
259	01E3	DD360520	LD	(IX+INDEX),NUM
260	01E7	FD7705	LD	(IY+INDEX),A
261	01EA	FD7005	LD	(IY+INDEX),B
262	01ED	FD7105	LD	(IY+INDEX),C
263	01F0	FD7205	LD	(IY+INDEX),D
264	01F3	FD7305	LD	(IY+INDEX),E
265	01F6	FD7405	LD	(IY+INDEX),H
266	01F9	FD7505	LD	(IY+INDEX),L
267	01FC	FD360520	LD	(IY+INDEX),NUM
268	0200	328405	LD	(NUMBER),A
269	0203	ED438405	LD	(NUMBER),BC
270	0207	ED538405	LD	(NUMBER),DE
271	020B	228405	LD	(NUMBER),HL
272	020E	DD228405	LD	(NUMBER),IX
273	0212	FD228405	LD	(NUMBER),IY
274	0216	ED738405	LD	(NUMBER),SP
275	021A	0A	LD	A,(BC)
276	021B	1A	LD	A,(DE)
277	021C	7E	LD	A,(HL)
278	021D	DD7E05	LD	A,(IX+INDEX)
279	0220	FD7E05	LD	A,(IY+INDEX)
280	0223	3A8405	LD	A,(NUMBER)
281	0226	7F	LD	A,A
282	0227	78	LD	A,B
283	0228	79	LD	A,C
284	0229	7A	LD	A,D
285	022A	7B	LD	A,E
286	022B	7C	LD	A,H
287	022C	ED57	LD	A,I
288	022E	7D	LD	A,L
289	022F	3E20	LD	A,NUM
290	0231	ED5F	LD	A,R
291	0233	46	LD	B,(HL)
292	0234	DD4605	LD	B,(IX+INDEX)
293	0237	FD4605	LD	B,(IY+INDEX)
294	023A	47	LD	B,A
295	023B	40	LD	B,B
296	023C	41	LD	B,C
297	023D	42	LD	B,D
298	023E	43	LD	B,E
299	023F	44	LD	B,H
300	0240	45	LD	B,L

301 0241 0620	LD B,NUM
302 0243 ED4B8405	LD BC,(NUMBER)
303 0247 018405	LD BC,NUMBER
304 024A 4E	LD C,(HL)
305 024B DD4E05	LD C,(IX+INDEX)
306 024E FD4E05	LD C,(IY+INDEX)
307 0251 4F	LD C,A
308 0252 48	LD C,B
309 0253 49	LD C,C
310 0254 4A	LD C,D
311 0255 4B	LD C,E
312 0256 4C	LD C,H
313 0257 4D	LD C,L
314 0258 0E20	LD C,NUM
315 025A 56	LD D,(HL)
316 025B DD5605	LD D,(IX+INDEX)
317 025E FD5605	LD D,(IY+INDEX)
318 0261 57	LD D,A
319 0262 50	LD D,B
320 0263 51	LD D,C
321 0264 52	LD D,D
322 0265 53	LD D,E
323 0266 54	LD D,H
324 0267 55	LD D,L
325 0268 1620	LD D,NUM
326 026A ED5B8405	LD DE,(NUMBER)
327 026E 118405	LD DE,NUMBER
328 0271 5E	LD E,(HL)
329 0272 DD5E05	LD E,(IX+INDEX)
330 0275 FD5E05	LD E,(IY+INDEX)
331 0278 5F	LD E,A
332 0279 58	LD E,B
333 027A 59	LD E,C
334 027B 5A	LD E,D
335 027C 5B	LD E,E
336 027D 5C	LD E,H
337 027E 5D	LD E,L
338 027F 1E20	LD E,NUM
339 0281 66	LD H,(HL)
340 0282 DD6605	LD H,(IX+INDEX)
341 0285 FD6605	LD H,(IY+INDEX)
342 0288 67	LD H,A
343 0289 60	LD H,B
344 028A 61	LD H,C
345 028B 62	LD H,D
346 028C 63	LD H,E
347 028D 64	LD H,H
348 028E 65	LD H,L
349 028F 2620	LD H,NUM
350 0291 2A8405	LD HL,(NUMBER)
351 0294 218405	LD HL,NUMBER
352 0297 ED47	LD I,A
353 0299 DD2A8405	LD IX,(NUMBER)
354 029D DD218405	LD IX,NUMBER
355 02A1 FD2A8405	LD IY,(NUMBER)
356 02A5 FD218405	LD IY,NUMBER
357 02A9 6E	LD L,(HL)
358 02AA DD6E05	LD L,(IX+INDEX)
359 02AD FD6E05	LD L,(IY+INDEX)
360 02B0 6F	LD L,A

361	02B1	68	LD	L,B
362	02B2	69	LD	L,C
363	02B3	6A	LD	L,D
364	02B4	6B	LD	L,E
365	02B5	6C	LD	L,H
366	02B6	6D	LD	L,L
367	02B7	2E20	LD	L,NUM
368	02B9	ED4F	LD	R,A
369	02BB	ED7B8405	LD	SP,(NUMBER)
370	02BF	F9	LD	SP,HL
371	02C0	DDF9	LD	SP,IX
372	02C2	FDF9	LD	SP,IY
373	02C4	318405	LD	SP,NUMBER
374	02C7	EDA8	LDD	
375	02C9	EDB8	LDDR	
376	02CB	EDA0	LDI	
377	02CD	EDB0	LDIR	
378	02CF	ED44	NEG	
379	02D1	00	NOP	
380	02D2	B6	OR	(HL)
381	02D3	DDB605	OR	(IX+INDEX)
382	02D6	FDB605	OR	(IY+INDEX)
383	02D9	B7	OR	A
384	02DA	B0	OR	B
385	02DB	B1	OR	C
386	02DC	B2	OR	D
387	02DD	B3	OR	E
388	02DE	B4	OR	H
389	02DF	B5	OR	L
390	02E0	F620	OR	NUM
391	02E2	EDBB	OTDR	
392	02E4	EDB3	OTIR	
393	02E6	ED79	OUT	(C),A
394	02E8	ED41	OUT	(C),B
395	02EA	ED49	OUT	(C),C
396	02EC	ED51	OUT	(C),D
397	02EE	ED59	OUT	(C),E
398	02F0	ED61	OUT	(C),H
399	02F2	ED69	OUT	(C),L
400	02F4	D320	OUT	(NUM),A
401	02F6	EDAB	OUTD	
402	02F8	EDAS	OUTI	
403	02FA	F1	POP	AF
404	02FB	C1	POP	BC
405	02FC	D1	POP	DE
406	02FD	E1	POP	HL
407	02FE	DDE1	POP	IX
408	0300	FDE1	POP	IY
409	0302	F5	PUSH	AF
410	0303	C5	PUSH	BC
411	0304	D5	PUSH	DE
412	0305	E5	PUSH	HL
413	0306	DDE5	PUSH	IX
414	0308	FDES	PUSH	IY
415	030A	CB86	RES	0,(HL)
416	030C	DDCB0586	RES	0,(IX+INDEX)
417	0310	FDCB0586	RES	0,(IY+INDEX)
418	0314	CB87	RES	0,A
419	0316	CB80	RES	0,B
420	0318	CB81	RES	0,C

421	031A	CB82	RES	0,D
422	031C	CB83	RES	0,E
423	031E	CB84	RES	0,H
424	0320	CB85	RES	0,L
425	0322	CB8E	RES	1,(HL)
426	0324	DDCB058E	RES	1,(IX+INDEX)
427	0328	FDCB058E	RES	1,(IY+INDEX)
428	032C	CB8F	RES	1,A
429	032E	CB88	RES	1,B
430	0330	CB89	RES	1,C
431	0332	CB8A	RES	1,D
432	0334	CB8B	RES	1,E
433	0336	CB8C	RES	1,H
434	0338	CB8D	RES	1,L
435	033A	CB96	RES	2,(HL)
436	033C	DDCB0596	RES	2,(IX+INDEX)
437	0340	FDCB0596	RES	2,(IY+INDEX)
438	0344	CB97	RES	2,A
439	0346	CB90	RES	2,B
440	0348	CB91	RES	2,C
441	034A	CB92	RES	2,D
442	034C	CB93	RES	2,E
443	034E	CB94	RES	2,H
444	0350	CB95	RES	2,L
445	0352	CB9E	RES	3,(HL)
446	0354	DDCB059E	RES	3,(IX+INDEX)
447	0358	FDCB059E	RES	3,(IY+INDEX)
448	035C	CB9F	RES	3,A
449	035E	CB98	RES	3,B
450	0360	CB99	RES	3,C
451	0362	CB9A	RES	3,D
452	0364	CB9B	RES	3,E
453	0366	CB9C	RES	3,H
454	0368	CB9D	RES	3,L
455	036A	CBA6	RES	4,(HL)
456	036C	DDCB05A6	RES	4,(IX+INDEX)
457	0370	FDCB05A6	RES	4,(IY+INDEX)
458	0374	CBA7	RES	4,A
459	0376	CBA0	RES	4,B
460	0378	CBA1	RES	4,C
461	037A	CBA2	RES	4,D
462	037C	CBA3	RES	4,E
463	037E	CBA4	RES	4,H
464	0380	CBA5	RES	4,L
465	0382	CBAE	RES	5,(HL)
466	0384	DDCB05AE	RES	5,(IX+INDEX)
467	0388	FDCB05AE	RES	5,(IY+INDEX)
468	038C	CBAF	RES	5,A
469	038E	CBA8	RES	5,B
470	0390	CBA9	RES	5,C
471	0392	CBAA	RES	5,D
472	0394	CBAB	RES	5,E
473	0396	CBAC	RES	5,H
474	0398	CBAD	RES	5,L
475	039A	CBB6	RES	6,(HL)
476	039C	DDCB05B6	RES	6,(IX+INDEX)
477	03A0	FDCB05B6	RES	6,(IY+INDEX)
478	03A4	CBB7	RES	6,A
479	03A6	CBB0	RES	6,B
480	03A8	CBB1	RES	6,C

481	03AA	CBB2	RES	6,D
482	03AC	CBB3	RES	6,E
483	03AE	CBB4	RES	6,H
484	03B0	CBB5	RES	6,L
485	03B2	CBBE	RES	7,(HL)
486	03B4	DDCB05BE	RES	7,(IX+INDEX)
487	03B8	FDCB05BE	RES	7,(IY+INDEX)
488	03BC	CBBF	RES	7,A
489	03BE	CBB8	RES	7,B
490	03C0	CBB9	RES	7,C
491	03C2	CBBA	RES	7,D
492	03C4	CBBB	RES	7,E
493	03C6	CBBC	RES	7,H
494	03C8	CBBD	RES	7,L
495	03CA	C9	RET	
496	03CB	D8	RET	C
497	03CC	F8	RET	M
498	03CD	D0	RET	NC
499	03CE	C0	RET	NZ
500	03CF	F0	RET	P
501	03D0	E8	RET	PE
502	03D1	E0	RET	PO
503	03D2	C8	RET	Z
504	03D3	ED4D	RETI	
505	03D5	ED45	RETN	
506	03D7	CB16	RL	(HL)
507	03D9	DDCB0516	RL	(IX+INDEX)
508	03DD	FDCB0516	RL	(IY+INDEX)
509	03E1	CB17	RL	A
510	03E3	CB10	RL	B
511	03E5	CB11	RL	C
512	03E7	CB12	RL	D
513	03E9	CB13	RL	E
514	03EB	CB14	RL	H
515	03ED	CB15	RL	L
516	03EF	17	RLA	
517	03F0	CB06	RLC	(HL)
518	03F2	DDCB0506	RLC	(IX+INDEX)
519	03F6	FDCB0506	RLC	(IY+INDEX)
520	03FA	CB07	RLC	A
521	03FC	CB00	RLC	B
522	03FE	CB01	RLC	C
523	0400	CB02	RLC	D
524	0402	CB03	RLC	E
525	0404	CB04	RLC	H
526	0406	CB05	RLC	L
527	0408	07	RLCA	
528	0409	ED6F	RLD	
529	040B	CB1E	RR	(HL)
530	040D	DDCB051E	RR	(IX+INDEX)
531	0411	FDCB051E	RR	(IY+INDEX)
532	0415	CB1F	RR	A
533	0417	CB18	RR	B
534	0419	CB19	RR	C
535	041B	CB1A	RR	D
536	041D	CB1B	RR	E
537	041F	CB1C	RR	H
538	0421	CB1D	RR	L
539	0423	1F	RRA	
540	0424	CB0E	RRC	(HL)

541	0426	DDCB050E	RRC	(IX+INDEX)
542	042A	FDCB050E	RRC	(IY+INDEX)
543	042E	CB0F	RRC	A
544	0430	CB08	RRC	B
545	0432	CB09	RRC	C
546	0434	CB0A	RRC	D
547	0436	CB0B	RRC	E
548	0438	CB0C	RRC	H
549	043A	CB0D	RRC	L
550	043C	0F	RRCA	
551	043D	ED67	RRD	
552	043F	C7	RST	0
553	0440	D7	RST	10H
554	0441	DF	RST	18H
555	0442	E7	RST	20H
556	0443	EF	RST	28H
557	0444	F7	RST	30H
558	0445	FF	RST	38H
559	0446	CF	RST	8
560	0447	9E	SBC	A,(HL)
561	0448	DD9E05	SBC	A,(IX+INDEX)
562	044B	FD9E05	SBC	A,(IY+INDEX)
563	044E	9F	SBC	A,A
564	044F	98	SBC	A,B
565	0450	99	SBC	A,C
566	0451	9A	SBC	A,D
567	0452	9B	SBC	A,E
568	0453	9C	SBC	A,H
569	0454	9D	SBC	A,L
570	0455	DE20	SBC	A,NUM
571	0457	ED42	SBC	HL,BC
572	0459	ED52	SBC	HL,DE
573	045B	ED62	SBC	HL,HL
574	045D	ED72	SBC	HL,SP
575	045F	37	SCF	
576	0460	CBC6	SET	0,(HL)
577	0462	DDCB05C6	SET	0,(IX+INDEX)
578	0466	FDCB05C6	SET	0,(IY+INDEX)
579	046A	CBC7	SET	0,A
580	046C	CBC0	SET	0,B
581	046E	CBC1	SET	0,C
582	0470	CBC2	SET	0,D
583	0472	CBC3	SET	0,E
584	0474	CBC4	SET	0,H
585	0476	CBC5	SET	0,L
586	0478	CBCE	SET	1,(HL)
587	047A	DDCB05CE	SET	1,(IX+INDEX)
588	047E	FDCB05CE	SET	1,(IY+INDEX)
589	0482	CBCF	SET	1,A
590	0484	CBC8	SET	1,B
591	0486	CBC9	SET	1,C
592	0488	CBCA	SET	1,D
593	048A	CBCB	SET	1,E
594	048C	CBCC	SET	1,H
595	048E	CBCD	SET	1,L
596	0490	CBD6	SET	2,(HL)
597	0492	DDCB05D6	SET	2,(IX+INDEX)
598	0496	FDCB05D6	SET	2,(IY+INDEX)
599	049A	CBD7	SET	2,A
600	049C	CBD0	SET	2,B

601	049E	CBD1	SET	2,C
602	04A0	CBD2	SET	2,D
603	04A2	CBD3	SET	2,E
604	04A4	CBD4	SET	2,H
605	04A6	CBD5	SET	2,L
606	04A8	CBD6	SET	3,(HL)
607	04AA	DDCB05DE	SET	3,(IX+INDEX)
608	04AE	FDCB05DE	SET	3,(IY+INDEX)
609	04B2	CBDF	SET	3,A
610	04B4	CBD8	SET	3,B
611	04B6	CBD9	SET	3,C
612	04B8	CBDA	SET	3,D
613	04BA	CBDB	SET	3,E
614	04BC	CBDC	SET	3,H
615	04BE	CBDD	SET	3,L
616	04C0	CBE6	SET	4,(HL)
617	04C2	DDCB05E6	SET	4,(IX+INDEX)
618	04C6	FDCB05E6	SET	4,(IY+INDEX)
619	04CA	CBE7	SET	4,A
620	04CC	CBE0	SET	4,B
621	04CE	CBE1	SET	4,C
622	04D0	CBE2	SET	4,D
623	04D2	CBE3	SET	4,E
624	04D4	CBE4	SET	4,H
625	04D6	CBE5	SET	4,L
626	04D8	CBEE	SET	5,(HL)
627	04DA	DDCB05EE	SET	5,(IX+INDEX)
628	04DE	FDCB05EE	SET	5,(IY+INDEX)
629	04E2	CBEF	SET	5,A
630	04E4	CBE8	SET	5,B
631	04E6	CBE9	SET	5,C
632	04E8	CBEA	SET	5,D
633	04EA	CBEB	SET	5,E
634	04EC	CBEC	SET	5,H
635	04EE	CBED	SET	5,L
636	04F0	CBF6	SET	6,(HL)
637	04F2	DDCB05F6	SET	6,(IX+INDEX)
638	04F6	FDCB05F6	SET	6,(IY+INDEX)
639	04FA	CBF7	SET	6,A
640	04FC	CBF0	SET	6,B
641	04FE	CBF1	SET	6,C
642	0500	CBF2	SET	6,D
643	0502	CBF3	SET	6,E
644	0504	CBF4	SET	6,H
645	0506	CBF5	SET	6,L
646	0508	CBFE	SET	7,(HL)
647	050A	DDCB05FE	SET	7,(IX+INDEX)
648	050E	FDCB05FE	SET	7,(IY+INDEX)
649	0512	CBFF	SET	7,A
650	0514	CBF8	SET	7,B
651	0516	CBF9	SET	7,C
652	0518	CBFA	SET	7,D
653	051A	CBFB	SET	7,E
654	051C	CBFC	SET	7,H
655	051E	CBFD	SET	7,L
656	0520	CB26	SLA	(HL)
657	0522	DDCB0526	SLA	(IX+INDEX)
658	0526	FDCB0526	SLA	(IY+INDEX)
659	052A	CB27	SLA	A
660	052C	CB20	SLA	B

661	052E	CB21	SLA	C
662	0530	CB22	SLA	D
663	0532	CB23	SLA	E
664	0534	CB24	SLA	H
665	0536	CB25	SLA	L
666	0538	CB2E	SRA	(HL)
667	053A	DDCB052E	SRA	(IX+INDEX)
668	053E	FDCB052E	SRA	(IY+INDEX)
669	0542	CB2F	SRA	A
670	0544	CB28	SRA	B
671	0546	CB29	SRA	C
672	0548	CB2A	SRA	D
673	054A	CB2B	SRA	E
674	054C	CB2C	SRA	H
675	054E	CB2D	SRA	L
676	0550	CB3E	SRL	(HL)
677	0552	DDCB053E	SRL	(IX+INDEX)
678	0556	FDCB053E	SRL	(IY+INDEX)
679	055A	CB3F	SRL	A
680	055C	CB38	SRL	B
681	055E	CB39	SRL	C
682	0560	CB3A	SRL	D
683	0562	CB3B	SRL	E
684	0564	CB3C	SRL	H
685	0566	CB3D	SRL	L
686	0568	96	SUB	(HL)
687	0569	DD9605	SUB	(IX+INDEX)
688	056C	FD9605	SUB	(IY+INDEX)
689	056F	97	SUB	A
690	0570	90	SUB	B
691	0571	91	SUB	C
692	0572	92	SUB	D
693	0573	93	SUB	E
694	0574	94	SUB	H
695	0575	95	SUB	L
696	0576	D620	SUB	NUM
697	0578	AE	XOR	(HL)
698	0579	DDAE05	XOR	(IX+INDEX)
699	057C	FDAE05	XOR	(IY+INDEX)
700	057F	AF	XOR	A
701	0580	A8	XOR	B
702	0581	A9	XOR	C
703	0582	AA	XOR	D
704	0583	AB	XOR	E
705	0584	AC	XOR	H
706	0585	AD	XOR	L
707	0586	EE20	XOR	NUM
708				
709			END	

```

1      ; ****
2      ; **      AMSTRAD ZEN 1.0      **
3      ; **
4      ; ** Written by John Hawthorne **
5      ; **
6      ; **      Copyright 1984      **
7      ; **      AVALON SOFTWARE      **
8      ; **      Cowley , Middlesex   **
9      ; ****
10
11          ORG 4000H
12
13          ; Control characters
14
15          BS:      EQU 8
16          LF:      EQU 10
17          CR:      EQU 13
18          FF:      EQU 12
19          BLANK:   EQU 32
20          DEL:     EQU 7FH
21          St:      EQU 80H
22
23          ; External s
24
25          WAITCHAR: EQU 0BBB6H
26          READCHAR: EQU 0BBB9H
27          TXTOUT:   EQU 0BB5AH
28          CURON:    EQU 0BBS1H
29          CUROFF:   EQU 0BBS4H
30          CINIT:    EQU 0BC63H
31          CCAT:     EQU 0PC9BH
32          CIDIR:   EQU 0BC93H
33          CODIR:   EQU 0BC98H
34          CIABON:   EQU 0BC7DH
35          COABAN:   EQU 0BC92H
36          CIOCHAR:  EQU 0BC80H
37          COCHAR:   EQU 0BC95H
38          CIOPEN:   EQU 0BC77H
39          COOPEN:   EQU 0BC8CH
40          CICLOSE:  EQU 0BC7AH
41          COCLOSE:  EQU 0BC8FH
42          BMIR:     EQU 0B91BH
43          PRUSY:    EQU 0BD2EH
44          PSEND:    EQU 0BD31H
45
46          ; Flag displacements
47
48          F1:      EQU 0
49          F2:      EQU 1
50          F3:      EQU 2
51          F4:      EQU 3
52          F5:      EQU 4
53          F6:      EQU 5
54          F7:      EQU 6
55
56          ; Code starts here, skip text etc.
57
58 4000 C3E041 ENTRY:    JP ZEN
59 4003 C34E47 REENTRY:   JP TRAP
60 4006 5A454E3E M1:      DB 'ZEN>',CR

```

60	400A 0D		
61	400B 4855483F M2:	DB	'HUUH?',CR
61	400F 0D		
62	4010 50414745 M4:	DB	'TYPE?',CR
62	4014 0D		
63	4015 454F6620 M5:	DB	'EOPT?',CR
64	4019 4F505449 M7:	DB	'OPTIONS?',CR
64	401D 4F4E3E0D		
65	4021 44415441 M9:	DB	'DATA AREA?',CR
65	4025 20415245		
65	4029 41533A0D		
66	402D 52554E53 M11:	DB	'TRUNC AT?',CR
66	4031 2041543E		
66	4035 0D		
67	4036 52455345 M12:	DB	'RESERVED?',CR
67	403A 52564544		
67	403E 0D		
68	403F 46554C40 M14:	DB	'FULL?',CR
68	4043 0D		
69	4044 444F5542 M15:	DB	'DOUBLE?',CR
69	4048 4C4520		
70	404B 53594D42 M16:	DB	'SYMBOL?',CR
70	404F 4F400D		
71	4052 4F504552 M16:	DB	'PURAND?',CR
71	4056 414E442D		
72	405A 554E4445 M17:	DB	'INFTY?',CR
72	405E 46494E45		
72	4062 442D		
73	4064 4F524721 M18:	DB	'NORM?',CR
73	4068 0D		
74	4069 49454D4F M20:	DB	'MEMORY?',CR
74	406D 52590D		
75	4070 4E414D45 M21:	DB	'NAME?',CR
75	4074 3E0D		
76	4076 53544152 M22:	DB	'START?',CR
76	407A 543E0D		
77	407D 53544F50 M23:	DB	'STOP?',CR
77	4081 3E0D		
78	4083 424E5054 M24:	DB	'INPUT?',CR
78	4087 3E0D		
79	4089 45584543 M25:	DB	'EXED?',CR
79	408D 3E0D		
80	408F 44455354 M27:	DB	'DEST?',CR
80	4093 3E0D		
81	4093 44415441 M28:	DB	'DATA?',CR
81	4099 3E0D		
82	409B 20484C20 M29:	DB	'HL DE',CR
82	409F 20204445		
82	40A3 202020		
83	40A6 42432020	DB	'BC AF RI',CR
83	40AA 20414620		
83	40AE 20205249		
83	40B2 0D		
84	40B3 20495820 M30:	DB	IY IY
84	40B7 20204959		
84	40BB 202020		
85	40BE 53502020	DB	'SP PC',CR
85	40C2 20504300		
86			
87	40C6 560000 FLAG:	DB	'V',0,0

88	40C9 00000000	DB	0,0,0,0	
89				
90		; List field widths		
91				
92	40CD 3C19	COMMWIDTH:	DB	60,25
93	40CF 0007	SYMWIDTH:	DB	12,7
94	40D1 0505		DB	5,5
95	40D3 1200		DB	18,12
96	40D5 1901		DB	25,1
97				
98	40D7 0000	PAGENO:	DW	0
99	40D9 0000	LCT:	DW	0
100	40DB 7FAB	LIMIT:	DW	0AB7FH
101	40DD 0000	CURRENT:	DW	0
102	40DF 0060	SDFP:	DW	AEND+1733
103	40E1 0060	EOFP:	DW	AEND+1733
104	40E3 0000	NDEF:	DW	0
105	40E5 0000	UDEF:	DW	0
106	40E7 0000	TEMP:	DW	0
107	40E9 0000	FEF:	DW	0
108	40EB 0000	STK:	DW	0
109	40ED 0000	LBLP:	DW	0
110	40EF 0000	FC:	DW	0
111	40F1 0000	OBJ:	DW	0
112	40F3 0000	BKPTADDR:	DW	0
113	40F5 00	BKPTCODE:	DB	0
114	40F6 C3	VECTOR:	DB	0C3H
115	40F7 0340		DW	REENTRY
116	40F9 0000	DSTART:	DW	0
117	40FB 0000	DSTOP:	DW	0
118	40FD 0000	DIP:	DW	0
119	40FF 0000	DRSTART:	DW	0
120	4101 0000	DRSTOP:	DW	0
121	4103 0000	DRIP:	DW	0
122	4105 0000	DECAF:	DW	0
123	4107 3D5A	DSOSP:	DW	AEND+258
124	4109 0000	DEOSP:	DW	0
125	410B 0030	CRBUFF:	DW	3000H
126	410D 0038	CWBUFF:	DW	3800H
127				
128		USTK:	DS	40
129	4137 0000	IMAGE:	DW	0
130	4139 0000		DW	0
131	413B 0000		DW	0
132	413D 0000		DW	0
133	413F 0000		DW	0
134	4141 0000		DW	0
135	4143 0000		DW	0
136	4145 857F		DW	7FB5H
137	4147 8C8D		DW	8D8CH
138	4149 0000		DW	0
139	414B 0000		DW	0
140	414D 31	EXIT:	DB	31H
141	414E 3741	USP:	DW	IMAGE
142	4150 FB		EI	
143	4151 C3		DS	0C3H
144	4152 0000	UPC:	DW	0
145				
146		TBUFF:	DS	140
147		STACK:	DS	0

143			
149			; ZEN Mainloop
150			
151	41E0 31E041	ZEN:	LD SP,STACK
152	41E3 FB		EI
153	41E4 DD21C640		LD IX,FLAGS
154	41E8 CD7042		CALL TOP
155	41EB 21EB41		LD HL,\$
156	41EE ES		PUSH HL
157	41EF ED73EB40		LD (STK),SP
158	41F3 DD360056		LD (IX+F1),V
159	41F7 2E06		LD L,M13255
160	41F9 CDAC46		CALL CUE
161	41FC 0D		DEC C
162	41FD CA2D48		JP Z,CLEAR
163	4200 FE53		CP 'S'
164	4202 CA1B44		JP Z,BORT
165	4205 FE57		CP 'W'
166	4207 CA4643		JP Z,WRITE
167	420A FE4C		CP 'L'
168	420C 2824		JR Z,LOCATE
169	420E ES		PUSH HL
170	420F CS		PUSH BC
171	4210 0E01		LD C,1
172	4212 115441		LD DE,TBUFF
173	4215 21C045		LD HL,COMTAB
174	4218 CD1A4B		CALL SEARCH
175	421B DACD47		JP C,E10
176	421E C1		POP BC
177	421F E3		EX (SP),HL
178	4220 41		LD B,C
179	4221 05		DEC B
180	4222 37		SCF
181	4223 2809		JR Z,ZEN2
182	4225 13		INC DE
183	4226 CDD247		CALL CONVERT
184	4229 DACD47		JP C,E10
185	422C 44		LD B,H
186	422D 4D		LD C,L
187	422E 2ADD40	ZEN2:	LD HL,(CURRENT)
188	4231 C9		RET
189			
190	4232 0D	LOCATE:	DEC C
191	4233 CACD47		JP Z,E10
192	4236 2ADD40		LD HL,(CURRENT)
193	4239 CS		PUSH BC
194	423A CD5248		CALL NEXT
195	423D C1		POP BC
196	423E 2B		DEC HL
197	423F ES		PUSH HL
198	4240 E1	LC1:	POP HL
199	4241 7E		LD A,(HL)
200	4242 23		INC HL
201	4243 FE0D		CP CR
202	4245 CCAB48		CALL Z,UPDATE
203	4248 CD0646		CALL EOF
204	424B 41		LD B,C
205	424C 115541		LD DE,TBUFF+1
206	424F ES		PUSH HL
207	4250 1A	LC2:	LD A,(DE)

208	4251	BE	OF	(HL)
209	4252	20EC	JR	NZ,LC1
210	4254	13	INC	DE
211	4255	23	INC	HL
212	4256	10FB	DJNZ	LC2
213	4258	E1	POP	HL
214	4259	CDCE42	CALL	THIS
215	425C	1832	JR	LINE
216				
217	425E	78	UP:	LD A,B
218	425F	B1		OR C
219	4260	282E		JR Z,LINE
220	4262	CDC442		CALL LAST
221	4263	3029		JR NC,LINE
222	4267	0B		DEC BC
223	4268	18F4		JR UP
224				
225	426A	2ADF40	KILL:	LD HL,(SOFP)
226	426D	22E140		LD (EOFPP),HL
227				
228	4270	210100	TOP:	LD HL,1
229	4273	22D940		LD (LCT),HL
230	4276	2ADF40		LD HL,(SOFP)
231	4279	22DD40		LD (CURRENT),HL
232	427C	C9		RET
233				
234	427D	CD7042	TARGET:	CALL TOP
235	4280	0B		DEC BC
236				
237	4281	78	DOWN:	LD A,B
238	4282	B1		OR C
239	4283	280B		JR Z,LINE
240	4285	CS		PUSH BC
241	4286	CD5248		CALL NEXT
242	4289	C1		POP BC
243	428A	CDAB48		CALL UPDATE
244	428D	0B		DEC BC
245	428E	18F1		JR DOWN
246	4290	CD0646	LINE:	CALL EOF
247	4293	CD6048		CALL POSITION
248	4296	C31E46		JP PR3
249				
250	4299	78	ZAP:	LD A,B
251	429A	B1		OR C
252	429B	28F3		JR Z,LINE
253	429D	E5		PUSH HL
254	429E	C5		PUSH BC
255	429F	CD8C47		CALL REMOVE
256	42A2	C1		POP BC
257	42A3	E1		POP HL
258	42A4	0B		DEC BC
259	42A5	18F2		JR ZAP
260				
261	42A7	2E4B	E0:	LD L,M15&255
262	42A9	ED7BEB40	ER:	LD SP,(STK)
263	42AD	CD1846		CALL ERR2
264	42B0	2AE740		LD HL,(TEMP)
265	42B3	010100		LD BC,1
266				
267	42B6	78	PRINT:	LD A,B

268	42B7	B1	DR	C
269	42B8	280A	JR	Z, LAST
270	42BA	CD9042	CALL	LINE
271	42BD	23	INC	HL
272	42BE	CDAB48	CALL	UPDATE
273	42C1	0B	DEC	BC
274	42C2	18F2	JR	PRINT
275				
276	42C4	E5	LAST:	PUSH HL
277	42C5	2AD940	LD	HL, (LCT)
278	42C8	2B	DEC	HL
279	42C9	22D940	LD	(LCT), HL
280	42CC	E1	POP	HL
281	42CD	2B	DEC	HL
282	42CE	CD3248	THIS:	CALL SOF
283	42D1	309D	JR	NC, TOP
284	42D3	2B	DEC	HL
285	42D4	7E	LD	A, (HL)
286	42D5	FE0D	CP	DR
287	42D7	20F5	JR	NZ, THIS
288	42D9	23	INC	HL
289	42DA	22DD40	LD	(CURRENT), HL
290	42DD	37	SCF	
291	42DE	C9	RET	
292				
293	42DF	CD6048	ENTER:	CALL POSITION
294	42E2	EB	EX	DE, HL
295	42E3	CDAF46	CALL	USER
296	42E6	FE2E	CP	'.'
297	42E8	C8	RET	Z
298	42E9	2AE140	LD	HL, (EOFPP)
299	42EC	CD3D48	CALL	MEMCHECK
300	42EF	CD2643	CALL	INSERT
301	42F2	EB	EX	DE, HL
302	42F3	CDAB48	CALL	UPDATE
303	42F6	18E7	JR	ENTER
304				
305	42FB	E5	NEW:	PUSH HL
306	42F9	CD5248	CALL	NEXT
307	42FC	2AE140	LD	HL, (EOFPP)
308	42FF	ED42	SBC	HL, BC
309	4301	E3	EX	(SP), HL
310	4302	E5	PUSH	HL
311	4303	C5	PUSH	BC
312	4304	115441	LD	DE, TBUFF
313	4307	D5	PUSH	DE
314	4308	EDB0	LDIR	
315	430A	E1	POP	HL
316	430B	C1	POP	BC
317	430C	0B	DEC	BC
318	430D	CD6048	CALL	POSITION
319	4310	CDA246	CALL	STR1
320	4313	CD8946	CALL	US1
321	4316	CD2146	CALL	CRLF
322	4319	E1	POP	HL
323	431A	E3	EX	(SP), HL
324	431B	CD3D48	CALL	MEMCHECK
325	431E	E1	POP	HL
326	431F	E5	PUSH	HL
327	4320	C5	PUSH	BC

328	4321	CD8C47		CALL REMOVE
329	4324	C1		POP BC
330	4325	D1		POP DE
331				
332	4326	D5	INSERT:	PUSH DE
333	4327	C5		PUSH BC
334	4328	2AE140		LD HL, (EOFPP)
335	432B	E5		PUSH HL
336	432C	09		ADD HL, BC
337	432D	22E140		LD (EOFPP), HL
338	4330	E3		EX (SP), HL
339	4331	E5		PUSH HL
340	4332	ED52		SBC HL, DE
341	4334	E3		EX (SP), HL
342	4335	C1		POP BC
343	4336	D1		POP DE
344	4337	03		INC BC
345	4338	EDB8		LDDR
346	433A	C1		POF BC
347	433B	D1		POP DE
348	433C	215441		LD HL, TBUFF
349	433F	EDB0		LDIR
350	4341	C9		RET
351				
352	4342	31F8BF	BYE:	LD SP, 0BFFBH
353	4345	C9		RET
354				
355	4346	0D	WRITE:	DEC C
356	4347	2B27		JR Z, WSOURCE
357	4349	CDBD47	WBIN:	CALL STARTSTOP
358	434C	E5		PUSH HL
359	434D	D5		PUSH DE
360	434E	2E89		LD L, M25&255
361	4350	CDA847		CALL PARAMETER
362	4353	E5		PUSH HL
363	4354	CDFB46		CALL WOPEN
364	4357	C1		POP BC
365	4358	E1		POP HL
366	4359	D1		POP DE
367	435A	3E02		LD A, 2
368	435C	DDE5		PUSH IX
369	435E	CD98BC		CALL CODIR
370	4361	DDE1		POP IX
371	4363	3008		JR NC, WB4
372	4365	DDE5	WB3:	PUSH IX
373	4367	CD8FB0		CALL COCLOSE
374	436A	DDE1		POP IX
375	436C	D8		RET C
376	436D	C392BC	WB4:	JP COABAN
377				
378	4370	2AE140	WSOURCE:	LD HL, (EOFPP)
379	4373	ED5BDF40		LD DE, (SOPP)
380	4377	B7		OR A
381	4378	ED52		SBC HL, DE
382	437A	CACD47		JP Z, E10
383	437D	E5		PUSH HL
384	437E	D5		PUSH DE
385	437F	CDFB46		CALL WOPEN
386	4382	E1		POP HL
387	4383	C1		POP BC

388 4384 7E	WS2:	LD A, (HL)
389 4385 FE0D		CP CR
390 4387 2007		JR NZ, WS3
391 4389 CDEB46		CALL WCHAR
392 438C 30DF		JR NC, WB4
393 438E 3E0A		LD A, LF
394 4390 CDEB46	WS3:	CALL WCHAR
395 4393 3008		JR NC, WB4
396 4395 23		INC HL
397 4396 0B		DEC BC
398 4397 78		LD A, B
399 4398 B1		OR C
400 4399 20E9		JR NZ, WS2
401 439B 18C8		JR WB3
402		
403 439D F5	READ:	PUSH AF
404 439E C5		PUSH BC
405 439F CD0A47		CALL ROPEN
406 43A2 E1		POP HL
407 43A3 C1		POP BC
408 43A4 F5		PUSH AF
409 43A5 C5		PUSH BC
410 43A6 F1		POP AF
411 43A7 3001		JR NC, RD2
412 43A9 EB		EX DE, HL
413 43AA F1	RD2:	POP AF
414 43AB 3017		JR NC, RB4
415 43AD FE16		CP 16H
416 43AF 2816		JR Z, RSOURCE
417 43B1 FE02		CP 2
418 43B3 200F		JR NZ, RB4
419 43B5 DDE5		PUSH IX
420 43B7 CD83BC		CALL CIDIR
421 43B8 DDE1		POP IX
422 43BC 3006		JR NC, RB4
423 43BE 225241		LD (UPC), HL
424 43C1 C37ABC		JP CICLOSE
425 43C4 C37DBC	RB4:	JP CIABAN
426		
427 43C7 2AE140	RSOURCE:	LD HL, (EOFPP)
428 43CA CDF346	RS2:	CALL RCHAR
429 43CD 301F		JR NC, RS4
430 43CF FE0A		CP LF
431 43D1 28F7		JR Z, RS2
432 43D3 EB		EX DE, HL
433 43D4 CD4E48		CALL MEMTOP
434 43D7 B7		OR A
435 43D8 ED52		SBC HL, DE
436 43DA EB		EX DE, HL
437 43DB 300D		JR NC, RS3
438 43DD 2B		DEC HL
439 43DE 22E140		LD (EOFPP), HL
440 43E1 2B		DEC HL
441 43E2 360D		LD (HL), DR
442 43E4 CDC443		CALL RB4
443 43E7 C34948		JP E20
444 43EA 77	RS3:	LD (HL), A
445 43EB 23		INC HL
446 43EC 18DC		JR RS2
447 43EE 2BD4	RS4:	JR Z, RB4

448	43F0	22E140		LD	(EOF),HL
449	43F3	C37ABC		JP	CICLOSE
450					
451	43F6	CD65BC	CATALOG:	CALL	CINIT
452	43F9	ED5B0841		LD	DE,(CRBUFF)
453	43FD	DDE5		PUSH	IX
454	43FF	CD9BBC		CALL	CCAT
455	4402	DDE1		POP	JX
456	4404	18BE		JR	RB4
457					
458	4406	2ADF40	HOWBIG:	LD	HL,(SUFF)
459	4409	CD8D40		CALL	WORDSP
460	440C	2AE140		LD	HL,(EOF)
461	440F	CD8D48		CALL	WORDSP
462	4412	CD4E48		CALL	MEMTOP
463	4415	CD8D48		CALL	WORDSP
464	4418	C32146		JP	CRLF
465					
466	441B	212146	SORT:	LD	HL,CRLF
467	441E	E5		PUSH	HL
468	441F	3A5541		LD	A,(TBUFF+1)
469	4422	F5		PUSH	AF
470	4423	CD1C49		CALL	GETOPTION
471	4426	DD360201		LD	(IX+F3),L
472	442A	F1		POP	AF
473	442B	4F		LD	C,A
474	442C	FE0D		CP	CR
475	442E	200B		JR	NZ,SCAN
476	4430	0E41		LD	C,A'
477	4432	CD3B44	SRT2:	CALL	SCAN
478	4435	0C		INC	C
479	4436	79		LD	A,C
480	4437	FE5A		CP	'Z'
481	4439	20F7		JR	NZ,SRT2
482	443B	213A59	SCAN:	LD	HL,AEND--1
483	443E	23	SCN1:	INC	HL
484	443F	23	SCN2:	INC	HL
485	4440	7E		LD	A,(HL)
486	4441	3C		INC	A
487	4442	CB		RET	Z
488	4443	CD3149		CALL	HOLD
489	4446	0600		LD	B,0
490	4448	54		LD	D,H
491	4449	5D		LD	E,L
492	444A	04	SCN3:	INC	B
493	444B	CB7E		BIT	7,(HL)
494	444D	23		INC	HL
495	444E	28FA		JR	Z,SCN3
496	4450	1A		LD	A,(DE)
497	4451	CDBF		RES	7,A
498	4453	B9		CP	C
499	4454	20E8		JR	NZ,SCN1
500	4456	DD3502		DEC	(IX+F3)
501	4459	2015		JR	NZ,SCN4
502	445B	CD2146		CALL	CRLF
503	445E	DD360204		LD	(IX+F3),4
504	4462	DDCB004E		BIT	1,(IX+F1)
505	4466	2803		JR	Z,SCN31
506	4468	DD3502		DEC	(IX+F3)
507	446B	D5	SCN31:	PUSH	DE

508 446C CD1847		CALL PAGE
509 446F D1		POP DE
510 4470 EB	SCN4:	EX DE,HL
511 4471 C5		PUSH BC
512 4472 D5		PUSH DE
513 4473 S0		LD D,B
514 4474 0E7F		LD C,7FH
515 4476 CDA44A		CALL SYMFIELD
516 4479 E1		POP HL
517 447A C1		POP BC
518 447B 5E		LD E,(HL)
519 447C 23		INC HL
520 447D 56		LD D,(HL)
521 447E EB		EX DE,HL
522 447F CD8D48		CALL WORDSP
523 4482 EB		EX DE,HL
524 4483 18BA		JR SCN2
525		
526 4485 3804	GOTO:	JR C,GOT2
527 4487 ED435241		LD (UPC),BC
528 448B 2EB3	GOT2:	LD L,M24 &255
529 448D CDA847		CALL PARAMETER
530 4490 381A		JR C,GOT3
531 4492 22F340		LD (BKPTADDR),HL
532 4495 7E		LD A,(HL)
533 4496 32F540		LD (BKPTCODE),A
534 4499 3EF7		LD A,0F7H
535 449B 77		LD (HL),A
536 449C BE		CP (HL)
537 449D C24948		JP NZ,E20
538 44A0 21F640		LD HL,VECTOR
539 44A3 113000		LD DE,30H
540 44A6 010300		LD BC,3
541 44A9 CD1BB9		CALL BMIR
542 44AC F3	GOT3:	DI
543 44AD 313741		LD SP,IMAGE
544 44B0 E1		POP HL
545 44B1 D1		POP DE
546 44B2 C1		POP BC
547 44B3 F1		POP AF
548 44B4 08		EX AF,AF
549 44B5 D9		EXX
550 44B6 C1		POP BC
551 44B7 79		LD A,C
552 44B8 ED47		LD I,A
553 44B9 78		LD A,B
554 44B8 ED4F		LD R,A
555 44BD E1		POP HL
556 44BE D1		POP DE
557 44BF C1		POP BC
558 44C0 F1		POP AF
559 44C1 D9		EXX
560 44C2 08		EX AF,AF
561 44C3 DDE1		POP IX
562 44C5 FDE1		POP IY
563 44C7 C34D41		JP EXIT
564		
565 44CA CDBD47	COPY:	CALL STARTSTOP
566 44CD E5		PUSH HL
567 44CE 2EBF		LD L,M27 &255

568	44D0	CDA847		CALL	PARAMETER
569	44D3	EB		EX	DE,HL
570	44D4	C1		POP	BC
571	44D5	EDB0		LDIR	
572	44D7	C9		RET	
573					
574	44D8	CDBD47	FILL:	CALL	STARTSTOP
575	44DB	ES		PUSH	HL
576	44DC	2E95		LD	L,M2B &255
577	44DE	CDA847		CALL	PARAMETER
578	44E1	EB		EX	DE,HL
579	44E2	C1		POP	BC
580	44E3	73	FIL2:	LD	(HL),E
581	44E4	23		INC	HL
582	44E5	0B		DEC	BC
583	44E6	78		LD	A,B
584	44E7	B1		OR	C
585	44E8	20F9		JR	NZ,FIL2
586	44EA	C9		RET	
587					
588	44EB	3804	MODIFY:	JR	C,MOD1
589	44ED	ED43E340		LD	(MDEF),BC
590	44F1	2AE340	MOD1:	LD	HL,(MDEF)
591	44F4	CD2146	MOD2:	CALL	CRLF
592	44F7	CD8D48		CALL	WORDSP
593	44FA	22E340	MOD3:	LD	(MDEF),HL
594	44FD	7E		LD	A,(HL)
595	44FE	CD9248		CALL	BYTESP
596	4501	EB		EX	DE,HL
597	4502	CDB346		CALL	US0
598	4505	FE2E		CP	' '
599	4507	CA2146		JP	Z,CRLF
600	450A	C5		PUSH	BC
601	450B	CDA847		CALL	PARAM1
602	450E	C1		POP	BC
603	450F	EB		EX	DE,HL
604	4510	3810		JR	C,MOD5
605	4512	73		LD	(HL),E
606	4513	79		LD	A,C
607	4514	C602		ADD	A,2
608	4516	47		LD	B,A
609	4517	3E08	MOD4:	LD	A,BS
610	4519	CD3046		CALL	OUTPUT
611	451C	10F9		DJNZ	MOD4
612	451E	7E		LD	A,(HL)
613	451F	CD9248		CALL	BYTESP
614	4522	23	MOD5:	INC	HL
615	4523	7D		LD	A,L
616	4524	E607		AND	7
617	4526	28CC		JR	Z,MOD2
618	4528	18D0		JR	MOD3
619					
620	452A	3804	QUERY:	JR	C,QU2
621	452C	ED43E540		LD	(QDEF),BC
622	4530	2AE540	QU2:	LD	HL,(QDEF)
623	4533	7D		LD	A,L
624	4534	E6FB		AND	0F8H
625	4536	6F		LD	L,A
626	4537	0E08		LD	C,8
627	4539	0608	QU3:	LD	B,B

628	453B	E5		PUSH HL
629	453C	CD8D48		CALL WORDSP
630	453F	7E	0U4:	LD A, (HL)
631	4540	CD9248		CALL BYTESP
632	4543	23		INC HL
633	4544	10F9		DJNZ 0U4
634	4546	E1		POP HL
635	4547	CD2E46		CALL SPACE
636	454A	0608		LD B,8
637	454C	7E	0U5:	LD A, (HL)
638	454D	FE20		CP BLANK
639	454F	3002		JR NC,0U7
640	4551	3E2E		LD A, .
641	4553	CD3046	0U7:	CALL OUTPUT
642	4556	23		INC HL
643	4557	10F3		DJNZ 0U5
644	4559	CD2146		CALL CRLF
645	455C	0D		DEC C
646	455D	20DA		JR NZ,0U3
647	455F	22E540		LD (QDEF),HL
648	4562	C9		RET
649				
650	4563	212146	XAMINE:	LD HL,CRLF
651	4566	E5		PUSH HL
652	4567	2E9B		LD L,M29&255
653	4569	CD1046		CALL PR2
654	456C	213741		LD HL,IMAGE
655	456F	0605		LD B,5
656	4571	CD9245		CALL PAIR
657	4574	CD2146		CALL CRLF
658	4577	0604		LD B,4
659	4579	CD9245		CALL PAIR
660	457C	CD2146		CALL CRLF
661	457F	E5		PUSH HL
662	4580	2EB3		LD L,M30&255
663	4582	CD1046		CALL PR2
664	4585	E1		POP HL
665	4586	0602		LD B,2
666	4588	CD9245		CALL PAIR
667	458B	23		INC HL
668	458C	CD9145		CALL ONEPAIR
669	458F	23		INC HL
670	4590	23		INC HL
671	4591	04	ONEPAIR:	INC B
672	4592	5E	PAIR:	LD E, (HL)
673	4593	23		INC HL
674	4594	56		LD D, (HL)
675	4595	23		INC HL
676	4596	EB		EX DE,HL
677	4597	CD8D48		CALL WORDSP
678	459A	EB		EX DE,HL
679	459B	10F5		DJNZ PAIR
680	459D	C9		RET
681				
682	459E	C5	OUTPORT:	PUSH BC
683	459F	2E95		LD L,M28&255
684	45A1	CDA847		CALL PARAMETER
685	45A4	C1		POP BC
686	45A5	ED69		OUT (C),L
687	45A7	C9		RET

688

689	45AB ED78	INPORT:	IN	A, (C)
690	45AA F5		PUSH	AF
691	45AB CD9248		CALL	BYTESP
692	45AE F1		POP	AF
693	45AF 0E08		LD	B,B
694	45B1 07	IN2:	RLCA	
695	45B2 F5		PUSH	AF
696	45B3 E601		AND	I
697	45B5 C630		ADD	A, '0'
698	45B7 CD3046		CALL	OUTPUT
699	45BA F1		POP	AF
700	45BB 10F4		DJNZ	IN2
701	45BD 032146		JP	ORLF
702				
703	45C0 D5	COMTAB:	DB	'U'.S
704	45C1 5E42		DW	UP
705	45C3 C9		DB	'1'.S
706	45C4 A845		DW	TINPORT
707	45C6 CF		DB	'0'.S
708	45C7 9E45		DW	OUTPORT
709	45C9 D1		DB	'0'.S
710	45CA 2A45		DW	QUERY
711	45CC D2		DB	'R'.S
712	45CD 9D43		DW	READ
713	45CF C2		DB	'B'.S
714	45D0 4243		DW	BYE
715	45D2 CD		DB	'M'.S
716	45D3 EB44		DW	MODIFY
717	45D5 C6		DB	'F'.S
718	45D6 D844		DW	FILL
719	45D8 C3		DB	'G'.S
720	45D9 C944		DW	COPY
721	45DB C7		DB	'G'.S
722	45DC B544		DW	GOTO
723	45DE D8		DB	'X'.S
724	45DF 6345		DW	XAMINE
725	45E1 C1		DB	'A'.S
726	45E2 B848		DW	ASMB
727	45E4 CB		DB	'K'.S
728	45E5 6A42		DW	KILL
729	45E7 C8		DB	'H'.S
730	45E8 0E44		DW	HOWBIG
731	45EA C5		DB	'E'.S
732	45EB DF42		DW	ENTER
733	45ED D4		DB	'T'.S
734	45EE 7D42		DW	TARGET
735	45F0 CE		DB	'N'.S
736	45F1 F842		DW	NEW
737	45F3 C4		DB	'D'.S
738	45F4 B142		DW	DOWN
739	45F6 DA		DB	'Z'.S
740	45F7 9942		DW	ZAP
741	45F9 D0		DB	'P'.S
742	45FA B642		DW	PRINT
743	45FC E3		DB	'c'.S
744	45FD F643		DW	CATALOG
745	45FF E4		DB	'd'.S
746	4600 0E52		DW	DASM
747	4602 F5		DB	'u'.S

748	4603 AF52		DW	UNSCRAMBLE
749	4605 FF		DB	0FFH
750				
751	4606 D5	EOF:	PUSH	DE
752	4607 EB		EX	DE,HL
753	4608 2AE140		LD	HL,(EOF#)
754	460B 2B		DEC	HL
755	460C B7		OR	A
756	460D ED52		SBC	HL,DE
757	460F EB		EX	DE,HL
758	4610 D1		POP	DE
759	4611 D0		RET	NC
760	4612 2E15		LD	L,M5&255
761				
762	4614 ED7BEB40	ERR:	LD	SP,(STK)
763	4618 DD360056	ERR2:	LD	(IX+F1), 'V'
764				
765	461C 2640	PR2:	LD	H,M1/256
766	461E CDA246	PR3:	CALL	STR1
767	4621 F5	CRLF:	PUSH	AF
768	4622 3E00		LD	A,CR
769	4624 CD3046		CALL	OUTPUT
770	4627 3E0A		LD	A,LF
771	4629 CD3046		CALL	OUTPUT
772	462C F1		POP	AF
773	462D C9		RET	
774				
775	462E 3E20	SPACE:	LD	A,BLANK
776				
777	4630 DDCB004E	OUTPUT:	BIT	1,(IX+F1)
778	4634 2811		JR	Z,EXTERN
779				
780	4636 FE08	VIDEO:	CP	BS
781	4638 200A		JR	NZ,VID2
782	463A CD4446		CALL	VID2
783	463D 3E20		LD	A,BLANK
784	463F CD4446		CALL	VID2
785	4642 3E08		LD	A,BS
786	4644 C35ABB	VID2:	JP	TXTOUT
787				
788	4647 00000000	EXTERN:	DB	0,0,0,0
789	4648 00000000		DB	0,0,0,0
790	464F 00000000		DB	0,0,0,0
791	4653 00000000		DB	0,0,0,0
792	4657 00000000		DB	0,0,0,0
793	465B 00000000		DB	0,0,0,0
794	465F 00000000		DB	0,0,0,0
795	4663 00000000		DB	0,0,0,0
796	4667 00000000		DB	0,0,0,0
797	466B 00000000		DB	0,0,0,0
798	466F 00000000		DB	0,0,0,0
799	4673 F5		PUSH	AF
800	4674 CD2EBD	EXT2:	CALL	PBUSY
801	4677 38FB		JR	C,EXT2
802	4679 F1		POP	AF
803	467A C331BD		JP	PSEND
804				
805	467D CD81BB	KEYBOARD:	CALL	CURON
806	4680 CD06BB	KB2:	CALL	WAITCHAR
807	4683 FE7F		CP	DEL

808	4685	2002		JR	NZ,KB22
809	4687	3E08		LD	A,BS
810	4689	FE0D	KB22:	CP	CR
811	468B	2810		JR	Z,KB3
812	468D	FE08		CP	BS
813	468F	280C		JR	Z,KB3
814	4691	FE20		CP	BLANK
815	4693	38EB		JR	C,KB2
816	4695	FEFC		CP	0FCH
817	4697	28E7		JR	Z,KB2
818	4699	FEFF		CP	0EFFH
819	469B	28E3		JR	Z,KB2
820	469D	C384BB	KB3:	JP	CUROFF
821					
822	46A0	2640	STRING:	LD	H,M1/256
823	46A2	7E	STR1:	LD	A,(HL)
824	46A3	FE0D		CP	CR
825	46A5	C8		RET	Z
826	46A6	CD3046		CALL	OUTPUT
827	46A9	23		INC	HL
828	46AA	18F6		JR	STR1
829					
830	46AC	CDA046	CUE:	CALL	STRING
831	46AF	212146	USER:	LD	HL,CRLF
832	46B2	E5		PUSH	HL
833	46B3	215441	US0:	LD	HL,TBUFF
834	46B6	010000		LD	BC,0
835	46B9	CD7D46	US1:	CALL	KEYBOARD
836	46BC	77		LD	(HL),A
837	46BD	FE08		CP	BS
838	46BF	2007		JR	NZ,US2
839	46C1	0D		DEC	C
840	46C2	FAB346		JP	M,US0
841	46C5	2B		DEC	HL
842	46C6	1810		JR	US4
843	46C8	0C	US2:	INC	C
844	46C9	FE0D		CP	CR
845	46CB	3A5441		LD	A,(TBUFF)
846	46CE	C8		RET	Z
847	46CF	0D		DEC	C
848	46D0	79		LD	A,C
849	46D1	FE22		CP	34
850	46D3	28E4		JR	Z,US1
851	46D5	7E		LD	A,(HL)
852	46D6	0C		INC	C
853	46D7	23		INC	HL
854	46D8	CD3046	US4:	CALL	OUTPUT
855	46DB	18DC		JR	US1
856					
857	46DD	CD65BC	GETNAME:	CALL	CINIT
858	46E0	2E70		LD	L,M21&255
859	46E2	CDAC46		CALL	CUE
860	46E5	215441		LD	HL,TBUFF
861	46E8	0D		DEC	C
862	46E9	41		LD	B,C
863	46EA	C9		RET	
864					
865	46EB	DDE5	WCHAR:	PUSH	IX
866	46ED	CD95BC		CALL	COCHAR
867	46F0	DDE1		POP	IX

928 46F2 C9		RET
929		
92A 46F3 DDE5	POCHAR	PUSH IX
92B 46F5 CD89EC		CALL CICHAR
92C 46F8 DDE1		POP IX
92D 46F9 C9		RET
92E		
92F 46FB CD9946	WOPEN:	CALL GETNAME
930 46FC ED580D41		LD DE,(CRBUFF)
931 4702 00E0		PUSH IX
932 4704 CD8C8C		CALL COOPEN
933 4707 DDE1	WPE2:	POP IX
934 4709 C9		RET
935		
936 471A C10042	KOPEN:	CALL GETNAME
937 4720 ED580B43		LD DE,(CRBUFF)
938 4721 DDE5		PUSH IX
939 4723 CD77DC		CALL CIOPEN
93A 4726 02E1		JR WPE2
93B		
93C 4726 02C964	PAGE1:	DEC (IX+F5)
93D 4726 C9		RET NZ
93E 472C 313C		LD A,60
93F 472D DDCC8042		BIT 1,(IX+F1)
940 472E 2902		JR Z,PG2
941 472F 3E16		LD A,22
942 472G DD7784	PG2:	LD (IX+F5,A)
943 4729 C01243		CALL DELAY
944 472C E5		PUSH HL
945 472D 2E10		LD L,M4&255
946 472E CDA046		CALL STRING
947 4732 24D948		LD HL,(LCT)
948 4735 E5		PUSH HL
949 4736 24D748		LD HL,(PAGENO)
950 4739 23		INC HL
951 473A 22D748		LD (PAGENO),HL
952 473D 22D948		LD (LCT),HL
953 4740 CD6842		CALL POSITION
954 4743 E1		POP HL
955 4744 32D948		LD (LCT),HL
956 4747 E1		POP HL
957 4748 C02146		CALL CRLF
958 4749 C32146		JP CRLF
959		
960 474E F3	TRIM:	DI
961 474F E5		EX (SP),HL
962 4750 2B		DEC HL
963 4751 225241		LD (UPC),HL
964 4754 E1		POP HL
965 4755 ED734E41		LD (USP),SP
966 4759 314041		LD SP,EXIT
967 475C FDES		PUSH IY
968 475E DDE5		PUSH IX
969 4760 03		EX AF,AF
970 4761 D9		EXX
971 4762 F5		PUSH AF
972 4763 C5		PUSH BC
973 4764 D5		PUSH DE
974 4765 E5		PUSH HL
975 4766 E05F		LD A,R

928	4768	67	LD	H,A
929	4769	ED57	LD	A,I
930	476B	6F	LD	L,A
931	476C	E5	PUSH	HL
932	476D	D9	EXX	
933	476E	08	EX	AF,AF
934	476F	F5	PUSH	AF
935	4770	C5	PUSH	BC
936	4771	D5	PUSH	DE
937	4772	E5	PUSH	HL
938	4773	2AF340	LD	HL,(BKPTADDR)
939	4776	ED5B5241	LD	DE,(UPC)
940	477A	B7	OR	A
941	477B	ED52	SBC	HL,DE
942	477D	2005	JR	NZ,TRAP2
943	477F	3AF540	LD	A,(BKPTCODE)
944	4782	12	LD	(DE),A
945	4783	1B	DEC	DE
946	4784	13	INC	DE
947	4785	ED535241	LD	(UPC),DE
948	4789	C3E041	JP	ZEN
949				
950	478C	E5	REMOVE:	PUSH HL
951	478D	C05242	CALL	NEXT
952	4790	E5	PUSH	HL
953	4791	2AE140	LD	HL,(EOFPP)
954	4794	E5	PUSH	HL
955	4795	B7	OR	A
956	4796	ED42	SBC	HL,BC
957	4798	22E140	LD	(EOFPP),HL
958	479B	E1	POP	HL
959	479C	D1	POP	DE
960	479D	D5	PUSH	DE
961	479E	B7	OR	A
962	479F	ED52	SBC	HL,DE
963	47A1	E3	EX	(SP),HL
964	47A2	C1	POP	BC
965	47A3	D1	POP	DE
966	47A4	C8	RET	Z
967	47A5	EDB0	LDIR	
968	47A7	C9	RET	
969				
970	47AB	CDAC46	PARAMETER:	CALL CUE
971	47AB	41	PARAM1:	LD B,C
972	47AC	05	DEC	B
973	47AD	37	SCF	
974	47AE	C8	RET	Z
975	47AF	D5	PUSH	DE
976	47B0	115441	LD	DE,TBUFF
977	47B3	CDD247	CALL	CONVERT
978	47B6	D1	POP	DE
979	47B7	D0	RET	NC
980	47B8	CD2146	CALL	CRLF
981	47BB	1810	JR	E10
982				
983	47BD	2E76	STARTSTOP:	LD L,M22&255
984	47BF	CDA847	CALL	PARAMETER
985	47C2	EB	EX	DE,HL
986	47C3	2E7D	LD	L,M23&255
987	47C5	CDA847	CALL	PARAMETER

988	47C8	B7		OR	A
989	47C9	ED52		SBC	HL,DE
990	47CB	23		INC	HL
991	47CC	D0		RET	NC
992					
993	47CD	2E0B	E10:	LD	L,M2%255
994	47CF	C31446		JP	ERR
995					
996	47D2	2B	CONVERT:	DEC	HL
997	47D3	7E		LD	A,(HL)
998	47D4	0E10		LD	C,16
999	47D6	FE48		CP	'H'
1000	47D8	2809		JR	Z,CV0
1001	47DA	0E08		LD	C,8
1002	47DC	FE4F		CP	'O'
1003	47DE	2803		JR	Z,CV0
1004	47E0	0E0A		LD	C,10
1005	47E2	04		INC	B
1006	47E3	05	CV0:	DEC	B
1007	47E4	210000		LD	HL,0
1008	47E7	1A	CV1:	LD	A,(DE)
1009	47EB	D530		SUB	48
1010	47EA	FE0A		CP	10
1011	47EC	3805		JR	C,CV2
1012	47EE	D607		SUB	7
1013	47F0	FE0A		CP	10
1014	47F2	D8		RET	C
1015	47F3	B9	CV2:	CP	C
1016	47F4	3F		CCF	
1017	47F5	D8		RET	C
1018	47F6	D5		PUSH	DE
1019	47F7	5D		LD	E,L
1020	47F8	54		LD	D,H
1021	47F9	CB49		BIT	1,C
1022	47FB	2008		JR	NZ,CV3
1023	47FD	110000		LD	DE,0
1024	4800	CB59		BIT	3,C
1025	4802	2001		JR	NZ,CV3
1026	4804	29		ADD	HL,HL
1027	4805	29	CV3:	ADD	HL,HL
1028	4806	29		ADD	HL,HL
1029	4807	19		ADD	HL,DE
1030	4808	29		ADD	HL,HL
1031	4809	5F		LD	E,A
1032	480A	1600		LD	D,0
1033	480C	19		ADD	HL,DE
1034	480D	D1		POP	DE
1035	480E	13		INC	DE
1036	480F	10D6		DJNZ	CV1
1037	4811	C9		RET	
1038					
1039	4812	11C832	DELAY:	LD	DE,13000
1040	4815	C03149	DEL1:	CALL	HOLD
1041	4818	1B		DEC	DE
1042	4819	7A		LD	A,D
1043	481A	B3		OR	E
1044	481B	20F8		JR	NZ,DEL1
1045	481D	DDCB005E		BIT	3,(IX+F1)
1046	4821	CC7D46		CALL	Z,KEYBOARD
1047	4824	FE51		CP	'Q'

1048 4826 CAE041		JP Z,ZEN
1049 4829 DDCB00DE		SET 3,(IX+F1)
1050 482D 3E0C	CLEAR:	LD A,FF
1051 482F C33046		JP OUTPUT
1052		
1053 4832 D5	SOF:	PUSH DE
1054 4833 EB		EX DE,HL
1055 4834 2ADF40		LD HL,(SOFP)
1056 4837 B7		OR A
1057 4838 ED52		SBC HL,DE
1058 483A EB		EX DE,HL
1059 483B D1		POP DE
1060 483C C9		RET
1061		
1062 483D D5	MEMCHECK:	PUSH DE
1063 483E 09		ADD HL,BC
1064 483F EB		EX DE,HL
1065 4840 CD4E48		CALL MEMTOP
1066 4843 B7		OR A
1067 4844 ED52		SBC HL,DE
1068 4846 EB		EX DE,HL
1069 4847 D1		POP DE
1070 4848 D0		RET NC
1071 4849 2E69	E20:	LD L,M20&255
1072 484B C31446		JP ERR
1073		
1074 484E 2ADB40	MEMTOP:	LD HL,(LJMIT)
1075 4851 C9		RET
1076		
1077 4852 CD0646	NEXT:	CALL EOF
1078 4855 010000	NX0:	LD BC,0
1079 4858 7E	NX1:	LD A,(HL)
1080 4859 23		INC HL
1081 485A 03		INC BC
1082 485B FE0D		CP CR
1083 485D 20F9		JR NZ,NX1
1084 485F C9		RET
1085		
1086 4860 E5	POSITION:	PUSH HL
1087 4861 C5		PUSH BC
1088 4862 217841		LD HL,TBUFF+36
1089 4865 E5		PUSH HL
1090 4866 0605		LD B,S
1091 4868 3620	POS1:	LD (HL),BLANK
1092 486A 23		INC HL
1093 486B 10FB		DJNZ POS1
1094 486D 360D		LD (HL),CR
1095 486F EB		EX DE,HL
1096 4870 1B		DEC DE
1097 4871 010A00		LD BC,10
1098 4874 2AD940		LD HL,(LCT)
1099 4877 1B	POS2:	DEC DE
1100 4878 D5		PUSH DE
1101 4879 EB		EX DE,HL
1102 487A CD464C		CALL MA50
1103 487D 7B		LD A,E
1104 487E D1		POP DE
1105 487F C630		ADD A,'0'
1106 4881 12		LD (DE),A
1107 4882 7D		LD A,L

1108	4883	B4		OR	H
1109	4884	20F1		JR	NZ,POS2
1110	4886	E1		POP	HL
1111	4887	CDA246		CALL	STR1
1112	488A	C1		POP	BC
1113	488B	E1		POP	HL
1114	488C	C9		RET	
1115					
1116	488D	7C	WORDSP:	LD	A,H
1117	488E	CD9748		CALL	BYTE
1118	4891	7D		LD	A,L
1119	4892	E5	BYTESP:	PUSH	HL
1120	4893	212E46		LD	HL,SPACE
1121	4896	E3		EX	(SP),HL
1122	4897	F5	BYTE:	PUSH	AF
1123	4898	0F		RRCA	
1124	4899	0F		RRCA	
1125	489A	0F		RRCA	
1126	489B	0F		RRCA	
1127	489C	CDA048		CALL	NYB
1128	489F	F1		POP	AF
1129	48A0	E60F	NYB:	AND	0FH
1130	48A2	C690		ADD	A,90H
1131	48A4	27		DAA	
1132	48A5	CE40		ADC	A,40H
1133	48A7	27		DAA	
1134	48A8	C33046		JP	OUTPUT
1135					
1136	48AB	22DD40	UPDATE:	LD	(CURRENT),HL
1137	48AE	E5	LINC:	PUSH	HL
1138	48AF	2AD940		LD	HL,(LCT)
1139	48B2	23		INC	HL
1140	48B3	22D940		LD	(LCT),HL
1141	48B6	E1		POP	HL
1142	48B7	C9		RET	
1143					
1144			; Table lengths		
1145					
1146			JL:	EQU	3
1147			CL:	EQU	1
1148			TL:	EQU	16
1149			LL:	EQU	21
1150			AL:	EQU	2
1151			SBL:	EQU	2
1152			ADL:	EQU	4
1153			INL:	EQU	3
1154			DL:	EQU	3
1155			XL:	EQU	4
1156					
1157			; Register pair identifiers		
1158					
1159			IBC:	EQU	0
1160			IDE:	EQU	2
1161			IHL:	EQU	4
1162			IAF:	EQU	0EH
1163			ISP:	EQU	6
1164					
1165			; Tiny register IDs		
1166					
1167			IB:	EQU	0

1168	IC:	EQU 1
1169	ID:	EQU 2
1170	IE:	EQU 3
1171	IH:	EQU 4
1172	IL:	EQU 5
1173	IA:	EQU 7
1174		
1175	IIX:	EQU 0DDH
1176	IY:	EQU 0FDH
1177		
1178	IREF:	EQU 8
1179	IINT:	EQU 0
1180		
1181	; Condition code IDs	
1182		
1183	ICY:	EQU 18H
1184	INCY:	EQU 10H
1185	IZ:	EQU 8
1186	INZ:	EQU 0
1187	IPO:	EQU 20H
1188	IPE:	EQU 28H
1189	IMIN:	EQU 38H
1190	IPOS:	EQU 30H
1191		
1192	; Parser primary IDs	
1193		
1194	TR:	EQU 0
1195	TRI:	EQU 4
1196	RP:	EQU 1
1197	RPI:	EQU 5
1198	XY:	EQU 2
1199	XYI:	EQU 6
1200	NO:	EQU 3
1201	NOI:	EQU 7
1202	RE:	EQU 8
1203	CC:	EQU 9
1204	XYD:	EQU 10
1205	EOL:	EQU 11
1206	TNO:	EQU 12
1207	TNOI:	EQU 13
1208		
1209	; Parser intermediate IDs	
1210		
1211	TALPHA:	EQU 30H
1212	TLAB:	EQU 31H
1213	TOFD:	EQU 32H
1214	TCOM:	EQU 33H
1215	TIND:	EQU 34H
1216	TADD:	EQU 40H
1217	TSUB:	EQU 0C0H
1218	TMUL:	EQU 80H
1219	TDIV:	EQU 81H
1220	TAND:	EQU 82H
1221	TOR:	EQU 83H
1222	TDEF:	EQU 35H
1223	TLIT:	EQU 36H
1224		
1225	; Assembler	
1226		
1227	48B88 CD1C49	ASMB: CALL GETOPTION

1228 48BB 213C59		LD	HL,AEND+1
1229 48BE 36FF		LD	(HL),0FFH
1230 48C0 22E940		LD	(FEP),HL
1231 48C3 CDCA48		CALL	PASS
1232 48C6 DDCB00AE		RES	5,(IX+F1)
1233 48CA CD7042	PASS:	CALL	TOP
1234 48CD CD3149	PS1:	CALL	HOLD
1235 48D0 2ADD40		LD	HL,(CURRENT)
1236 48D3 22E740		LD	(TEMP),HL
1237 48D6 2AEF40		LD	HL,(PC)
1238 48D9 E5		PUSH	HL
1239 48DA 210000		LD	HL,0
1240 48DD 22C740		LD	(FLAGS+F2),HL
1241 48E0 22CB40		LD	(FLAGS+F6),HL
1242 48E3 CD0A4D		CALL	CLASS
1243 48E6 FE31		CP	TLAB
1244 48E8 CC4149		CALL	Z,SYMBOL
1245 48EB FE0B		CP	EOL
1246 48ED 2819		JR	Z,PS2
1247 48EF FE30		CP	TALPHA
1248 48F1 2024		JR	NZ,E1
1249 48F3 CDFB4A		CALL	OPTSCH
1250 48F6 381F		JR	C,E1
1251 48F8 DD7105		LD	(IX+F6),C
1252 48FB CD9549		CALL	JUMP
1253 48FE C25048		JP	NZ,E6
1254 4901 CD9B4B		CALL	PARSER
1255 4904 FE0B		CP	EOL
1256 4906 200F		JR	NZ,E1
1257 4908 E1	PS2:	POP	HL
1258 4909 DDCB006E		BIT	5,(IX+F1)
1259 490D CC0F4A		CALL	Z,LIST
1260 4910 CDAE48		CALL	LINC
1261 4913 04		INC	B
1262 4914 20B7		JR	NZ,PS1
1263 4916 C9		RET	
1264			
1265 4917 2E0B	E1:	LD	L,M2&255
1266 4919 C3A942		JP	ER
1267			
1268 491C 2E19	GETOPTION:	LD	L,M7&255
1269 491E CDAC46		CALL	CUE
1270 4921 F6B8		OR	0BBH
1271 4923 DD7700		LD	(IX+F1),A
1272 4926 DD360401		LD	(IX+F5),1
1273 492A 210000		LD	HL,0
1274 492D 22D740		LD	(PAGENO),HL
1275 4930 C9		RET	
1276			
1277 4931 CD09BB	HOLD:	CALL	READCHAR
1278 4934 D0		RET	NC
1279 4935 DDCB0076		BIT	6,(IX+F1)
1280 4939 CAE041		JP	Z,ZEN
1281 493C DDCB009E		RES	3,(IX+F1)
1282 4940 C9		RET	
1283			
1284 4941 DDCB01CE	SYMBOL:	SET	1,(IX+F2)
1285 4945 0C		INC	C
1286 4946 DD7106		LD	(IX+F7),C
1287 4949 0D		DEC	C

1288	494A	CAA742	JP	Z,E0	
1289	494D	CDEB4A	CALL	SYMSCH	
1290	4950	FD22ED40	LD	(LBLP),IY	
1291	4954	DDCB006E	BIT	S,(IX+F1)	
1292	4958	2838	JR	Z,SY2	
1293	495A	2E44	LD	L,M13&255	
1294	495C	D2A942	JP	NC,ER	
1295	495F	CDED4A	CALL	QFDSCB	
1296	4962	2E36	LD	L,M12&255	
1297	4964	D2A942	JP	NC,ER	
1298	4967	2AE940	LD	HL,(FEP)	
1299	496A	E5	PUSH	HL	
1300	496B	0600	LD	B,0	
1301	496D	09	ADD	HL,BC	
1302	496E	23	INC	HL	
1303	496F	23	INC	HL	
1304	4970	23	INC	HL	
1305	4971	CD3248	CALL	SOF	
1306	4974	2E3F	LD	L,M14&255	
1307	4976	DAA942	JP	C,ER	
1308	4979	E1	POP	HL	
1309	497A	EB	EX	DE,HL	
1310	497B	E0B0	LDIR		
1311	497D	EB	EX	DE,HL	
1312	497E	2B	DEC	HL	
1313	497F	CBFE	SET	7,(HL)	
1314	4981	C1	POP	BC	
1315	4982	D1	POP	DE	
1316	4983	D5	PUSH	DE	
1317	4984	C5	PUSH	BC	
1318	4985	23	INC	HL	
1319	4986	73	LD	(HL),E	
1320	4987	23	INC	HL	
1321	4988	72	LD	(HL),0	
1322	4989	22ED40	LD	(LBLP),HL	
1323	498C	23	INC	HL	
1324	498D	36FF	LD	(HL),0FFF	
1325	498F	22E940	LD	(FEP),HL	
1326	4992	C30A4D	SY2:	JP	CLASS
1327					
1328	4995	44	JUMP:	LD	B,H
1329	4996	CB7D		BIT	7,L
1330	4998	2004		JR	NZ,JP2
1331	499A	DDCB01DE		SET	3,(IX+F2)
1332	499E	CBBD	JP2:	RES	7,L
1333	49A0	5D		LD	E,L
1334	49A1	1600		LD	D,0
1335	49A3	7D		LD	A,L
1336	49A4	21D749		LD	HL,JPTAB
1337	49A7	19		ADD	HL,DE
1338	49AB	5E		LD	E,(HL)
1339	49A9	23		INC	HL
1340	49AA	56		LD	D,(HL)
1341	49AB	D5		PUSH	DE
1342	49AC	FE05		CP	S
1343	49AE	D8		RET	C
1344	49AF	FE25		CP	37
1345	49B1	DA9B4B		JP	C,PARSER
1346	49B4	CD9B4B		CALL	PARSER
1347	49B7	E5		PUSH	HL

1348	49B8 F5	PUSH AF
1349	49B9 CD9B48	CALL PARSER
1350	49BC 4F	LD C,A
1351	49BD F1	POP AF
1352	49BE EB	EX DE, HL
1353	49BF E1	POP HL
1354	49C0 07	RLCA
1355	49C1 07	RLCA
1356	49C2 07	RLCA
1357	49C3 07	RLCA
1358	49C4 B1	OR C
1359	49C5 4F	LD C,A
1360	49C6 FDE1	POP IY
1361	49C8 CD8B4C	CALL FIND
1362	49CB 47	LD B,A
1363	49CC 2B01	JR Z,JP3
1364	49CE EB	EX DE,HL
1365	49CF 7D	JP3: LD A,L
1366	49D0 07	RLCA
1367	49D1 07	RLCA
1368	49D2 07	RLCA
1369	49D3 07	RLCA
1370	49D4 B3	OR E
1371	49D5 FDE9	JP (IY)
1372		
1373	49D7 6C4B	JPTAB: DW MOFB
1374	49D9 624E	DW L30
1375	49DB 0B4E	DW ENDH
1376	49DD CE4E	DW RSTH
1377	49DF DB4E	DW RETH
1378	49E1 104F	DW PPH
1379	49E3 7D4D	DW JRH
1380	49E5 8B4D	DW DJH
1381	49E7 3C4F	DW INCH
1382	49E9 9B4F	DW ML1
1383	49EB D24F	DW SRH
1384	49ED C04F	DW BITH
1385	49EF AA4D	DW DWH
1386	49F1 B04D	DW DBH
1387	49F3 CD4D	DW DSH
1388	49F5 FE4D	DW EDUH
1389	49F7 ED4D	DW ORSH
1390	49F9 284F	DW IMH
1391	49FB E14D	DW LOADH
1392	49FD 0D4E	DW LTAB
1393	49FF FA4E	DW CALTAB
1394	4A01 E54E	DW JMPTAB
1395	4A03 1050	DW XTAB
1396	4A05 EB4F	DW INTAB
1397	4A07 644F	DW ADDTAB
1398	4A09 564F	DW ADCTAB
1399	4A0B 5D4F	DW SECTAB
1400	4A0D F54F	DW OUTAB
1401		
1402	4A0F DDCB0076 LIST:	BIT 6,(IX+F1)
1403	4A13 C8	RET Z
1404	4A14 C5	PUSH BC
1405	4A15 DD4E02	LD C,(IX+F3)
1406	4A18 ED5BCB40	LD DE,(FLAGS+F6)
1407	4A1C FD215441	LD IY,TBUFF

1408 4A20 D5	LS1:	PUSH DE
1409 4A21 DDDB0176		BIT 6,(IX+F2)
1410 4A25 CC1847		CALL Z,PAGE
1411 4A28 DDDB004E		BIT 1,(IX+F1)
1412 4A2C 2007		JR NZ,LS12
1413 4A2E DDDB017E		BIT 7,(IX+F2)
1414 4A32 CC6048		CALL Z,POSITION
1415 4A35 D1	LS12:	POP DE
1416 4A36 060E		LD B,14
1417 4A38 0C		INC C
1418 4A39 0D		DEC C
1419 4A3A 2B17		JR Z,LS4
1420 4A3C CDSD48		CALL WORDSP
1421 4A3F 0604		LD B,4
1422 4A41 FD7E00	LS2:	LD A,(IY+0)
1423 4A44 CD9748		CALL BYTE
1424 4A47 FD23		INC IY
1425 4A49 23		INC HL
1426 4A4A 0D		DEC C
1427 4A4B 2B03		JR Z,LS3
1428 4A4D 10F2		DJNZ LS2
1429 4A4F 04		INC B
1430 4A50 CB20	LS3:	SLA B
1431 4A52 05		DEC B
1432 4A53 CD2E46	LS4:	CALL SPACE
1433 4A56 10FB		DJNZ LS4
1434 4A58 C5		PUSH BC
1435 4A59 E5		PUSH HL
1436 4A5A FDE5		PUSH IY
1437 4A5C FD21CD40		LD IY,COMMONWIDTH
1438 4A60 2AE740		LD HL,(TEMP)
1439 4A63 0EFF		LD C,0FFH
1440 4A65 DDDB0146		BIT 0,(IX+F2)
1441 4A69 2B1A		JR Z,LS7
1442 4A6B CDA44A		CALL SYMFIELD
1443 4A6E 53		LD D,E
1444 4A6F CDAB4A		CALL FIELD
1445 4A72 5A		LD E,D
1446 4A73 E5		PUSH HL
1447 4A74 7E	LS5:	LD A,(HL)
1448 4A75 FE00		CP CR
1449 4A77 2B08		JR Z,LS6
1450 4A79 FE3B		CP 3BH
1451 4A7B 2B04		JR Z,LS6
1452 4A7D 14		INC D
1453 4A7E 23		INC HL
1454 4A7F 18F3		JR LSS
1455 4A81 E1	LS6:	POF HL
1456 4A82 CDAB4A		CALL FIELD
1457 4A85 E5	LS7:	PUSH HL
1458 4A86 7E	LS8:	LD A,(HL)
1459 4A87 FE00		CP CR
1460 4A89 2B04		JR Z,LS9
1461 4A8B 14		INC D
1462 4A8C 23		INC HL
1463 4A8D 18F7		JR LSS
1464 4A8F E1	LS9:	POP HL
1465 4A90 CDAB4A		CALL FIELD
1466 4A93 22E740		LD (TEMP),HL
1467 4A96 FDE1		POP IY

1468	4A98	E1		POP	HL
1469	4A99	C1		POP	BC
1470	4A9A	CD2146		CALL	CRLF
1471	4A9D	0C		INC	C
1472	4A9E	0D		DEC	C
1473	4A9F	C2204A		JP	NZ,LS1
1474	4AA2	C1		POP	BC
1475	4AA3	C9		RET	
1476					
1477	4AAA	FD21CF40	SYMFIELD:	LD	IY,SYMWIDTH
1478	4AA8	FD4600	FIELD:	LD	B,(IY+0)
1479	4AAB	DDCB004E		BIT	1,(IX+F1)
1480	4AAF	2803		JR	Z,FD1
1481	4AB1	FD4601		LD	B,(IY+1)
1482	4AB4	FD23	FD1:	INC	IY
1483	4AB6	FD23		INC	IY
1484	4ABB	7A		LD	A,D
1485	4AB9	B8		CP	B
1486	4ABA	3801		JR	C,FD2
1487	4ABC	78		LD	A,B
1488	4ABD	3C	FD2:	INC	A
1489	4ABE	3D	FD3:	DEC	A
1490	4ABF	280A		JR	Z,FD4
1491	4AC1	F5		PUSH	AF
1492	4AC2	7E		LD	A,(HL)
1493	4AC3	A1		AND	C
1494	4AC4	CD3046		CALL	OUTPUT
1495	4AC7	F1		POP	AF
1496	4AC8	23		INC	HL
1497	4AC9	18F3		JR	FD3
1498	4ACB	78	FD4:	LD	A,B
1499	4ACC	92		SUB	D
1500	4ACD	3004		JR	NC,FD6
1501	4ACF	23	FD5:	INC	HL
1502	4AD0	3C		INC	A
1503	4AD1	20FC		JR	NZ,FD5
1504	4AD3	7A	FD6:	LD	A,D
1505	4AD4	90		SUB	B
1506	4AD5	1600		LD	D,0
1507	4AD7	3008		JR	NC,FD8
1508	4AD9	F5	FD7:	PUSH	AF
1509	4ADA	CD2E46		CALL	SPACE
1510	4ADD	F1		POP	AF
1511	4ADE	3C		INC	A
1512	4ADF	20FB		JR	NZ,FD7
1513	4AE1	7E	FD8:	LD	A,(HL)
1514	4AE2	FE20		CP	BLANK
1515	4AE4	C0		RET	NZ
1516	4AE5	23		INC	HL
1517	4AE6	18F9		JR	FD8
1518					
1519	4AE8	213C59	SYMSCH:	LD	HL,AEND+1
1520	4AEB	182D		JR	SEARCH
1521					
1522	4AED	21BA51	OPDSCH:	LD	HL,CCODES
1523	4AF0	DDCB015E		BIT	3,(IX+F2)
1524	4AF4	2824		JR	Z,SEARCH
1525	4AF6	21D651		LD	HL,TREGS
1526	4AF9	181F		JR	SEARCH
1527					

1528 4AFB 79	OPTSCH:	LD	A,C
1529 4AFC 3D		DEC	A
1530 4AFD 37		SCF	
1531 4AFE C8		RET	Z
1532 4AFF 1A		LD	A,(DE)
1533 4B00 D641		SUB	'A'
1534 4B02 D8		RET	C
1535 4B03 FE1A		CP	'Z'-'A'+1
1536 4B05 3F		CCF	
1537 4B06 D8		RET	C
1538 4B07 CDEB54		CALL	KEYADDR
1539 4B0A 13		INC	DE
1540 4B0B 0B		DEC	BC
1541 4B0C CD1A4B		CALL	SEARCH
1542 4B0F 03		INC	BC
1543 4B10 1B		DEC	DE
1544 4B11 C9		RET	
1545			
1546 4B12 CB7E	BAD:	BIT	Z,(HL)
1547 4B14 23		INC	HL
1548 4B15 29FB		JR	Z,BAD
1549 4B17 23		INC	HL
1550 4B18 23		INC	HL
1551 4B19 D1		POP	DE
1552 4B1A 7E	SEARCH:	LD	A,(HL)
1553 4B1B 3C		INC	A
1554 4B1C 37		SCF	
1555 4B1D C8		RET	Z
1556 4B1E D5		PUSH	DE
1557 4B1F 41		LD	B,C
1558 4B20 1A	SC2:	LD	A,(DE)
1559 4B21 1002		DJNZ	SC3
1560 4B23 CBFF		SET	Z,A
1561 4B25 04	SC3:	INC	B
1562 4B26 BE		CP	(HL)
1563 4B27 20E9		JR	NZ,BAD
1564 4B29 13		INC	DE
1565 4B2A 23		INC	HL
1566 4B2B 10F3		DJNZ	SC2
1567 4B2D 5E		LD	E,(HL)
1568 4B2E 23		INC	HL
1569 4B2F 56		LD	D,(HL)
1570 4B30 E3		EX	(SP),HL
1571 4B31 EB		EX	DE,HL
1572 4B32 FDE1		POP	XY
1573 4B34 C9		RET	
1574			
1575 4B35 FE03	RESOLV:	CP	NO
1576 4B37 2017		JR	NZ,E6
1577 4B39 DD7E01		LD	A,(IX+F2)
1578 4B3C CB67		BIT	4,A
1579 4B3E C2A64C		JP	NZ,E7
1580 4B41 CB4F		BIT	1,A
1581 4B43 C9		RET	
1582			
1583 4B44 FE03	LITLE:	CP	NO
1584 4B46 2008		JR	NZ,E6
1585 4B48 DDCB006E	LITLE2:	BIT	5,(IX+F1)
1586 4B4C C0		RET	NZ
1587 4B4D 7C		LD	A,H

1588	4B4E	B7		OR	A
1589	4B4F	C8		RET	Z
1590	4B50	2E52	E6:	LD	L,M16&255
1591	4B52	C3A942		JP	ER
1592					
1593	4B55	5D	MOFMIX:	LD	E,L
1594	4B56	CB5B	MOFMX2:	BIT	3,E
1595	4B58	20F6		JR	NZ,E6
1596	4B5A	7B		LD	A,E
1597	4B5B	07		RLCA	
1598	4B5C	07		RLCA	
1599	4B5D	07		RLCA	
1600	4B5E	B0		OR	B
1601	4B5F	180C		JR	MOF
1602	4B61	3EED	MOFPRE:	LD	A,0EDH
1603	4B63	1808		JR	MOF
1604	4B65	7D	MOFLH:	LD	A,L
1605	4B66	CD6D4B		CALL	MOF
1606	4B69	7C	MOFH:	LD	A,H
1607	4B6A	1801		JR	MOF
1608	4B6C	78	MOFB:	LD	A,B
1609					
1610	4B6D	E5	MOF:	PUSH	HL
1611	4B6E	C5		PUSH	BC
1612	4B6F	CD1A4D		CALL	CL2
1613	4B72	23		INC	HL
1614	4B73	22EF40		LD	(PC),HL
1615	4B76	DDCB006E		BIT	5,(IX+F1)
1616	4B7A	2018		JR	NZ,MOFS
1617	4B7C	DDCB0066		BIT	4,(IX+F1)
1618	4B80	2008		JR	NZ,MOF2
1619	4B82	2AF140		LD	HL,(OBJ)
1620	4B85	77		LD	(HL),A
1621	4B86	23		INC	HL
1622	4B87	22F140		LD	(OBJ),HL
1623	4B8A	0600	MOF2:	LD	B,0
1624	4B8C	DD4E02		LD	C,(IX+F3)
1625	4B8F	215441		LD	HL,TBUFF
1626	4B92	09		ADD	HL,BC
1627	4B93	77		LD	(HL),A
1628	4B94	DD3402	MOF5:	INC	(IX+F3)
1629	4B97	C1		POP	BC
1630	4B98	E1		POP	HL
1631	4B99	AF		XOR	A
1632	4B9A	C9		RET	
1633					
1634	4B9B	DDCB0146	PARSER:	BIT	0,(IX+F2)
1635	4B9F	3E0B		LD	A,EOL
1636	4BA1	C0		RET	NZ
1637	4BA2	C5		PUSH	BC
1638	4BA3	CDA84B		CALL	PA1
1639	4BA6	C1		POP	BC
1640	4BA7	C9		RET	
1641					
1642	4BAB	CD754C	PA1:	CALL	TERM
1643	4BAB	D8		RET	C
1644	4BAC	FE34		CP	TIND
1645	4BAE	0600		LD	B,0
1646	4BB0	2005		JR	NZ,PA2
1647	4BB2	CD754C		CALL	TERM

1648 4BB5 0604		LD	B,4
1649 4BB7 FE32	PA2:	CP	TOPD
1650 4BB9 2031		JR	NZ,PA7
1651 4BBC 7C		LD	A,H
1652 4BBC B0		OR	B
1653 4BBD 57		LD	D,A
1654 4BBE E5		PUSH	HL
1655 4BBF CD754C		CALL	TERM
1656 4BC2 E1		POP	HL
1657 4BC3 4F		LD	C,A
1658 4BC4 7A		LD	A,D
1659 4BC5 D8		RET	C
1660 4BC6 FE06		CP	XYI
1661 4BC8 202F		JR	NZ,PER
1662 4BCA CB71		BIT	6,C
1663 4BCC 282B		JR	Z,PER
1664 4BCE 45		LD	E,L
1665 4BCF C5		PUSH	BC
1666 4BD0 CD754C		CALL	TERM
1667 4BD3 CDFC4B		CALL	PA4
1668 4BD6 C1		POP	BC
1669 4BD7 CD484B		CALL	LITTLE2
1670 4BDA 200C		JR	NZ,PA3
1671 4BDC 7D		LD	A,L
1672 4BDD CB79		BIT	Z,C
1673 4BDF 2803		JR	Z,PA31
1674 4BE1 ED44		NEG	
1675 4BE3 5F		LD	L,A
1676 4BE4 A9	PA31:	XOR	C
1677 4BE5 FA504B		JP	M,E6
1678 4BE8 60	PA3:	LD	H,B
1679 4BE9 3E0A		LD	A,XYD
1680 4BEB C9		RET	
1681			
1682 4BED FE36	PA7:	CP	TLIT
1683 4BEE 200C		JR	NZ,PA4
1684 4BF0 B0		OR	B
1685 4BF1 6F		LD	L,A
1686 4BF2 E5		PUSH	HL
1687 4BF3 CD754C		CALL	TERM
1688 4BF6 E1		POP	HL
1689 4BF7 7D		LD	A,L
1690 4BF8 DB		RET	C
1691 4BF9 C3504B	PER:	JP	E6
1692			
1693 4BFC FE03	PA4:	CP	NO
1694 4BFE 20F9		JR	NZ,PER
1695 4C00 B0		OR	B
1696 4C01 F5		PUSH	AF
1697 4C02 E5	PAS:	PUSH	HL
1698 4C03 CD754C		CALL	TERM
1699 4C06 E1		POP	HL
1700 4C07 3811		JR	C,PA6
1701 4C09 F5		PUSH	AF
1702 4C0A E5		PUSH	HL
1703 4C0B CD754C		CALL	TERM
1704 4C0E EB		EX	DE,HL
1705 4C0F E1		POP	HL
1706 4C10 FE03		CP	NO
1707 4C12 20E5		JR	NZ,PER

1708	4C14	F1		POP	AF
1709	4C15	CD1C4C		CALL	MATH
1710	4C18	18E8		JR	PA5
1711	4C1A	F1	PA6:	POP	AF
1712	4C1B	C9		RET	
1713					
1714	4C1C	FE40	MATH:	CP	TADD
1715	4C1E	2002		JR	NZ,MA2
1716	4C20	19		ADD	HL,DE
1717	4C21	C9		RET	
1718	4C22	FEC0	MA2:	CP	TSUB
1719	4C24	2003		JR	NZ,MA3
1720	4C26	ED52		SBC	HL,DE
1721	4C28	C9		RET	
1722	4C29	FE82	MA3:	CP	TAND
1723	4C2B	2007		JR	NZ,MA4
1724	4C2D	7B		LD	A,E
1725	4C2E	A5		AND	L
1726	4C2F	6F		LD	L,A
1727	4C30	7A		LD	A,D
1728	4C31	A4		AND	H
1729	4C32	67		LD	H,A
1730	4C33	C9		RET	
1731					
1732	4C34	FE83	MA4:	CP	TOR
1733	4C36	2007		JR	NZ,MA5
1734	4C38	7B		LD	A,E
1735	4C39	B5		OR	L
1736	4C3A	6F		LD	L,A
1737	4C3B	7A		LD	A,D
1738	4C3C	B4		OR	H
1739	4C3D	67		LD	H,A
1740	4C3E	C9		RET	
1741					
1742	4C3F	4B	MA5:	LD	C,E
1743	4C40	42		LD	B,D
1744	4C41	EB		EX	DE,HL
1745	4C42	FE81		CP	TDIV
1746	4C44	2018		JR	NZ,MA6
1747	4C46	210000	MA50:	LD	HL,0
1748	4C49	3E11		LD	A,17
1749	4C4B	B7		OR	A
1750	4C4C	ED6A	MA51:	ADC	HL,HL
1751	4C4E	ED42		SBC	HL,BC
1752	4C50	3002		JR	NC,MA52
1753	4C52	09		ADD	HL,BC
1754	4C53	37		SCF	
1755	4C54	3F	MA52:	CCF	
1756	4C55	CB13		RL	E
1757	4C57	CB12		RL	D
1758	4C59	3D		DEC	A
1759	4C5A	20F0		JR	NZ,MA51
1760	4C5C	EB		EX	DE,HL
1761	4C5D	C9		RET	
1762					
1763	4C5E	FE80	MA6:	CP	TMUL
1764	4C60	2097		JR	NZ,PER
1765	4C62	210000		LD	HL,0
1766	4C65	3E10		LD	A,16
1767	4C67	CB38	MA61:	SRL	B

1768	4C69	CB19		RR	C
1769	4C6B	3001		JR	NC,MA62
1770	4C6D	19		ADD	HL,DE
1771	4C6E	EB	MA62:	EX	DE,HL
1772	4C6F	29		ADD	HL,HL
1773	4C70	EB		EX	DE,HL
1774	4C71	3D		DEC	A
1775	4C72	20F3		JR	NZ,MA61
1776	4C74	C9		RET	
1777					
1778	4C75	CD0A4D	TERM:	CALL	CLASS
1779	4C78	FE31		CP	TLAB
1780	4C7A	CA504B		JP	Z,E6
1781	4C7D	FE0B	TE2:	CP	EOL
1782	4C7F	2006		JR	NZ,TE3
1783	4C81	DDCB01C6		SET	0,(IX+F2)
1784	4C85	37		SCF	
1785	4C86	C9		RET	
1786	4C87	FE33	TE3:	CP	TCOM
1787	4C89	37		SCF	
1788	4C8A	C9		RET	Z
1789	4C8B	FE30		CP	TALPHA
1790	4C8D	37		SCF	
1791	4C8E	3F		CCF	
1792	4C8F	C0		RET	NZ
1793	4C90	CDED4A		CALL	OPDSCH
1794	4C93	3E32		LD	A,TOPD
1795	4C95	D0		RET	NC
1796	4C96	CDE84A		CALL	SYMSCH
1797	4C99	3E03		LD	A,ND
1798	4C9B	D0		RET	NC
1799	4C9C	3F		CCF	
1800	4C9D	DDCB01E6		SET	4,(IX+F2)
1801	4CA1	DDCB006E		BIT	5,(IX+F1)
1802	4CA3	C0		RET	NZ
1803	4CA6	2ESA	E7:	LD	L,M17&255
1804	4CA8	C3A942		JP	ER
1805					
1806	4CAB	2ADD40	TYPE:	LD	HL,(CURRENT)
1807	4CAE	CD0646		CALL	EOF
1808	4CB1	23		INC	HL
1809	4CE2	22DD40		LD	(CURRENT),HL
1810	4CB5	2B		DEC	HL
1811	4CB6	7E		LD	A,(HL)
1812	4CB7	FD21D94C		LD	IY,TYPTAB
1813					
1814	4CBB	D5	FIND:	PUSH	DE
1815	4CBC	FDES		PUSH	IY
1816	4CBE	E3		EX	(SP),HL
1817	4CBF	5E		LD	E,(HL)
1818	4CC0	53		LD	D,E
1819	4CC1	23	FIN1:	INC	HL
1820	4CC2	BE		CP	(HL)
1821	4CC3	2803		JR	Z,FIN2
1822	4CC5	15		DEC	D
1823	4CC6	20F9		JR	NZ,FIN1
1824	4CCB	1600	FIN2:	LD	D,0
1825	4CCA	19		ADD	HL,DE
1826	4CCB	7E		LD	A,(HL)
1827	4CCC	19		ADD	HL,DE

1828	4CCD 5F		LD	E,A
1829	4CCE 7E		LD	A,(HL)
1830	4CCF CB7B		BIT	7,E
1831	4CD1 CBBB		RES	7,E
1832	4CD3 19		ADD	HL,DE
1833	4CD4 E3		EX	(SP),HL
1834	4CD5 FDE1		POP	IY
1835	4CD7 D1		POP	DE
1836	4CD8 C9		RET	
1837				
1838	4CD9 100D27	TYPTAB:	DB	TL,CR,""
1839	4CDC 242A2F2B		DB	'*/+-&.()
1839	4CE0 2D262E2B			
1839	4CE4 29			
1840	4CE5 3B3A222C		DB	3BH,':",'
1841	4CE9 00		DB	0
1842				
1843	4CEA 1F		DB	CL3-\$-TL
1844	4CEB 2C		DB	CL4-\$-TL
1845	4CEC 1E		DB	CL2-\$-TL
1846	4CED 1C		DB	CL3-\$-TL
1847	4CEE 1B		DB	CL3-\$-TL
1848	4CEF 1A		DB	CL3-\$-TL
1849	4CF0 19		DB	CL3-\$-TL
1850	4CF1 18		DB	CL3-\$-TL
1851	4CF2 17		DB	CL3-\$-TL
1852	4CF3 16		DB	CL3-\$-TL
1853	4CF4 06		DB	CLASS-\$-TL
1854	4CF5 0D		DB	CL1-\$-TL
1855	4CF6 13		DB	CL3-\$-TL
1856	4CF7 20		DB	CL4-\$-TL
1857	4CF8 11		DB	CL3-\$-TL
1858	4CF9 3B		DB	CL5-\$-TL
1859				
1860	4CFA 0B000380		DB	EOL,0,NO,TMUL,TDIV
1860	4CFE 81			
1861	4CFF 40C08283		DB	TADD,TSUB,TAND,TOR
1862	4D03 34000031		DB	TIND,0,0,TLAB
1863	4D07 003335		DB	0,TCOM,TDEF
1864				
1865	4D0A CDAB4C	CLASS:	CALL	TYPE
1866	4D0D 010021		LD	BC,2100H
1867	4D10 FDE?		JP	(IY)
1868				
1869	4D12 CDAB4C	CL1:	CALL	TYPE
1870	4D15 FE0B		CP	EOL
1871	4D17 20F9		JR	NZ,CL1
1872	4D19 C9	CL3:	RET	
1873	4D1A 2AEF40	CL2:	LD	HL,(PC)
1874	4D1D DDCB007E		BIT	7,(IX+F1)
1875	4D21 C8		RET	Z
1876	4D22 2E64	E11:	LD	L,M18&255
1877	4D24 C3A942		JP	ER
1878	4D27 E5	CL4:	PUSH	HL
1879	4D28 46		LD	B,(HL)
1880	4D29 5E	CL41:	LD	E,(HL)
1881	4D2A 0C		INC	C
1882	4D2B CDAB4C		CALL	TYPE
1883	4D2E FE0B		CP	EOL
1884	4D30 282C		JR	Z,CLER

1885	4D32	7E		LD	A, (HL)
1886	4D33	B8		CP	B
1887	4D34	20F3		JR	NZ,CL41
1888	4D36	EB		EX	DE,HL
1889	4D37	D1		POP	DE
1890	4D38	0D		DEC	C
1891	4D39	2823		JR	Z,CLER
1892	4D3B	61		LD	H,C
1893	4D3C	3E03		LD	A,NO
1894	4D3E	25		DEC	H
1895	4D3F	C8		RET	Z
1896	4D40	24		INC	H
1897	4D41	3E36		LD	A,TLIT
1898	4D43	C9		RET	
1899					
1900	4D44	7E	CL5:	LD	A, (HL)
1901	4D45	B8		CP	B
1902	4D46	38C2		JR	C,CLASS
1903	4D48	FE30		CP	30H
1904	4D4A	3815		JR	C,CL7
1905	4D4C	FE3A		CP	3AH
1906	4D4E	3011		JR	NC,CL7
1907	4D50	CD614D	CL6:	CALL	CL7
1908	4D53	FE31		CP	TLAB
1909	4D55	2807		JR	Z,CLER
1910	4D57	41		LD	B,C
1911	4D58	CDD247		CALL	CONVERT
1912	4D5B	3E03		LD	A,NO
1913	4D5D	D0		RET	NC
1914	4D5E	C3504B	CLER:	JP	E8
1915					
1916	4D61	E5	CL7:	PUSH	HL
1917	4D62	D1		POP	DE
1918	4D63	CB7E	CL71:	BIT	7, (HL)
1919	4D65	C21749		JP	NZ,E1
1920	4D68	0C		INC	C
1921	4D69	CDAB4C		CALL	TYPE
1922	4D6C	FE31		CP	TLAB
1923	4D6E	C8		RET	Z
1924	4D6F	FE35		CP	TDEF
1925	4D71	2004		JR	NZ,CL72
1926	4D73	7E		LD	A, (HL)
1927	4D74	B8		CP	B
1928	4D75	30EC		JR	NC,CL71
1929	4D77	22DD40	CL72:	LD	(CURRENT), HL
1930	4D7A	3E30		LD	A,TALPHA
1931	4D7C	C9		RET	
1932					
1933	4D7D	FE09	JRH:	CP	CC
1934	4D7F	200A		JR	NZ,DJH
1935	4D81	7D		LD	A,L
1936	4D82	E6E7		AND	0E7H
1937	4D84	C0		RET	NZ
1938	4D85	45		LD	B,L
1939	4D86	CBE8		SET	S,B
1940	4D88	CD9B4B		CALL	PARSER
1941					
1942	4D8B	FE03	DJH:	CP	NO
1943	4D8D	C0		RET	NZ
1944	4D8E	CD6C4B		CALL	MOFB

1945	4D91	DDCB006E		BIT	5,(IX+F1)
1946	4D95	200F		JR	NZ,DJ2
1947	4D97	ED5BEF40		LD	DE,(PC)
1948	4D9B	37		SCF	
1949	4D9C	ED52		SBC	HL,DE
1950	4D9E	7C		LD	A,H
1951	4D9F	24		INC	H
1952	4DA0	2802		JR	7,DJ1
1953	4DA2	25		DEC	H
1954	4DA3	C0		RET	NZ
1955	4DA4	AD	DJ1:	XOR	L
1956	4DAS	F8		RET	M
1957	4DA6	7D	DJ2:	LD	A,L
1958	4DA7	C36D4B		JP	MOF
1959					
1960	4DAA	FE03	DWH:	CP	NO
1961	4DAC	C0		RET	NZ
1962	4DAD	C3654B		JP	MOFLH
1963					
1964	4DB0	FE36	DBH:	CP	TLIT
1965	4DB2	200A		JR	NZ,DBH3
1966	4DB4	13	DBH1:	INC	DE
1967	4DB5	1A		LD	A,(DE)
1968	4DB6	C06D4B		CALL	MOF
1969	4DB9	25		DEC	H
1970	4DBA	20F8		JR	NZ,DBH1
1971	4DBC	1807		JR	DBH4
1972					
1973	4DBE	CD444B	DBH3:	CALL	LITLE
1974	4DC1	7D		LD	A,L
1975	4DC2	CD6D4B		CALL	MOF
1976	4DC5	CD9B4B	DBH4:	CALL	PARSER
1977	4DCB	FE0B		CP	EOL
1978	4DCA	20E4		JR	NZ,DBH
1979	4DCC	C9		RET	
1980					
1981	4DDC	CD354B	DSH:	CALL	RESOLV
1982	4DD0	EB		EX	DE,HL
1983	4DD1	2AEF40		LD	HL,(PC)
1984	4DD4	19		ADD	HL,DE
1985	4DD5	22EF40		LD	(PC),HL
1986	4DD8	2AF140		LD	HL,(OBJ)
1987	4DDB	19		ADD	HL,DE
1988	4DDC	22F140		LD	(OBJ),HL
1989	4DDF	AF		XOR	A
1990	4DE0	C9		RET	
1991					
1992	4DE1	CD354B	LOADH:	CALL	RESOLV
1993	4DE4	22F140		LD	(OBJ),HL
1994	4DE7	DDCB00A6		RES	4,(IX+F1)
1995	4DEB	AF		XOR	A
1996	4DEC	C9		RET	
1997					
1998	4DED	CD354B	ORGH:	CALL	RESOLV
1999	4DF0	22EF40		LD	(PC),HL
2000	4DF3	DDCB00E6		SET	4,(IX+F1)
2001	4DF7	DDCB00BE		RES	7,(IX+F1)
2002	4DFB	2007		JR	NZ,EO2
2003	4DFD	C9		RET	
2004					

2005	4E0E	CD354B	EQUH:	CALL RESOLV
2006	4E01	CAA742		JP Z,E0
2007	4E04	E8	E02:	EX DE,HL
2008	4E05	2AED40		LD HL,(LBLEP)
2009	4E08	72		LD (HL),D
2010	4E09	2B		DEC HL
2011	4E0A	73		LD (HL),E
2012	4E0B	AF	ENDH:	XOR A
2013	4E0C	C9		RET
2014				
2015	4E0D	15	LTAH:	DB L1
2016	4E0E	53		DB RP1*16,NO
2017	4E0F	02		DB TR*16,NO
2018	4E10	80		DB RE*16,TR
2019	4E11	08		DB TR*16,RE
2020	4E12	00		DB TR*16,TR
2021	4E13	11		DB RP*16,RP
2022	4E14	72		DB NOI*16,YY
2023	4E15	27		DB YY*16,NOI
2024	4E16	23		DB XY*16,NO
2025	4E17	70		DB NOI*16,TR
2026	4E18	07		DB TR*16,NOI
2027	4E19	71		DB NOI*16,RF
2028	4E1A	17		DB RP*16,NOT
2029	4E1B	12		DB RP*16,XY
2030	4E1C	A3		DB YYD*16,NO
2031	4E1D	13		DB RP*16,NO
2032	4E1E	A0		DB XYD*16,TR
2033	4E1F	0A		DB TR*16,XYD
2034	4E20	50		DB RP1*16,TR
2035	4E21	05		DB TR*16,RPI
2036	4E22	00		DB @
2037				
2038	4E23	95		DB L1-\$LL,S
2039	4E24	76		DB L2-\$LL,S
2040	4E25	21		DB L3-\$LL
2041	4E26	A0		DB L3-\$LL,S
2042	4E27	A0		DB L4-\$LL,S
2043	4E28	31		DB L5-\$LL
2044	4E29	C5		DB L6-\$LL
2045	4E2A	B4		DB L6-\$LL,S
2046	4E2B	B3		DB L6-\$LL,S
2047	4E2C	3C		DB L7-\$LL
2048	4E2D	BB		DB L7-\$LL,S
2049	4E2E	42		DB L8-\$LL
2050	4E2F	C1		DB L8-\$LL,S
2051	4E30	D2		DB L9-\$LL,S
2052	4E31	D8		DB LA-\$LL,S
2053	4E32	DF		DB LB-\$LL,S
2054	4E33	63		DB LC-\$LL
2055	4E34	E2		DB LD-\$LL,S
2056	4E35	6A		DB LE-\$LL
2057	4E36	E9		DB LE-\$LL,S
2058	4E37	36		DB LER-\$LL
2059				
2060	4E38	16064757		DB 16H,6,47H,57H,10H
2060	4E3C	40		
2061	4E3D	F9222A21		DB 0F9H,22H,2AH,21H
2062	4E41	32		DB 32H
2063	4E42	3A222AF9		DB 3AH,22H,2AH,0FH

2064	4E46	36		DB	36H
2065	4E47	01020A02		DB	1,2,0AH,2,0AH,0
2065	4E4B	0A00			
2066					
2067	4E4D	7B	L1:	LD	A,E
2068	4E4E	FE04		CP	IHL
2069	4E50	C0		RET	NZ
2070	4E51	CD484B	L2:	CALL	LITTLE2
2071	4E54	CD564B		CALL	MOFMX2
2072	4E57	7D		LD	A,L
2073	4E58	C36D4B	L21:	JP	MOF
2074					
2075	4E5B	7B	L3:	LD	A,E
2076	4E5C	FE07		CP	IA
2077	4E5E	C0		RET	NZ
2078	4E5F	7D		LD	A,L
2079	4E60	B0		OR	B
2080	4E61	47		LD	B,A
2081	4E62	CD614B	L30:	CALL	MOFPRE
2082	4E65	C36C4B	L31:	JP	MOFB
2083					
2084	4E68	7D	L4:	LD	A,L
2085	4E69	B0		OR	B
2086	4E6A	47		LD	B,A
2087	4E6B	C3564B		JP	MOFMX2
2088					
2089	4E6E	FE64	L5:	CP	ISP*16.IHL
2090	4E70	C0		RET	NZ
2091	4E71	18F2		JR	L31
2092					
2093	4E73	7B	L6:	LD	A,E
2094	4E74	CD6D4B	L61:	CALL	MOF
2095	4E77	CD6C4B	L62:	CALL	MOFB
2096	4E7A	C3654B	L63:	JP	MOFLH
2097					
2098	4E7D	7B	L7:	LD	A,E
2099	4E7E	FE07		CP	IA
2100	4E80	28F5		JR	Z,L62
2101	4E82	C3504B	LER:	JP	E6
2102					
2103	4E85	7B	L8:	LD	A,E
2104	4E86	FE04		CP	IHL
2105	4E88	28ED		JR	Z,L62
2106	4E8A	CD614B		CALL	MOFPRE
2107	4E8D	7B		LD	A,B
2108	4E8E	EE61		XOR	61H
2109	4E90	47		LD	B,A
2110	4E91	CD564B		CALL	MOFMX2
2111	4E94	C3654B		JP	MOFLH
2112					
2113	4E97	7B	L9:	LD	A,E
2114	4E98	FE06		CP	ISP
2115	4E9A	C0		RET	NZ
2116	4E9B	60		LD	H,B
2117	4E9C	18DC		JR	L63
2118					
2119	4E9E	CD484B	LA:	CALL	LITTLE2
2120	4EA1	7A		LD	A,D
2121	4EA2	65		LD	H,L
2122	4EA3	6B		LD	L,E

2123	4E04	18CE		JR	L61
2124					
2125	4EA6	C0564B	LB:	CALL	M0FMX2
2126	4EA9	18CF		JR	L63
2127					
2128	4EB0	CD694B	LC:	CALL	M0FH
2129	4EAE	CDC24E		CALL	LE1
2130	4EB1	7D		LD	A,L
2131	4EB2	18A4		JR	L21
2132					
2133	4EB4	FE07	LE:	CP	I0C*16.IA
2134	4EB6	28AD		JR	Z,L31
2135	4EB8	CBE0		SET	4,B
2136	4EBA	FE27		CP	IDE*16.1A
2137	4EBC	28A7		JR	Z,L31
2138	4EBE	7D		LD	A,L
2139	4EBF	FE04		CP	IHL
2140	4EC1	C0		RET	NZ
2141	4EC2	C858	LE1:	BIT	3,B
2142	4EC4	0646		LD	B,46H
2143	4EC6	C2564B		JP	NZ,M0FMX2
2144	4EC9	7B		LD	A,E
2145	4ECA	F670		OR	70H
2146	4ECC	188A		JR	L21
2147					
2148	4ED0	CD444B	RSTH:	CALL	LITTLE
2149	4ED1	2003		JR	NZ,RST2
2150	4ED3	7D		LD	A,L
2151	4ED4	A0		AND	B
2152	4ED5	C0		RET	NZ
2153	4ED6	78	RST2:	LD	A,B
2154	4ED7	B5		OR	L
2155	4ED8	C36D4B		JP	M0F
2156					
2157	4EDB	FE09	RETH:	CP	CC
2158	4EDD	28F7		JR	Z,RST2
2159	4EDF	06C9		LD	B,0C9H
2160	4EE1	FE0B		CP	EOL
2161	4EE3	1811		JR	JMP21
2162					
2163	4EE5	03	JMFTAB:	DB	JL
2164	4EE6	6B		DB	XYI*16.EOL
2165	4EE7	5B		DB	RPI*16.EOL
2166	4EE8	00		DB	0
2167	4EE9	03		DB	JMP1-\$-JL
2168	4EEA	06		DB	JMP2-\$-JL
2169	4EEB	10		DB	JMP3-\$-JL
2170	4ECC	E9E9C3		DB	0E9H,0E9H,0C3H
2171					
2172	4EEF	60	JMP1:	LD	H,B
2173	4EF0	C3654B		JP	M0FLH
2174	4EF3	7D	JMP2:	LD	A,L
2175	4EF4	FE04		CP	IHL
2176	4EF6	C0	JMP21:	RET	NZ
2177	4EF7	C36C4B		JP	M0FB
2178					
2179	4EFA	01	CALTAB:	DB	CL
2180	4EFB	00		DB	0
2181	4EFC	01		DB	JMP3-\$-CL
2182	4EFD	CD		DB	0CDH

2183				
2184	4EFF 79	JMP3:	LD	A,C
2185	4EFF FE0B		CP	NO*16.EOL
2186	4F01 D4774D		JP	Z,L62
2187	3F04 FE93		CP	CC*16.NO
2188	4F06 50		RET	NZ
2189	4F07 72		LD	A,B,
2190	4F08 F6C4		AND	0C6H
2191	4F0A B3		OR	L
2192	4F0B 47		LD	B,A
2193	4F0C E8		EX	DE,HL
2194	4F0D C5774E		JP	L62
2195				
2196	4F10 FE01	PPH:	CP	RP
2197	4F12 2008		JR	NZ,PP2
2198	4F14 7D		LD	A,L
2199	4F15 FE06		CP	ISP
2200	4F17 C4C04B		JP	Z,E6
2201	4F1A CBFD		RES	3,L
2202	4F1C C3554B		JP	MOFMIX
2203	4F1F FF02	PP2:	CP	XY
2204	4F21 C0		RET	NZ
2205	4F22 CB68	PP21:	SET	S,B
2206	4F24 50		LD	H,B
2207	4F25 C3554B		JP	MOFLH
2208				
2209	4F28 C0444B	IMH:	CALL	LITTLE
2210	4F2B 2004		JR	NZ,IM2
2211	4F2D 3E02		LD	A,2
2212	4F2F 95		SUB	L
2213	4F30 D8		RET	C
2214	4F31 11334F	IM2:	LD	DE,IMTAB
2215	4F34 19		ADD	HL,DE
2216	4F35 46		LD	B,(HL)
2217	4F36 C3624E		JP	L30
2218				
2219	4F39 46565E	IMTAB:	DB	46H,56H,5EH
2220				
2221	4F3C FF02	INCH:	CP	XY
2222	4F3E 29E2		JR	Z,PP21
2223	4F40 FE01		CP	RP
2224	4F42 C4554B		JP	Z,MOFMIX
2225	4F45 CB50		BIT	3,B
2226	4F47 0634		LD	B,34H
2227	4F49 2B01		JR	Z,INC2
2228	4F4B 04		INC	B
2229	4F4C 57	INC2:	OR	A
2230	4F4D 205A		JR	NZ,ML2
2231	4F4F 78		LD	A,B
2232	4F50 E6C7		AND	0C7H
2233	4F52 47		LD	B,A
2234	4F53 C3554B		JP	MOFMIX
2235				
2236	4F56 02	ADCTAB:	DB	AL
2237	4F57 11		DB	RP*16.RP
2238	4F58 00		DB	0
2239	4F59 16		DB	DL1-\$-AL
2240	4F5A B3		DB	DL5-\$-AL.S
2241	4F5B 4A8E		DB	4AH,8EH
2242				

2243	4F5D 02	SCTAB:	DB	SBL
2244	4F5E 11		DB	RP*16,RP
2245	4F5F 00		DB	0
2246	4F60 0F		DB	DL1-\$-SBL
2247	4F61 AC		DB	DL5-\$-SBL,S
2248	4F62 429E		DB	42H,?EM
2249				
2250	4F64 04	ADDTAB:	DB	ADL
2251	4F65 11		DB	RP*16,RP
2252	4F66 21		DB	XY*16,RP
2253	4F67 22		DB	XY*16,XY
2254	4F68 00		DB	0
2255	4F69 07		DB	DL2-\$-ADL
2256	4F6A 00		DB	DL3-\$-ADL
2257	4F6B 19		DB	DL4-\$-ADL
2258	4F6C 9F		DB	DL5-\$-ADL,S
2259	4F6D 09092985		DB	9,7,29H,36H
2260				
2261	4F71 CD614B	DL1:	CALL	MOPPRE
2262	4F74 7D	DL2:	LD	A,L
2263	4F75 FE04		CP	IHL
2264	4F77 C0		RET	NZ
2265	4F78 C3654B		JP	MOPMX2
2266				
2267	4F7B 7B	DL3:	LD	A,E
2268	4F7C FE04		CP	IHL
2269	4F7E CA504B		JP	Z,E6
2270	4F81 7D		LD	A,L
2271	4F82 CD6D4B		CALL	MOP
2272	4F85 C3654B		JP	MOPMX2
2273				
2274	4F88 7B	DL4:	LD	A,E
2275	4F89 BD		CP	L
2276	4F8A 60		LD	H,B
2277	4F8B C0		RET	NZ
2278	4F8C C3654B		JP	MOPFH
2279				
2280	4F8F 79	DL5:	LD	A,C
2281	4F90 E6F0		AND	0F0H
2282	4F92 C0		RET	NZ
2283	4F93 CB53		BIT	Z,E
2284	4F95 CA504B		JP	Z,E6
2285	4F98 79		LD	A,C
2286	4F99 E60F		AND	0FH
2287				
2288	4F9B FE03	ML1:	CP	ND
2289	4F9D 200A		JR	NZ,ML2
2290	4F9F CBF0		SET	A,B
2291	4FA1 CD484B	ML11:	CALL	LITTLE2
2292	4FA4 65	ML12:	LD	H,L
2293	4FA5 68		LD	L,B
2294	4FA6 C3654B		JP	MOPFH
2295				
2296	4FA7 FE0A	ML2:	CP	XYD
2297	4FAB 2005		JR	NZ,ML3
2298	4FAD CD694B		CALL	MOPFH
2299	4FB0 18F2		JR	ML12
2300				
2301	4FB2 FE05	ML3:	CP	RPI
2302	4FB4 CAF34E		JP	Z,JMP2

2303 4FB7 B7		OR A
2304 4FB8 C0		RET NZ
2305 4FB9 78		LD A,E
2306 4FBA E6F8		AND 0F8H
2307 4FBC B5		OR L
2308 4FBD C36D4B		JP MOF
2309		
2310 4FC0 CD444B	BITH:	CALL LITTLE
2311 4FC3 2004		JR NZ,BIT2
2312 4FC5 3E07		LD A,7
2313 4FC7 95		SUB L
2314 4FC8 DB		RET C
2315 4FC9 7D	BIT2:	LD A,L
2316 4FC A 07		RLCA
2317 4FCB 07		RLCA
2318 4FCC 07		RLCA
2319 4FCD B0		OR B
2320 4FCE 47		LD B,A
2321 4FCF CD9B4B		CALL PARSER
2322		
2323 4FD2 FE0A	SRH:	CP XYD
2324 4FD4 200C		JR NZ,SR2
2325 4FD6 E5		PUSH HL
2326 4FD7 6C		LD L,H
2327 4FD8 26CB		LD H,0CBH
2328 4FDA CD654B		CALL MOFLH
2329 4FDD E1		POP HL
2330 4FDE 60		LD H,B
2331 4FDF C3654B		JP MOFLH
2332		
2333 4FE2 F5	SR2:	PUSH AF
2334 4FE3 3ECB		LD A,0CBH
2335 4FE5 CD6D4B		CALL MOF
2336 4FE8 F1		POP AF
2337 4FE9 18C7		JR ML3
2338		
2339 4FEB 03	INTAB:	DB INL
2340 4FEC 07		DB TR*16.NOI
2341 4FED 04		DB TR*16.TRI
2342 4FEE 00		DB 0
2343 4FEF 8D		DB IO1-\$-INL.S
2344 4FF0 93		DB IO2-\$-INL.S
2345 4FF1 19		DB IOER-\$-INL
2346 4FF2 DB4000		DB 0DBH,40H,0
2347		
2348 4FF5 03	OUTAB:	DB DL
2349 4FF6 70		DB NOI*16.TR
2350 4FF7 40		DB TRI*16.TR
2351 4FF8 00		DB 0
2352 4FF9 03		DB IO1-\$-DL
2353 4FFA 09		DB IO2-\$-DL
2354 4FFB 0F		DB IOER-\$-DL
2355 4FFC D34100		DB 0D3H,41H,0
2356		
2357 4FFF CB53	I01:	BIT 2,E
2358 5001 280A		JR Z,IOER
2359 5003 C3A14F		JP ML11
2360 5006 CD614B	I02:	CALL MOFPRE
2361 5009 2D		DEC L
2362 500A CA564B		JP Z,MOFMX2

2363	500D	C3504B	IDER:	JP	E6
2364					
2365	5010	04	XTAB:	DB	XL
2366	5011	11		DB	RP*16.RP
2367	5012	51		DB	RPI*16.RP
2368	5013	52		DB	RPI*16.XY
2369	5014	00		DB	0
2370	5015	04		DB	X1-\$-XL
2371	5016	11		DB	X2-\$-XL
2372	5017	93		DB	X3-\$-XL.S
2373	5018	00		DB	XER-\$-XL
2374	5019	E8E3E300		DB	0EBH,0E3H,0E3H,0
2375					
2376	501D	FE24	X1:	CP	IDE*16.IHL
2377	501F	CA6C4B		JP	Z,MOFB
2378	5022	0608		LD	B,B
2379	5024	FEEE		CP	IAF*16.IAF
2380	5026	CA6C4B		JP	Z,MOFB
2381	5029	18E2	XER:	JR	IDER
2382					
2383	502B	C36E4E	X2:	JP	L5
2384					
2385	502E	C3974E	X3:	JP	L9
2386					
2387	5031	6550	KEYTB:	DW	AOPS
2388	5033	7250		DW	BOPS
2389	5035	7750		DW	COPS
2390	5037	9A50		DW	DOPS
2391	5039	C350		DW	EOPS
2392	503B	D650		DW	FOPS
2393	503D	D750		DW	GOPS
2394	503F	D850		DW	HOPS
2395	5041	DE50		DW	IOPS
2396	5043	F850		DW	JOPS
2397	5045	0251		DW	KOPS
2398	5047	0351		DW	LOPS
2399	5049	1E51		DW	MOPS
2400	504B	1F51		DW	NOPS
2401	504D	2851		DW	OOPS
2402	504F	4851		DW	POPS
2403	5051	5251		DW	QOPS
2404	5053	5351		DW	ROPS
2405	5055	9251		DW	SOPS
2406	5057	AF51		DW	TOPS
2407	5059	B051		DW	UOPS
2408	505B	B151		DW	VOPS
2409	505D	B251		DW	WOPS
2410	505F	B351		DW	XOPS
2411	5061	B851		DW	YOPS
2412	5063	B951		DW	ZOPS
2413					
2414	5065	44C33200	AOPS:	DB	'D','C'+\$,50,0
2415	5069	44C43000		DB	'D','D'+\$,48,0
2416	506D	4EC412A6		DB	'N','D'+\$,18,0A6H
2417	5071	FF		DB	0FFF
2418					
2419	5072	49D41646	BOPS:	DB	'I','T'+\$,22,46H
2420	5076	FF		DB	0FFF
2421					
2422	5077	414CCCC8	COPS:	DB	'AL','L'+\$,40+\$,0

2422	507B 00		
2423	507C D012BE	DB	'P'+S,18,0BEH
2424	507F 43C6003F	DB	'C','F'+S,0,3FH
2425	5083 50C002F	DB	'P','L'+S,0,2FH
2426	5087 50C902A1	DB	'P','I'+S,2,0A1H
2427	508B 5049D202	DB	'PI','R'+S,2,0B1H
2427	508F B1		
2428	5090 50C402A9	DB	'P','D'+S,2,0A9H
2429	5094 5044D202	DB	'PD','R'+S,2,0B9H
2429	5098 B9		
2430	5099 FF	DB	0FFH
2431			
2432	509A 45C3100B D0PS:	DB	'E','C'+S,16,0BH
2433	509E 4A4EDA0E	DB	'JN','Z'+S,14,10H
2433	50A2 10		
2434	50A3 41C10027	DB	'A','A'+S,0,27H
2435	50A7 C900F3	DB	'I'+S,0,0F3H
2436	50AA C21A00	DB	'B'+S,26,0
2437	50AD 4546C21A	DB	'EF','B'+S,26,0
2437	50B1 00		
2438	50B2 D71800	DB	'W'+S,24,0
2439	50B5 4546D71B	DB	'EF','W'+S,24,0
2439	50B9 00		
2440	50BA D31C00	DB	'S'+S,28,0
2441	50BD 4546D31C	DB	'EF','S'+S,28,0
2441	50C1 00		
2442	50C2 FF	DB	0FFH
2443			
2444	50C3 D82C00 EDPS:	DB	'X'+S,44,0
2445	50C6 58D800D9	DB	'X','X'+S,0,0D9H
2446	50CA C900FB	DB	'I'+S,0,0FBH
2447	50CD 51D51E00	DB	'Q','U'+S,30,0
2448	50D1 4EC404FF	DB	'N','D'+S,4,0FFH
2449	50D5 FF	DB	0FFH
2450			
2451	50D6 FF F0PS:	DB	0FFH
2452	50D7 FF G0PS:	DB	0FFH
2453			
2454	50D8 414CD400 H0PS:	DB	'AL','T'+S,0,76H
2454	50DC 76		
2455	50DD FF	DB	0FFH
2456			
2457	50DE 4EC31003 I0PS:	DB	'N','C'+S,16,3
2458	50E2 CD2200	DB	'M'+S,34,0
2459	50E5 CE2E00	DB	'N'+S,46,0
2460	50E8 4EC902A2	DB	'N','I'+S,2,0A2H
2461	50E9 4E49D202	DB	'NI','R'+S,2,0B2H
2461	50F0 B2		
2462	50F1 4EC402AA	DB	'N','D'+S,2,0AAH
2463	50F5 4E44D202	DB	'ND','R'+S,2,0BAH
2463	50F9 BA		
2464	50FA FF	DB	0FFH
2465			
2466	50FB D2BC18 J0PS:	DB	'R'+S,12+S,18H
2467	50FE D2AA00	DB	'P'+S,42+S,0
2468	5101 FF	DB	0FFH
2469			
2470	5102 FF K0PS:	DB	0FFH
2471			
2472	5103 C42600 L0PS:	DB	'D'+S,38,0

2473	5106	44C902A0		DB	'D', 'I'+S, 2, 0A0H
2474	510A	4449D202		DB	'DI', 'R'+S, 2, 0B0H
2474	510E	B0			
2475	510F	44C402A8		DB	'D', 'I'+S, 2, 0ABH
2476	5113	4444D202		DB	'DD', 'R'+S, 2, 0B3H
2476	5117	B8			
2477	5118	4F41C424		DB	'DA', 'D'+S, 36, 0
2477	511C	00			
2478	511D	FF		DB	0FFH
2479					
2480	511E	FF	MOPS:	DB	0FFH
2481					
2482	511F	4FD00000	NOPS:	DB	'C', 'P'+S, 2, 0
2483	5123	45C70244		DB	'E', 'G'+S, 2, 44H
2484	5127	FF		DB	0FFH
2485					
2486	5128	D212B6	OOPS:	DB	'R'+S, 18, 0B6H
2487	512B	55D43600		DB	'U', 'T'+S, 54, 0
2488	512F	5554C902		DB	'UT', 'I'+S, 2, 0A3H
2488	5133	A3			
2489	5134	5449D202		DB	'TI', 'R'+S, 2, 0B3H
2489	5138	B3			
2490	5139	5554C402		DB	'UT', 'D'+S, 2, 0ABH
2490	513D	AB			
2491	513E	5444D202		DB	'TD', 'R'+S, 2, 0BBH
2491	5142	BB			
2492	5143	52C72000		DB	'R', 'G'+S, 32, 0
2493	5147	FF		DB	0FFH
2494					
2495	5148	5553C80A	POPS:	DB	'US', 'H'+S, 10, 0C5H
2495	514C	C5			
2496	514D	4FD00AC1		DB	'D', 'P'+S, 10, 0C1H
2497	5151	FF		DB	0FFH
2498					
2499	5152	FF	QOPS:	DB	0FFH
2500					
2501	5153	45D488C0	ROPS:	DB	'E', 'T'+S, 8+5, 0C0H
2502	5157	53D406C7		DB	'S', 'T'+S, 6, 0C7H
2503	515B	45D31686		DB	'E', 'S'+S, 22, 86H
2504	515F	CC1416		DB	'L', 'S', 20, 16H
2505	5162	4CC31406		DB	'L', 'C'+S, 20, 6
2506	5166	4C43C100		DB	'LC', 'A'+S, 0, 7
2506	516A	07			
2507	516B	4CC10017		DB	'L', 'A'+S, 0, 17H
2508	516F	D2141E		DB	'R'+S, 20, 1EH
2509	5172	52C3140E		DB	'R', 'C'+S, 20, 0EH
2510	5175	5243C100		DB	'RC', 'A'+S, 0, 0FH
2510	517A	0F			
2511	517B	52C1001F		DB	'R', 'A'+S, 0, 1FH
2512	517F	4CC4026F		DB	'L', 'D'+S, 2, 6FH
2513	5183	52C40267		DB	'R', 'D'+S, 2, 67H
2514	5187	4554C902		DB	'ET', 'I'+S, 2, 4DH
2514	518B	4D			
2515	518C	4554CE02		DB	'ET', 'N'+S, 2, 45H
2515	5190	45			
2516	5191	FF		DB	0FFH
2517					
2518	5192	42C33400	SOPS:	DB	'B', 'C'+S, 52, 0
2519	5196	43C60037		DB	'C', 'F'+S, 0, 37H
2520	519A	4CC11426		DB	'L', 'A'+S, 20, 26H

2521	519E	52C1142E	DB	'R', 'A'+S, 20, 2EH
2522	51A2	52CC143E	DB	'R', 'L'+S, 20, 3EH
2523	51A6	45D416C6	DB	'E', 'T'+S, 22, 0C6H
2524	51AA	55C21296	DB	'U', 'B'+S, 18, 96H
2525	51AE	FF	DB	0FFH
2526				
2527	51AF	FF	TOPS:	DB 0FFH
2528	51B0	FF	UOPS:	DB 0FFH
2529	51B1	FF	VOPS:	DB 0FFH
2530	51B2	FF	WOPS:	DB 0FFH
2531				
2532	51B3	4FD212AE	XOPS:	DB 'O', 'R'+S, 18, 0AEH
2533	51B7	FF		DB 0FFH
2534				
2535	51B8	FF	YOPS:	DB 0FFH
2536	51B9	FF	ZOPS:	DB 0FFH
2537				
2538	51BA	4EDA0009	CCODES:	DB 'N', 'Z'+S, INZ, CC
2539	51BE	DA0009		DB 'Z'+S, IZ, CC
2540	51C1	4EC31009		DB 'N', 'C'+S, INCY, CC
2541	51C5	C31809		DB 'C'+S, ICY, CC
2542	51C8	50CF2009		DB 'P', 'O'+S, IPO, CC
2543	51CC	50C52809		DB 'P', 'E'+S, IPE, CC
2544	51D0	D03009		DB 'P'+S, IPOS, CC
2545	51D3	CD3809		DB 'M'+S, IMIN, CC
2546	51D6	C20000	TREGS:	DB 'B'+S, IB, TR
2547	51D9	C30100		DB 'C'+S, IC, TR
2548	51DC	C40200		DB 'D'+S, ID, TR
2549	51DF	C50300		DB 'E'+S, IE, TR
2550	51E2	C80400		DB 'H'+S, IH, TR
2551	51E5	CC0500		DB 'L'+S, IL, TR
2552	51E8	C10700		DB 'A'+S, IA, TR
2553	51EB	42C30001	RPAIRS:	DB 'B', 'C'+S, IBC, RP
2554	51EF	44C50201		DB 'D', 'E'+S, IDE, RP
2555	51F3	48CC0401		DB 'H', 'L'+S, IHL, RP
2556	51F7	53D00601		DB 'S', 'P'+S, ISP, RP
2557	51FB	41C60E01		DB 'A', 'F'+S, IAF, RP
2558	51FF	49D8DD02	XYPAIRS:	DB 'I', 'X'+S, IIIX, XY
2559	5203	49D9FD02		DB 'I', 'Y'+S, IIY, XY
2560	5207	C90008	REREGS:	DB 'I'+S, IINT, RE
2561	520A	D20808		DB 'R'+S, IREF, RE
2562	520D	FF		DB 0FFH
2563				
2564			;	Disassembler
2565				
2566			ADCOP:	EQU 0*16+0
2567			ADDOP:	EQU 0*16+1
2568			ANDOP:	EQU 0*16+2
2569			BITOP:	EQU 1*16+0
2570			CALLOP:	EQU 2*16+0
2571			CPOP:	EQU 2*16+1
2572			CCFOP:	EQU 2*16+2
2573			CPLOP:	EQU 2*16+3
2574			CPIOP:	EQU 2*16+4
2575			CPIROP:	EQU 2*16+5
2576			CPDOP:	EQU 2*16+6
2577			CPDROP:	EQU 2*16+7
2578			DECOP:	EQU 3*16+0
2579			DJNZOP:	EQU 3*16+1
2580			DAAOOP:	EQU 3*16+2

2581	DIOP:	EQU	3*16+3
2582	DBOP:	EQU	3*16+4
2583	EXOP:	EQU	4*16+0
2584	EXXOP:	EQU	4*16+1
2585	E1OP:	EQU	4*16+2
2586	HALTOP:	EQU	5*16+0
2587	INCOP:	EQU	6*16+0
2588	IMOP:	EQU	6*16+1
2589	INOP:	EQU	6*16+2
2590	INIOP:	EQU	6*16+3
2591	INIROP:	EQU	6*16+4
2592	INDOP:	EQU	6*16+5
2593	INDROP:	EQU	6*16+6
2594	JROP:	EQU	7*16+0
2595	JPOF:	EQU	7*16+1
2596	LDOF:	EQU	8*16+0
2597	LDIOP:	EQU	8*16+1
2598	LDIROP:	EQU	8*16+2
2599	LDDOP:	EQU	8*16+3
2600	LDDROP:	EQU	8*16+4
2601	NOPDF:	EQU	9*16+0
2602	NEGOF:	EQU	9*16+1
2603	OROF:	EQU	10*16+0
2604	OUTOP:	EQU	10*16+1
2605	OUTIOP:	EQU	10*16+2
2606	OTIOP:	EQU	10*16+3
2607	OUTDOP:	EQU	10*16+4
2608	OTDROP:	EQU	10*16+5
2609	PUSHOP:	EQU	11*16+0
2610	POPOP:	EQU	11*16+1
2611	RETOP:	EQU	12*16+0
2612	RSTOP:	EQU	12*16+1
2613	RESOP:	EQU	12*16+2
2614	RLOP:	EQU	12*16+3
2615	RLCOP:	EQU	12*16+4
2616	RLCAOP:	EQU	12*16+5
2617	RLAOP:	EQU	12*16+6
2618	RROP:	EQU	12*16+7
2619	RRCOP:	EQU	12*16+8
2620	RRCAOP:	EQU	12*16+9
2621	RRAOP:	EQU	12*16+10
2622	RLDOP:	EQU	12*16+11
2623	RRDOP:	EQU	12*16+12
2624	RETIOP:	EQU	12*16+13
2625	RETNOP:	EQU	12*16+14
2626	SBCOP:	EQU	13*16+0
2627	SCFOP:	EQU	13*16+1
2628	SLAOP:	EQU	13*16+2
2629	SRAOP:	EQU	13*16+3
2630	SRLOP:	EQU	13*16+4
2631	SETOP:	EQU	13*16+5
2632	SUBOP:	EQU	13*16+6
2633	XOROP:	EQU	14*16+0
2634			
2635	520E CDBD47	DASM:	CALL STARTSTOP
2636	5211 2B		DEC HL
2637	5212 E5		PUSH HL
2638	5213 19		ADD HL,DE
2639	5214 ED53F940		LD (DSTART),DE
2640	5218 22FB40		LD (DSTOP),HL

2641	521B	2E2D	LD	L,M11&255
2642	521D	CDA847	CALL	PARAMETER
2643	5220	3001	JR	NC,DSM2
2644	5222	EB	EX	DE,HL
2645	5223	22FF40	DSM2:	LD (DRSTART),HL
2646	5226	D1	POP	DE
2647	5227	19	ADD	HL,DE
2648	5228	220141	LD	(DRSTOP),HL
2649	522B	213C59	LD	HL,AEND+1
2650	522E	22E940	LD	(FEP),HL
2651	5231	36FF	LD	(HL),0FFH
2652	5233	23	INC	HL
2653	5234	220541	LD	(DEOAP),HL
2654	5237	2A0741	LD	HL,(DSOSP)
2655	523A	220941	LD	(DEOSP),HL
2656	523D	CD8052	CALL	GETAREAS
2657	5240	CD1C49	CALL	GETOPTION
2658	5243	CD4A52	CALL	DPASS
2659	5246	DDCB00AE	RES	S,(IX+F1)
2660	524A	2AF940	DPASS:	LD HL,(DSTART)
2661	524D	FD2AFF40	LD	IY,(DRSTART)
2662	5251	22FD40	DPS2:	LD (DIP),HL
2663	5254	FD220341	LD	(DRIP),IY
2664	5258	CD3149	CALL	HOLD
2665	525B	DDCB03E6	SET	4,(IX+F4)
2666	525F	CD1B53	CALL	DINSTR
2667	5262	DDCB006E	BIT	S,(IX+F1)
2668	5266	CCD052	CALL	Z,DLIST
2669	5269	ED5BFD40	LD	DE,(DIP)
2670	526D	E5	DPS3:	PUSH HL
2671	526E	2AFB40	LD	HL,(DSTOP)
2672	5271	B7	OR	A
2673	5272	ED52	SBC	HL,DE
2674	5274	E1	POP	HL
2675	5275	C8	RET	Z
2676	5276	13	INC	DE
2677	5277	E5	PUSH	HL
2678	5278	B7	OR	A
2679	5279	ED52	SBC	HL,DE
2680	527B	E1	POP	HL
2681	527C	20EF	JR	NZ,DPS3
2682	527E	18D1	JR	DPS2
2683				
2684	5280	2E21	GETAREAS:	LD L,M9&255
2685	5282	CD1C46	CALL	PR2
2686	5285	ED5B0541	STA2:	LD DE,(DEOAP)
2687	5289	13	INC	DE
2688	528A	13	INC	DE
2689	528B	13	INC	DE
2690	528C	13	INC	DE
2691	528D	2A0741	LD	HL,(DSOSP)
2692	5290	B7	OR	A
2693	5291	ED52	SBC	HL,DE
2694	5293	DA2754	JP	C,E4
2695	5296	CDBD47	CALL	STARTSTOP
2696	5299	2B	DEC	HL
2697	529A	ED5A	ADC	HL,DE
2698	529C	C8	RET	Z
2699	529D	E5	PUSH	HL
2700	529E	2A0541	LD	HL,(DEOAP)

2701	52A1	73	LD	(HL),E
2702	52A2	23	INC	HL
2703	52A3	72	LD	(HL),D
2704	52A4	23	INC	HL
2705	52A5	D1	POP	DE
2706	52A6	73	LD	(HL),E
2707	52A7	23	INC	HL
2708	52A8	72	LD	(HL),D
2709	52A9	23	INC	HL
2710	52AA	220541	LD	(DEOAP),HL
2711	52AD	18D6	JR	GTA2
2712				
2713	52AF	3B04	UNSCRAMBLE:	JR C,UM2
2714	52B1	ED43FD40		LD (DIP),BC
2715	52B5	2AFD40	UM2:	LD HL,(DIP)
2716	52B8	0609		LD B,9
2717	52BA	22FD40	UM3:	LD (DIP),HL
2718	52BD	220341		LD (DRIP),HL
2719	52C0	05		DEC B
2720	52C1	C8		RET Z
2721	52C2	C5		PUSH BC
2722	52C3	DDCB03A6		RES 4,(IX+F4)
2723	52C7	CD1853		CALL DINSTR
2724	52CA	CDD052		CALL DLIST
2725	52CD	C1		POP BC
2726	52CE	18EA		JR UM3
2727				
2728	52D0	DDCB0076	DLIST:	BIT 6,(IX+F1)
2729	52D4	2829		JR Z,DLS3
2730	52D6	3E81		LD A,81H
2731	52D8	DDCB0366		BIT 4,(IX+F4)
2732	52DC	2002		JR NZ,DLS2
2733	52DE	3E01		LD A,0C1H
2734	52E0	DD7701	DLS2:	LD (IX+F2),A
2735	52E3	E5		PUSH HL
2736	52E4	FDE5		PUSH IY
2737	52E6	2AFD40		LD HL,(DIP)
2738	52E9	115441		LD DE,TBUFF
2739	52EC	010400		LD BC,4
2740	52EF	EDE0		LDIR
2741	52F1	ED53E740		LD (TEMP),DE
2742	52F5	2A0341		LD HL,(DRIP)
2743	52F8	CD0F4A		CALL LIST
2744	52FB	FDE1		POP IY
2745	52FD	E1		POP HL
2746	52FE	C9		RET
2747	52FF	E5	DLS3:	PUSH HL
2748	5300	215841		LD HL,TBUFF+4
2749	5303	E5		PUSH HL
2750	5304	CD5548		CALL NX0
2751	5307	2AE140		LD HL,(EOFPP)
2752	530A	E5		PUSH HL
2753	530B	CD3D48		CALL MEMCHECK
2754	530E	D1		POP DE
2755	530F	E1		POP HL
2756	5310	EDB0		LDIR
2757	5312	ED53E140		LD (EOFPP),DE
2758	5316	E1		POP HL
2759	5317	C9		RET
2760				

2761	5318	CD2656	DINSTR:	CALL DECODE
2762	531B	CD5D53		CALL CHKHL
2763	531E	CD7D53		CALL CHKXY
2764	5321	CDBE53		CALL CHKOPD
2765	5324	23		INC HL
2766	5325	D5		PUSH DE
2767	5326	E5		PUSH HL
2768	5327	ED5BFD40		LD DE,(DIP)
2769	532B	B7		OR A
2770	532C	ED52		SBC HL,DE
2771	532E	DD7502		LD (IX+F3),L
2772	5331	FD2A0341		LD IY,(DRIP)
2773	5335	EB		EX DE,HL
2774	5336	FD19		ADD IY,DE
2775	5338	E1		POP HL
2776	5339	D1		POP DE
2777	533A	DDCB006E		BIT 5,(IX+F1)
2778	533E	C0		RET NZ
2779	533F	CD9054		CALL DLABEL
2780	5342	F5		PUSH AF
2781	5343	CDC254		CALL DOUTOPT
2782	5346	3E20		LD A,BLANK
2783	5348	CDDA55		CALL DOUT
2784	534B	78		LD A,B
2785	534C	CDFA54		CALL DOUTOPD
2786	534F	CDB554		CALL COMMA
2787	5352	79		LD A,C
2788	5353	CDFA54		CALL DOUTOPD
2789	5356	3E0D		LD A,CR
2790	5358	CDDA55		CALL DOUT
2791	535B	F1		POP AF
2792	535C	C9		RET
2793				
2794	535D	F5	CHKHL:	PUSH AF
2795	535E	78		LD A,B
2796	535F	CD6A53		CALL SWAPHL
2797	5362	47		LD B,A
2798	5363	79		LD A,C
2799	5364	CD6A53		CALL SWAPHL
2800	5367	4F		LD C,A
2801	5368	F1		POP AF
2802	5369	C9		RET
2803				
2804	536A	FE06	SWAPHL:	CP TR*16+6
2805	536C	C0		RET NZ
2806	536D	3E54		LD A,RPI*16+IHL
2807	536F	DDCB034E		BIT 1,(IX+F4)
2808	5373	C8		RET Z
2809	5374	3EA0		LD A,XYD*16
2810	5376	DDCB0356		BIT 2,(IX+F4)
2811	537A	C0		RET NZ
2812	537B	23		INC HL
2813	537C	C9		RET
2814				
2815	537D	DDCB034E	CHKXY:	BIT 1,(IX+F4)
2816	5381	C8		RET Z
2817	5382	F5		PUSH AF
2818	5383	78		LD A,B
2819	5384	CDA053		CALL SWAPXY
2820	5387	47		LD B,A

2821	53B8	79		LD	A,C
2822	53B9	CDA053		CALL	SWAPXY
2823	53B0	4F		LD	C,A
2824	53B0	F1		POP	AF
2825	53B8	DDCB035E		BIT	3,(IX+F4)
2826	53B2	2B09		JR	Z,CXY2
2827	53B4	FE40		CP	EXOP
2828	53B6	C0		RET	NZ
2829	53B7	78		LD	A,B
2830	53B8	FE12		CP	RP*16+IDE
2831	53B9	3E40		LD	A,EXOP
2832	53B0	C0		RET	NZ
2833	53B0	3E34	CXY2:	LD	A,DBOP
2834	53B9	C9		RET	
2835					
2836	53A0	C5	SWAPXY:	PUSH	BC
2837	53A1	47		LD	B,A
2838	53A2	FEA0		CP	XYD*16
2839	53A4	2B0C		JR	Z,SXY2
2840	53A6	0620		LD	B,XY*16
2841	53A8	FE14		CP	RP*16+IHL
2842	53AA	2B06		JR	Z,SXY2
2843	53AC	0660		LD	B,XYI*16
2844	53AE	FE54		CP	RPI*16+IHL
2845	53B0	2B0A		JR	NZ,SXY3
2846	53B2	DDCB03DE	SXY2:	SET	3,(IX+F4)
2847	53B4	DD7E03		LD	A,(IX+F4)
2848	53B9	E601		AND	1
2849	53B8	B0		OR	B
2850	53B0	C1	SXY3:	POP	BC
2851	53B0	C9		RET	
2852					
2853	53B8	FD2AFD40	CHKOPD:	LD	IY,(DIP)
2854	53C2	FD5602		LD	D,(IY+2)
2855	53C5	FE61		CP	IMOP
2856	53C7	C8		RET	Z
2857	53C8	FEC1		CP	RSTOP
2858	53CA	C8		RET	Z
2859	53CB	FE10		CP	BITOP
2860	53CD	C8		RET	Z
2861	53CE	FED5		CP	SETOP
2862	53D0	C8		RET	Z
2863	53D1	FEC2		CP	RESOP
2864	53D3	C8		RET	Z
2865	53D4	F5		PUSH	AF
2866	53D5	CDDA53		CALL	GETOPD
2867	53D8	F1		POP	AF
2868	53D9	C9		RET	
2869					
2870	53DA	FE34	GETOPD:	CP	DBOP
2871	53DC	2008		JR	NZ,GD2
2872	53DE	01B0C0		LD	BC,TNO*256+EOL*16
2873	53E1	2AFD40		LD	HL,(DIP)
2874	53E4	5E		LD	E,(HL)
2875	53E5	C9		RET	
2876	53E6	FE70	GD2:	CP	JROP
2877	53E8	2B04		JR	Z,GD22
2878	53EA	FE31		CP	DJNZOP
2879	53EC	2B05		JR	NZ,GD3
2880	53EE	CD2C54	GD22:	CALL	OFFSET

2881	53F1	1810		JR	GD5
2882	53F3	CD4B54	GD3:	CALL	CHKTNO
2883	53F6	2003		JR	NZ, GD4
2884	53F8	23		INC	HL
2885	53F9	5E		LD	E, (HL)
2886	53FA	C9		RET	
2887	53FB	CD3F54	GD4:	CALL	CHKNO
2888	53FE	C0		RET	NZ
2889	53FF	23		INC	HL
2890	5400	5E		LD	E, (HL)
2891	5401	23		INC	HL
2892	5402	56		LD	D, (HL)
2893	5403	DDCB006E	GD5:	BIT	5, (IX+F1)
2894	5407	C8		RET	Z
2895	5408	CD5754		CALL	DBOUND
2896	540B	D8		RET	C
2897	540C	CD6B54		CALL	DSYMSCH
2898	540F	D0		RET	NC
2899	5410	E5		PUSH	HL
2900	5411	2A0941		LD	HL, (DEOSPF)
2901	5414	E5		PUSH	HL
2902	5415	23		INC	HL
2903	5416	23		INC	HL
2904	5417	23		INC	HL
2905	5418	CD3248		CALL	SOF
2906	541B	380A		JR	C,E4
2907	541D	E1		POP	HL
2908	541E	73		LD	(HL), E
2909	541F	23		INC	HL
2910	5420	72		LD	(HL), D
2911	5421	23		INC	HL
2912	5422	220941		LD	(DEOSPF), HL
2913	5425	E1		POP	HL
2914	5426	C9		RET	
2915					
2916	5427	2E3F	E4:	LD	L, M14&255
2917	5429	C31446		JP	ERR
2918					
2919	542C	23	OFFSET:	INC	HL
2920	542D	1600		LD	D, 0
2921	542F	5E		LD	E, (HL)
2922	5430	E5		PUSH	HL
2923	5431	2A0341		LD	HL, (DRIP)
2924	5434	23		INC	HL
2925	5435	23		INC	HL
2926	5436	CB7B		BIT	7, E
2927	5438	2801		JR	Z, OFS2
2928	543A	15		DEC	D
2929	543B	19	OFS2:	ADD	HL, DE
2930	543C	EB		EX	DE, HL
2931	543D	E1		POP	HL
2932	543E	C9		RET	
2933					
2934	543F	78	CHKNO:	LD	A, B
2935	5440	CD4554		CALL	CKN2
2936	5443	C8		RET	Z
2937	5444	79		LD	A, C
2938	5445	FE30	CKN2:	CP	NO*16
2939	5447	C8		RET	Z
2940	5448	FE70		CP	NOI*16

2941	544A C9		RET
2942			
2943	544B 78	CHKTN0:	LD A,B
2944	544C CD5154		CALL CKTN2
2945	544F C8		RET Z
2946	5450 79		LD A,C
2947	5451 FEC0	CKTN2:	CP TNO*16
2948	5453 C8		RET Z
2949	5454 FED0		CP TNO1*16
2950	5456 C9		RET
2951			
2952	5457 E5	DBOUND:	PUSH HL
2953	5458 D5		PUSH DE
2954	5459 EB		EX DE,HL
2955	545A ED5BFF40		LD DE,(DRSTART)
2956	545E B7		OR A
2957	545F ED52		SBC HL,DE
2958	5461 D1		POP DE
2959	5462 3805		JR C,DBD2
2960	5464 2A0141		LD HL,(DRSTOP)
2961	5467 ED52		SBC HL,DE
2962	5469 E1	DBD2:	POP HL
2963	546A C9		RET
2964			
2965	546B DDCB0366	DSYMSCH:	BIT 4,(IX+F4)
2966	546F 37		SCF
2967	5470 C8		RET Z
2968	5471 C5		PUSH BC
2969	5472 E5		PUSH HL
2970	5473 2A0741		LD HL,(DSOSP)
2971	5476 ED4B0941	DSS2:	LD BC,(DEOSP)
2972	547A B7		OR A
2973	547B ED42		SBC HL,BC
2974	547D 09		ADD HL,BC
2975	547E 37		SCF
2976	547F 280C		JR Z,DSS3
2977	5481 4E		LD C,(HL)
2978	5482 23		INC HL
2979	5483 46		LD B,(HL)
2980	5484 23		INC HL
2981	5485 EB		EX DE,HL
2982	5486 B7		OR A
2983	5487 ED42		SBC HL,BC
2984	5489 09		ADD HL,BC
2985	548A EB		EX DE,HL
2986	548B 20E9		JR NZ,DSS2
2987	548D E1	DSS3:	POP HL
2988	548E C1		POP BC
2989	548F C9		RET
2990			
2991	5490 F5	DLABEL:	PUSH AF
2992	5491 D5		PUSH DE
2993	5492 E5		PUSH HL
2994	5493 215841		LD HL,TBUFF+4
2995	5496 22E740		LD (TEMP),HL
2996	5499 ED5B0341		LD DE,(DRIP)
2997	549D CD6B54		CALL DSYMSCH
2998	54A0 3E00		LD A,0
2999	54A2 380A		JR C,DLB2
3000	54A4 CD8855		CALL DN2

3001	54A7	3E3A		LD	A, ','
3002	54A9	CDDASS		CALL	DOUT
3003	54AC	3E06		LD	A,6
3004	54AE	DD7706	DLB2:	LD	(IX+F7),A
3005	54B1	E1		POP	HL
3006	54B2	D1		POP	DE
3007	54B3	F1		POP	AF
3008	54B4	C9		RET	
3009					
3010	54B5	78	COMMA:	LD	A,B
3011	54B6	FEB0		CP	EOL*16
3012	54B8	C8		RET	Z
3013	54B9	79		LD	A,C
3014	54BA	FEB0		CP	EOL*16
3015	54BC	C8		RET	Z
3016	54BD	3E2C		LD	A, ','
3017	54BF	C3DASS		JP	DOUT
3018					
3019	54C2	C5	DOUTOPT:	PUSH	BC
3020	54C3	D5		PUSH	DE
3021	54C4	E5		PUSH	HL
3022	54C5	47		LD	B,A
3023	54C6	CDD054		CALL	GETKEY
3024	54C9	CDEBS4		CALL	KEYADDR
3025	54CC	C641		ADD	A,'A'
3026	54CE	CDDA55		CALL	DOUT
3027	54D1	CD5D55		CALL	DC2
3028	54D4	0C		INC	C
3029	54D5	DD7105		LD	(IX+F6),C
3030	54D8	E1		POP	HL
3031	54D9	D1		POP	DE
3032	54DA	C1		POP	BC
3033	54DB	C9		RET	
3034					
3035	54DC	211756	GETKEY:	LD	HL,KEYTRAN
3036	54DF	0F	GK2:	RRCA	
3037	54E0	0F		RRCA	
3038	54E1	0F		RRCA	
3039	54E2	0F		RRCA	
3040	54E3	E60F		AND	0FH
3041	54E5	5F		LD	E,A
3042	54E6	1600		LD	D,0
3043	54E8	19		ADD	HL,DE
3044	54E9	7E		LD	A,(HL)
3045	54EA	C9		RET	
3046					
3047	54EB	213150	KEYADDR:	LD	HL,KEYTB
3048	54EE	D5		PUSH	DE
3049	54EF	5F		LD	E,A
3050	54F0	1600		LD	D,0
3051	54F2	19		ADD	HL,DE
3052	54F3	19		ADD	HL,DE
3053	54F4	5E		LD	E,(HL)
3054	54F5	23		INC	HL
3055	54F6	56		LD	D,(HL)
3056	54F7	EB		EX	DE,HL
3057	54F8	D1		POP	DE
3058	54F9	C9		RET	
3059					
3060	54FA	C5	DOUTOPD:	PUSH	BC

3061	54FB	D5		PUSH DE
3062	54FC	E5		PUSH HL
3063	54FD	47		LD R,A
3064	54FE	CDE555		CALL CHKIND
3065	5501	F5		PUSH AF
3066	5502	3E28		LD A,' '
3067	5504	CCDA55		CALL Z,DOUT
3068	5507	CD1455		CALL DOPD
3069	550A	F1		POP AF
3070	550B	3E29		LD A,' '
3071	550D	CCDA55		CALL Z,DOUT
3072	5510	E1		POP HL
3073	5511	D1		POP DE
3074	5512	C1		POP BC
3075	5513	C9		RET
3076				
3077	5514	D5	DOPD:	PUSH DE
3078	5515	212055		LD HL,DOPDTAB
3079	5518	78		LD A,B
3080	5519	CDDF54		CALL GK2
3081	551C	5F		LD E,A
3082	551D	19		ADD HL,DE
3083	551E	D1		POP DE
3084	551F	E9		JP (HL)
3085				
3086	5520	0E	DOPDTAB:	DB DOTR-\$
3087	5521	1A		DB DORP-\$
3088	5522	28		DB DOXY-\$
3089	5523	56		DB DONO-\$
3090	5524	0A		DB DOTR-\$
3091	5525	16		DB DORP-\$
3092	5526	24		DB DOXY-\$
3093	5527	52		DB DONO-\$
3094	5528	27		DB DORE-\$
3095	5529	31		DB DOCC-\$
3096	552A	3A		DB DOXYD-\$
3097	552B	B9		DB DUT2-\$
3098	552C	68		DB DOTNO-\$
3099	552D	83		DB DOTNOI-\$
3100				
3101	552E	21D651	DOTR:	LD HL,TREGS
3102	5531	78		LD A,B
3103	5532	E60F		AND 0FH
3104	5534	FE07		CP IA
3105	5536	2026		JR NZ,DC3
3106	5538	3D		DEC A
3107	5539	1B23		JR DC3
3108				
3109	553B	21EB51	DORP:	LD HL,FPAIRS
3110	553E	78		LD A,B
3111	553F	E60F		AND 0FH
3112	5541	0F		RRCA
3113	5542	FE07		CP 1AF/2
3114	5544	2018		JR NZ,DC3
3115	5546	3E04		LD A,4
3116	5548	1B14		JR DC3
3117				
3118	554A	21FF51	DOXY:	LD HL,XYPAIRS
3119	554D	1B0E		JR DC2
3120				

3121	554F	210752	DORE:	LD	HL, REREGS
3122	5552	78		LD	A,B
3123	5553	E60F		AND	0FH
3124	5555	0F		RRCA	
3125	5556	0F		RRCA	
3126	5557	0F		RRCA	
3127	5558	1804		JR	DC3
3128					
3129	555A	21BA51	DOCC:	LD	HL, CCODES
3130	555D	78	DC2:	LD	A,B
3131	555E	CDDA55	DC3:	CALL	IDFIND
3132	5561	C30856		JP	IDOUT
3133					
3134	5564	CD4A55	DOXYD:	CALL	DOXY
3135	5567	3E2B		LD	A, '+'
3136	5569	CB7A		BIT	7,D
3137	556B	2806		JR	Z, DDXD2
3138	556D	7A		LD	A,D
3139	556E	ED44		NEG	
3140	5570	57		LD	D,A
3141	5571	3E2D		LD	A, '-'
3142	5573	CDDA55	DXD2:	CALL	DOUT
3143	5576	7A		LD	A,D
3144	5577	1838		JR	DTNI2
3145					
3146	5579	CD6B54	DONO:	CALL	DSYMSCH
3147	557C	300A		JR	NC, DN2
3148	557E	7A		LD	A,D
3149	557F	CDC055		CALL	DOUTH8
3150	5582	7B		LD	A,E
3151	5583	CDC955		CALL	DHB2
3152	5586	1834		JR	DTNI4
3153	5588	3E4C	DN2:	LD	A, 'L'
3154	558A	CDDA55		CALL	DOUT
3155	558D	7A		LD	A,D
3156	558E	CDC955		CALL	DHB2
3157	5591	7B		LD	A,E
3158	5592	1835		JR	DHB2
3159					
3160	5594	7B	DOTNO:	LD	A,E
3161	5595	FE41		CP	'A'
3162	5597	3817		JR	C, DOTNOI
3163	5599	FE5B		CP	'Z' +1
3164	559B	3808		JR	C, DTN2
3165	559D	FE61		CP	'a'
3166	559F	380F		JR	C, DOTNOI
3167	55A1	FE7B		CP	'z' +1
3168	55A3	300B		JR	NC, DOTNOI
3169	55A5	CDAC55	DTN2:	CALL	DTN3
3170	55A8	7B		LD	A,E
3171	55A9	CDDA55		CALL	DOUT
3172	55AC	3E27	DTN3:	LD	A, " "
3173	55AE	182A		JR	DOUT
3174					
3175	55B0	7B	DOTNOI:	LD	A,E
3176	55B1	FE0A	DTNI2:	CP	10
3177	55B3	3004		JR	NC, DTNI3
3178	55B5	C630		ADD	A, '0'
3179	55B7	1821		JR	DOUT
3180	55B9	CDC055	DTNI3:	CALL	DOUTH8

3181 558C 3E48	DTN14:	LD A, H
3182 558E 181A		JR DOUT
3183		
3184 55C0 FEA0	DOUTHB:	CP 0A0H
3185 55C2 F5		PUSH AF
3186 55C3 3E30		LD A, (HL)
3187 55C5 D4DASS		CALL NC, DOUT
3188 55C8 F1		SOP AF
3189 55C9 F5	DHB2:	PUSH AF
3190 55CA 0F		RRCA
3191 55CB 0F		RRCA
3192 55CC 0F		RRCA
3193 55CD 0F		RRCA
3194 55CE CDD255		CALL DHB3
3195 55D1 F1		POP AF
3196 55D2 E60F	DHB3:	AND 0FH
3197 55D4 C690		ADD A, 90H
3198 55D6 27		DAA
3199 55D7 CE40		ADC A, 40H
3200 55D9 27		DAA
3201 55DA E5	DOUT:	PUSH HL
3202 55D0 2AE740		LD HL, (TEMP)
3203 55D6 77		LD (HL), A
3204 55D9 23		INC HL
3205 55E0 22E740		LD (TEMP), HL
3206 55E3 E1		POP HL
3207 55E4 C9	DUT2:	RET
3209		
3209 55E5 7B	CHKIND:	LD A, B
3210 55E6 E6F0		AND 0F0H
3211 55E8 FE50		CP RP1*16
3212 55EA C8		RET Z
3213 55EB FE40		CP TRI*16
3214 55ED C8		RET Z
3215 55EE FE70		CP NOI*16
3216 55F0 C8		RET Z
3217 55F1 FED0		CP TNOT*16
3218 55F3 C8		RET Z
3219 55F4 FE60		CP XY1*16
3220 55F6 C8		RET Z
3221 55F7 FEA0		CP XYD*16
3222 55F9 C9		RET
3223		
3224 55FA E60F	IDFIND:	AND 0FH
3225 55FC C8		RET Z
3226 55FD CB7E	IDF2:	BIT 7, (HL)
3227 55FF 23		INC HL
3228 5600 28FB		JR Z, IDF2
3229 5602 23		INC HL
3230 5603 23		INC HL
3231 5604 3D		DEC A
3232 5605 20F6		JR NZ, IDF2
3233 5607 C9		RET
3234		
3235 5608 0E00	IDOUT:	LD C, 0
3236 560A 7E	IDT2:	LD A, (HL)
3237 560B CBBF		RES 7, A
3238 560D CDDASS		CALL DOUT
3239 5610 0C		INC C
3240 5611 CB7E		BIT 7, (HL)

3241	5613	23		INC	HL
3242	5614	28F4		JR	Z, IDT2
3243	5616	C9		RET	
3244					
3245	5617	00	KEYTRAN:	DB	'A'-'A'
3246	5618	01		DB	'B'-'A'
3247	5619	02		DB	'C'-'A'
3248	561A	03		DB	'D'-'A'
3249	561B	04		DB	'E'-'A'
3250	561C	07		DB	'H'-'A'
3251	561D	08		DB	'I'-'A'
3252	561E	09		DB	'J'-'A'
3253	561F	0B		DB	'L'-'A'
3254	5620	0D		DB	'N'-'A'
3255	5621	0E		DB	'O'-'A'
3256	5622	0F		DB	'P'-'A'
3257	5623	11		DB	'R'-'A'
3258	5624	12		DB	'S'-'A'
3259	5625	17		DB	'X'-'A'
3260					
3261	5626	CD9D57	DECODE:	CALL	CHKAREAS
3262	5629	3E34		LD	A,DBOF
3263	562B	D8		RET	C
3264	562C	DD7E03		LD	A,(IX+F4)
3265	562F	E6F0		AND	0F0H
3266	5631	47		LD	B,A
3267	5632	2AFD40		LD	HL,(DIP)
3268	5635	7E		LD	A,(HL)
3269	5636	FEDD		CP	0DDH
3270	5638	2805		JR	Z,DCD2
3271	563A	04		INC	B
3272	563B	FEFD		CP	0FDH
3273	563D	2004		JR	NZ,DCD3
3274	563F	CBC8	DCD2:	SET	1,B
3275	5641	23		INC	HL
3276	5642	7E		LD	A,(HL)
3277	5643	DD7003	DCD3:	LD	(IX+F4),B
3278	5646	01B0B0		LD	BC,EOL*256+EOL*16
3279	5649	110000		LD	DE,0
3280	564C	FEED		CP	0EDH
3281	564E	CA7057		JP	Z,DG6D
3282	5651	FECB		CP	0CBH
3283	5653	CA3757		JP	Z,DGCB
3284	5656	FE40		CP	40H
3285	5658	DAE356		JP	C,DG00
3286	565B	FE80		CP	80H
3287	565D	3872		JR	C,DG40
3288	565F	FEC0		CP	0C0H
3289	5661	3854		JR	C,DG80
3290					
3291	5663	E607	DGC0:	AND	7
3292	5665	2835		JR	Z,DGC00
3293	5667	FD21D957		LD	IY,DGC0TAB1
3294	566B	3D		DEC	A
3295	566C	2839		JR	Z,DGC0135
3296	566E	3D		DEC	A
3297	566F	2825		JR	Z,DGC02
3298	5671	FD21F157		LD	IY,DGC0TAB3
3299	5675	3D		DEC	A
3300	5676	282F		JR	Z,DGC0135

3301	5678	3D	DEC	A
3302	5679	2817	JR	Z,DGC04
3303	567B	FD210958	LD	IY,DGC0TA25
3304	567F	3D	DEC	A
3305	5680	2825	JR	Z,DGC0135
3306	5682	3D	DEC	A
3307	5683	2809	JR	Z,DGC06
3308	5685	7E	DGC07:	LD A,(HL)
3309	5686	E638		AND 38H
3310	5688	5F		LD E,A
3311	5689	0600		LD B,TNO*16
3312	568B	3EC1		LD A,RET0P
3313	568D	C9		RET
3314	568E	0600	DGC06:	LD B,TNO*16
3315	5690	1829		JF D6B02
3316	5692	3E20	DGC04:	LD A,CALLOP
3317	5694	1802		JR DGC022
3318	5696	3E71	DGC02:	LD A,JP0P
3319	5698	0E30	DGC022:	LD C,N0*16
3320	569A	1802		JR DGC002
3321	569C	3EC0	DGC00:	LD A,RET0P
3322	569E	F5	DGC002:	PUSH AF
3323	569F	CDDC57		CALL TRIPLET
3324	56A2	F690		OR CC*16
3325	56A4	47		LD B,A
3326	56A5	F1		POP AF
3327	56A6	C9		RET
3328	56A7	CDDC57	DGC0135:	CALL TRIPLET
3329	56AA	5F	DGC01352:	LD E,A
3330	56AB	07		RLCA
3331	56AC	83		ADD A,E
3332	56AD	CDDC57		CALL DGC04
3333	56B0	FD4601		LD B,(IY+1)
3334	56B3	FD4E02		LD C,(IY+2)
3335	56B6	C9		RET
3336				
3337	56B7	CDDC57	D6B0:	CALL GETREG
3338	56BA	47		LD B,A
3339	56BB	FD212158	DG802:	LD IY,DG80TAB
3340	56BF	CD5057		CALL DGC03
3341	56C2	FE01		CP ADDOP
3342	56C4	2807		JR Z,DG803
3343	56C6	FE00		CP ADCOP
3344	56C8	2803		JR Z,DG803
3345	56CA	FED0		CP SBCOP
3346	56CC	C0		RET NZ
3347	56CD	48	DG803:	LD C,B
3348	56CE	0607		LD B,TR*16+IA
3349	56D0	C9		RET
3350				
3351	56D1	FE76	DG40:	CP 76H
3352	56D3	3E50		LD A,HALTOP
3353	56D5	C8		RET Z
3354	56D6	CDDC57		CALL GETREG
3355	56D9	4F		LD C,A
3356	56DA	CDDC57	DG402:	CALL TRIPLET
3357	56DD	F600		OR TR*16
3358	56DF	47		LD B,A
3359	56E0	3E80		LD A,LDDP
3360	56E2	C9		RET

3361				
3362	56E3	FD212958	DG00:	LD IY,DG00TAB0
3363	56E7	E607		AND 7
3364	56E9	2BBC		JR Z,DGC0135
3365	56EB	3D		DEC A
3366	56EC	2B3B		JR Z,DG001
3367	56EE	FD214158		LD IY,DG00TAB2
3368	56F2	3D		DEC A
3369	56F3	2BB2		JR Z,DGC0135
3370	56F5	3D		DEC A
3371	56F6	2B20		JR Z,DG003
3372	56F8	3D		DEC A
3373	56F9	2B12		JR Z,DG004
3374	56FB	3D		DEC A
3375	56FC	2B0B		JR Z,DG005
3376	56FE	FD215958		LD IY,DG00TAB7
3377	5702	3D		DEC A
3378	5703	204B		JR NZ,DGC83
3379	5705	0EC0	DG006:	LD C,TNO*16
3380	5707	1BD1		JR DG402
3381	5709	3E30	DG005:	LD A,DECOP
3382	570B	1B02		JR DG0042
3383	570D	3E60	DG004:	LD A,INCOP
3384	570F	F5	DG0042:	PUSH AF
3385	5710	CDC057		CALL TRIPLET
3386	5713	F600		OR TR*16
3387	5715	47		LD B,A
3388	5716	F1		POP AF
3389	5717	C9		RET
3390	5718	7E	DG003:	LD A,(HL)
3391	5719	0F		RRCA
3392	571A	0F		RRCA
3393	571B	0F		RRCA
3394	571C	E606		AND 6
3395	571E	F610		OR RP*16
3396	5720	47		LD B,A
3397	5721	3E60		LD A,INCOP
3398	5723	CB5E		BIT 3,(HL)
3399	5725	C8		RET Z
3400	5726	3E30		LD A,DECOP
3401	5728	C9		RET
3402	5729	CD1857	DG001:	CALL DG003
3403	572C	0E30		LD C,N0*16
3404	572E	3E80		LD A,LDDP
3405	5730	C8		RET Z
3406	5731	48		LD C,B
3407	5732	0614		LD B,RP*16+IHL
3408	5734	3E01		LD A,ADDOP
3409	5736	C9		RET
3410				
3411	5737	23	DGC8:	INC HL
3412	5738	DDCB034E		BIT 1,(IX+F4)
3413	573C	2B05		JR Z,DGC81
3414	573E	DDCB03D6		SET 2,(IX+F4)
3415	5742	23		INC HL
3416	5743	7E	DGC81:	LD A,(HL)
3417	5744	E6C0		AND 0C0H
3418	5746	2012		JR NZ,DGC85
3419	5748	FD216158		LD IY,DGC8TAB1
3420	574C	.CDC357		CALL GETREG

3421	574F	47		LD	B,A
3422	5750	CDC057	DGCB3:	CALL	TRIPLET
3423	5753	5F	DGCB4:	LD	E,A
3424	5754	FD19		ADD	IY,DE
3425	5756	FD7E00		LD	A,(IY+0)
3426	5759	C9		RET	
3427	575A	FD21A658	DGCB5:	LD	IY,DGC0TAE2-1
3429	575E	07		RLCA	
3429	575F	07		RLCA	
3430	5760	CD5357		CALL	DGCBA4
3431	5763	F5		PUSH	AF
3432	5764	CDD057		CALL	GETREG
3433	5767	4F		LD	C,A
3434	5768	CDC057		CALL	TRIPLET
3435	576B	5F		LD	E,A
3436	576C	0600		LD	B,TNO*16
3437	576E	F1		POP	AF
3438	576F	C9		RET	
3439					
3440	5770	DDCB034E	DGED:	BIT	1,(IX+F4)
3441	5774	2024		JR	NZ,DGED4
3442	5776	23		INC	HL
3443	5777	7E		LD	A,(HL)
3444	5778	D640		SUB	40H
3445	577A	381E		JR	C,DGED4
3446	577C	FE30		CP	3CH
3447	577E	300E		JR	NC,DGED3
3448	5780	FD21AC58		LD	IY,DGEDTAB1
3449	5784	CDAAB6		CALL	DGC01352
3450	5787	FE61		UP	IMOP
3451	5789	C0		RET	NZ
3452	578A	59		LD	E,C
3453	578B	0EB0		LD	C,EOL*16
3454	578D	C9		RET	
3455	578E	D660	DGED3:	SUB	60H
3456	5790	380B		JR	C,DGED4
3457	5792	FD212059		LD	IY,DGEDTAB2
3458	5796	FE1C		CP	1CH
3459	5798	38B9		JR	C,DGCB4
3460	579A	3E34	DGED4:	LD	A,DBOP
3461	579C	C9		RET	
3462					
3463	579D	B7	CHKAREAS:	OR	A
3464	579E	DDCB0366		BIT	4,(IX+F4)
3465	57A2	C8		RET	Z
3466	57A3	213D59		LD	HL,AEND+2
3467	57A6	E5	CKA2:	PUSH	HL
3468	57A7	ED5B0541		LD	DE,(DEOAP)
3469	57AB	B7		OR	A
3470	57AC	ED52		SBC	HL,DE
3471	57AE	E1		POP	HL
3472	57AF	C8		RET	Z
3473	57B0	5E		LD	E,(HL)
3474	57B1	23		INC	HL
3475	57B2	56		LD	D,(HL)
3476	57B3	23		INC	HL
3477	57B4	4E		LD	C,(HL)
3478	57B5	23		INC	HL
3479	57B6	46		LD	B,(HL)
3480	57B7	23		INC	HL

3481 57B8 E5		PUSH HL
3482 57B9 2AFD40		LD HL,(DIP)
3483 57BC B7		OR A
3484 57BD ED52		SBC HL,DE
3485 57BF 3F		CCF
3486 57C0 3004		JR NC,CKA3
3487 57C2 19		ADD HL,DE
3488 57C3 B7		OR A
3489 57C4 ED42		SBC HL,BC
3490 57C6 E1	CKA3:	POP HL
3491 57C7 D8		RET C
3492 57C8 37		SCF
3493 57C9 CB		RET Z
3494 57CA 18DA		JR CKA2
3495		
3496 57CC 7E	TRIPLET:	LD A,(HL)
3497 57CD 0F		RRCA
3498 57CE 0F		RRCA
3499 57CF 0F		RRCA
3500 57D0 E607		AND 7
3501 57D2 C9		RET
3502		
3503 57D3 7E	GETREG:	LD A,(HL)
3504 57D4 E607		AND 7
3505 57D6 F600		OR TR*16
3506 57D8 C9		RET
3507		
3508 57D9 B1	DGC0TAB1:	DB F0F0P
3509 57DA 10		DB RP*16+IBC
3510 57DB B0		DB EOL*16
3511 57DC C0		DB RETOP
3512 57DD B0		DB EOL*16
3513 57DE B0		DB EOL*16
3514 57DF B1		DB F0F0P
3515 57E0 12		DB RP*16+IDE
3516 57E1 B0		DB EOL*16
3517 57E2 41		DB EXXOP
3518 57E3 B0		DB EOL*16
3519 57E4 B0		DB EOL*16
3520 57E5 B1		DB POPOP
3521 57E6 14		DB RP*16+IHL
3522 57E7 B0		DB EOL*16
3523 57E8 71		DB JPOP
3524 57E9 54		DB RPI*16+IHL
3525 57EA B0		DB EOL*16
3526 57EB B1		DB POPOP
3527 57EC 1E		DB RP*16+IAF
3528 57ED B0		DB EOL*16
3529 57EE B0		DB LDOP
3530 57EF 16		DB RP*16+ISP
3531 57F0 14		DB RP*16+IHL
3532		
3533 57F1 71	DGC0TAB3:	DB JFOP
3534 57F2 30		DB NO*16
3535 57F3 B0		DB EOL*16
3536 57F4 34		DB DBOP
3537 57F5 B0		DB EOL*16
3538 57F6 B0		DB EOL*16
3539 57F7 A1		DB OUTOP
3540 57F8 D0		DB TN0I*16

3541	57F9	07	DB	TR*16+IA
3542	57FA	62	DB	INOP
3543	57FB	07	DB	TR*16+IA
3544	57FC	D0	DB	TNOI*16
3545	57FD	40	DB	EXOP
3546	57FE	56	DB	RPI*16+ISP
3547	57FF	14	DB	RP*16+IHL
3548	5800	40	DB	EXOP
3549	5801	12	DB	RP*16+IDE
3550	5802	14	DB	RP*16+IHL
3551	5803	33	DB	DIOP
3552	5804	B0	DB	EOL*16
3553	5805	B0	DB	EOL*16
3554	5806	42	DB	EIOP
3555	5807	B0	DB	EOL*16
3556	5808	B0	DB	EOL*16
3557				
3558	5809	B0	DDC0TAB5:	DB PUSHOP
3559	580A	10		DB RP*16+IBC
3560	580B	B0		DB EOL*16
3561	580C	20		DB CALLOP
3562	580D	30		DB NO*16
3563	580E	B0		DB EOL*16
3564	580F	B0		DB PUSHOP
3565	5810	12		DB RP*16+IDE
3566	5811	B0		DB EOL*16
3567	5812	34		DB DBOP
3568	5813	B0		DB EOL*16
3569	5814	B0		DB EOL*16
3570	5815	B0		DB PUSHOP
3571	5816	14		DB RP*16+IHL
3572	5817	B0		DB EOL*16
3573	5818	34		DB DBOP
3574	5819	B0		DB EOL*16
3575	581A	B0		DB EOL*16
3576	581B	B0		DB PUSHOP
3577	581C	1E		DB RP*16+IAF
3578	581D	B0		DB EOL*16
3579	581E	34		DB DBOP
3580	581F	B0		DB EOL*16
3581	5820	B0		DB EOL*16
3582				
3583	5821	01	DDG0TAB:	DB ADDOP
3584	5822	00		DB ADCOP
3585	5823	D6		DB SUBOP
3586	5824	D0		DB SECOP
3587	5825	02		DB ANDOP
3588	5826	E0		DB XOROP
3589	5827	A0		DB CROP
3590	5828	21		DB CPOP
3591				
3592	5829	90	DG00TAB0:	DB NOPOP
3593	582A	B0		DB EOL*16
3594	582B	B0		DB EOL*16
3595	582C	40		DB EXOP
3596	582D	1E		DB RP*16+IAF
3597	582E	1E		DB RP*16+IAF
3598	582F	31		DB DJNZOP
3599	5830	30		DB NO*16
3600	5831	B0		DB EOL*16

3601	5832	70		DB	JROP
3602	5833	30		DB	NO*16
3603	5834	B0		DB	EOL*16
3604	5835	70		DB	JROP
3605	5836	90		DB	CC*128+INZ/8
3606	5837	30		DB	NO*16
3607	5838	70		DB	JROP
3608	5839	91		DB	CC*128+IZ/8
3609	583A	30		DB	NO*16
3610	583B	70		DB	JROP
3611	583C	92		DB	CC*128+INDY/8
3612	583D	30		DB	NO*16
3613	583E	70		DB	JROP
3614	583F	93		DB	CC*128+ICY/8
3615	5840	30		DB	NO*16
3616					
3617	5841	80	DG00TAB2:	DB	LDOP
3618	5842	50		DB	RPI*16+IBC
3619	5843	07		DB	TR*16+IA
3620	5844	80		DB	LDOP
3621	5845	07		DB	TR*16+IA
3622	5846	50		DB	RPI*16+IBC
3623	5847	80		DB	LDOP
3624	5848	52		DB	RPI*16+IDE
3625	5849	07		DB	TR*16+IA
3626	584A	80		DB	LDOP
3627	584B	07		DB	TR*16+IA
3628	584C	52		DB	RPI*16+IDE
3629	584D	80		DB	LDOP
3630	584E	70		DB	NOI*16
3631	584F	14		DB	RP*16+IHL
3632	5850	80		DB	LDOP
3633	5851	14		DB	RP*16+IHL
3634	5852	70		DB	NOI*16
3635	5853	80		DB	LDOP
3636	5854	70		DB	NOI*16
3637	5855	07		DB	TR*16+IA
3638	5856	80		DB	LDOP
3639	5857	07		DB	TR*16+IA
3640	5858	70		DB	NOI*16
3641					
3642	5859	C5	DG00TAB7:	DB	RLCAOP
3643	585A	C9		DB	RRCAOP
3644	585B	C6		DB	RLAOP
3645	585C	CA		DB	RRAOP
3646	585D	32		DB	DAAOP
3647	585E	23		DB	CPLOP
3648	585F	D1		DB	SCFOP
3649	5860	22		DB	CCFOP
3650					
3651	5861	C4	DGCBTAB1:	DB	RLCOP
3652	5862	C8		DB	RRCOP
3653	5863	C3		DB	RLOP
3654	5864	C7		DB	RROP
3655	5865	D2		DB	SLAOP
3656	5866	D3		DB	SRAOP
3657	5867	34		DB	DBOP
3658	5868	D4		DB	SRLOP
3659					
3660	5869	10	DGCBTAB2:	DB	BITOP

3661	586A	C2	DB	RESOP
3662	586B	D5	DB	SETOP
3663				
3664	586C	62	DB	INOP
3665	586D	00	DB	TR*16+IB
3666	586E	41	DB	TRI*16+IC
3667	586F	A1	DB	OUTOP
3668	5870	41	DB	TRI*16+IC
3669	5871	00	DB	TR*16+IB
3670	5872	D0	DB	SBCOP
3671	5873	14	DB	RP*16+IHL
3672	5874	10	DB	RP*16+IBC
3673	5875	00	DB	LDOF
3674	5876	70	DB	NOI*16
3675	5877	10	DB	RP*16+IBC
3676	5878	91	DB	NEGDOP
3677	5879	B0	DB	EOL*16
3678	587A	B0	DB	EOL*16
3679	587B	CE	DB	RETNOP
3680	587C	B0	DB	EOL*16
3681	587D	B0	DB	EOL*16
3682	587E	61	DB	IMOP
3683	587F	00	DB	TNO*16
3684	5880	00	DB	0
3685	5881	80	DB	LDOF
3686	5882	80	DB	RE*16+IINT
3687	5883	07	DB	TR*16+TR
3688	5884	62	DB	INOP
3689	5885	01	DB	TR*16+IC
3690	5886	41	DB	TRI*16+IC
3691	5887	A1	DB	OUTOP
3692	5888	A1	DB	TRI*16+IC
3693	5889	01	DB	TR*16+IC
3694	588A	00	DB	ADCO ⁴
3695	588B	14	DB	RP*16+IHL
3696	588C	10	DB	RP*16+IBC
3697	588D	00	DB	LDOF
3698	588E	10	DB	RP*16+IBC
3699	588F	70	DB	NOI*16
3700	5890	34	DB	DBOP
3701	5891	80	DB	EOL*16
3702	5892	B0	DB	EOL*16
3703	5893	CD	DB	RETIOP
3704	5894	B0	DB	EOL*16
3705	5895	B0	DB	EOL*16
3706	5896	34	DB	DBOP
3707	5897	B0	DB	EOL*16
3708	5898	B0	DB	EOL*16
3709	5899	80	DB	LDOF
3710	589A	88	DB	RE*16+IREF
3711	589B	07	DB	TR*16+IA
3712	589C	62	DB	INOP
3713	589D	02	DB	TR*16+ID
3714	589E	41	DB	TRI*16+IC
3715	589F	A1	DB	OUTOP
3716	58A0	41	DB	TRI*16+IC
3717	58A1	02	DB	TR*16+ID
3718	58A2	D0	DB	SBCOP
3719	58A3	14	DB	RP*16+IHL
3720	58A4	12	DB	RP*16+IDE

3721 58A5 B0	DB LDDP
3722 58A6 70	DB NOI*16
3723 58A7 12	DB RP*16+IDE
3724 58A8 34	DB DBOP
3725 58A9 B0	DB EOL*16
3726 58AA B0	DB ECL*16
3727 58AB 34	DB DBOP
3728 58AC B0	DB EOL*16
3729 58AD B0	DB EOL*16
3730 58AE 61	DB IMOP
3731 58AF C0	DB TND*16
3732 58B0 01	DB 1
3733 58B1 B0	DB LDDP
3734 58B2 07	DB TR*16+IA
3735 58B3 B0	DB RE*16+IINT
3736 58B4 62	DB INOP
3737 58B5 03	DB TR*16+IE
3738 58B6 41	DB TRI*16+IC
3739 58B7 A1	DB OUTOP
3740 58B8 41	DB TRI*16+IC
3741 58B9 03	DB TR*16+IE
3742 58BA 00	DB ADCOP
3743 58BB 14	DB RP*16+IHL
3744 58BC 12	DB RP*16+IDE
3745 58BD B0	DB LDDP
3746 58BE 12	DB RP*16+IDE
3747 58BF 70	DB NOI*16
3748 58C0 34	DB DBOP
3749 58C1 B0	DB EOL*16
3750 58C2 B0	DB ECL*16
3751 58C3 34	DB DBOP
3752 58C4 B0	DB EOL*16
3753 58C5 B0	DB EOL*16
3754 58C6 61	DB IMOP
3755 58C7 C0	DB TND*16
3756 58C8 02	DB 2
3757 58C9 B0	DB LDDP
3758 58CA 07	DB TR*16+IA
3759 58CB 88	DB RE*16+IREF
3760 58CC 62	DB INOP
3761 58CD 04	DB TR*16+IH
3762 58CE 41	DB TRI*16+IC
3763 58CF A1	DB OUTOP
3764 58D0 41	DB TRI*16+IC
3765 58D1 04	DB TR*16+IH
3766 58D2 D0	DB SBCOP
3767 58D3 14	DB RP*16+IHL
3768 58D4 14	DB RP*16+IHL
3769 58D5 34	DB DBOP
3770 58D6 B0	DB EOL*16
3771 58D7 B0	DB EOL*16
3772 58D8 34	DB DBOP
3773 58D9 B0	DB EOL*16
3774 58DA B0	DB EOL*16
3775 58DB 34	DB DBOP
3776 58DC B0	DB EOL*16
3777 58DD B0	DB EOL*16
3778 58DE 34	DB DBOP
3779 58DF B0	DB EOL*16
3780 58E0 B0	DB EOL*16

3781	58E1	CC	DB	RRDOP
3782	58E2	B0	DB	EOL*16
3783	58E3	B0	DB	EOL*16
3784	58E4	62	DB	INOP
3785	58E5	05	DB	TR*16+IL
3786	58E6	41	DB	TRI*16+IC
3787	58E7	A1	DB	OUTOP
3788	58E8	41	DB	TRI*16+IC
3789	58E9	05	DB	TR*16+IL
3790	58EA	00	DB	ADCOP
3791	58EB	14	DB	RP*16+IHL
3792	58EC	14	DB	RP*16+IHL
3793	58ED	34	DB	DBOP
3794	58EE	B0	DB	EOL*16
3795	58EF	B0	DB	EOL*16
3796	58F0	34	DB	DBOP
3797	58F1	B0	DB	EOL*16
3798	58F2	B0	DB	EOL*16
3799	58F3	34	DB	DBOP
3800	58F4	B0	DB	EOL*16
3801	58F5	B0	DB	EOL*16
3802	58F6	34	DB	DBOP
3803	58F7	B0	DB	EOL*16
3804	58F8	B0	DB	EOL*16
3805	58F9	CB	DB	RLDOP
3806	58FA	B0	DB	EOL*16
3807	58FB	B0	DB	EOL*16
3808	58FC	34	DB	DBOP
3809	58FD	B0	DB	EOL*16
3810	58FE	B0	DB	EOL*16
3811	58FF	34	DB	DBOP
3812	5900	B0	DB	EOL*16
3813	5901	B0	DB	EOL*16
3814	5902	D0	DB	SBCOP
3815	5903	14	DB	RP*16+IHL
3816	5904	16	DB	RP*16+ISP
3817	5905	B0	DB	LDOF
3818	5906	70	DB	NOI*16
3819	5907	16	DB	RP*16+ISP
3820	5908	34	DB	DBOP
3821	5909	B0	DB	EOL*16
3822	590A	B0	DB	EOL*16
3823	590B	34	DB	DBOP
3824	590C	B0	DB	EOL*16
3825	590D	B0	DB	EOL*16
3826	590E	34	DB	DBOP
3827	590F	B0	DB	EOL*16
3828	5910	B0	DB	EOL*16
3829	5911	34	DB	DBOP
3830	5912	B0	DB	EOL*16
3831	5913	B0	DB	EOL*16
3832	5914	62	DB	INOP
3833	5915	07	DB	TR*16+IA
3834	5916	41	DB	TRI*16+IC
3835	5917	A1	DB	OUTOP
3836	5918	41	DB	TRI*16+IC
3837	5919	07	DB	TR*16+IA
3838	591A	00	DB	ADCOP
3839	591B	14	DB	RP*16+IHL
3840	591C	16	DB	RP*16+ISP

3841 591D 80		DB	LDDOP
3842 591E 16		DB	RF*16+ISP
3843 591F 70		DB	NOI*16
3844			
3845 5920 81	DGEDTAB2:	DB	LDIOP
3846 5921 24		DB	CPIOP
3847 5922 63		DB	INIOP
3848 5923 A2		DB	OUTIOP
3849 5924 34		DB	DBOP
3850 5925 34		DB	DBOP
3851 5926 34		DB	DBOP
3852 5927 34		DB	DBOP
3853 5928 83		DB	LD-DOP
3854 5929 26		DB	CPDOP
3855 592A 65		DB	INDOP
3856 592B A4		DB	OUTDOP
3857 592C 34		DB	DBOP
3858 592D 34		DB	DBOP
3859 592E 34		DB	DBOP
3860 592F 34		DB	DBOP
3861 5930 82		DB	LDIROP
3862 5931 25		DB	CPIROP
3863 5932 64		DB	INIROP
3864 5933 A3		DB	OTIROP
3865 5934 34		DB	DBOP
3866 5935 34		DB	DBOP
3867 5936 34		DB	DBOP
3868 5937 34		DB	DBOP
3869 5938 84		DB	LDDRUP
3870 5939 27		DB	CPDROP
3871 593A 66		DB	INDRUP
3872 593B A5	AEND:	DB	OTDRUP
3873 593C FF		DB	0FFH
3874			
3875		END	

AL	0002 ADL	0004 ASMB	48B8 ADCTAB	4F56
ADDTAB	4F64 ADPS	5065 ADCOP	0000 ADDOP	0001
ANDOP	0002 AEND	593B BS	0008 BLANK	0020
BMR	E91B BKPTADDR	40F3 BKPTCODE	40F5 BYE	4342
BYTESP	4892 BYTE	4897 BAD	4B12 BITH	4FC0
BIT2	4FC9 BOPS	5072 BITOP	0010 CR	0000
CURON	BB81 CUROFF	BB84 CINIT	BC65 CCAT	BC9B
CIDIR	BC83 CODIR	BC98 CIABAN	BC7D COABAN	BC92
CICHAR	BC80 COCHAR	BC95 CIOPEN	BC77 COOPEN	BC8C
CICLOSE	BC7A COCLOSE	BC8F COMWIDTH	40CD CURRENT	40DD
CRBUFF	410B CWBUFF	410D CATALOG	43F6 COPY	44CA
COMTAB	45C0 CRLF	4621 CUE	46AC CONVERT	47D2
CV0	47E3 CV1	47E7 CV2	47F3 CV3	4805
CLEAR	482D CL	0001 CC	0009 CLASS	400A
CL1	4D12 CL3	4D19 CL2	4D1A CL4	4D27
CL41	4D29 CL5	4D44 CL6	4D50 CLER	4D5E
CL7	4D61 CL71	4D63 CL72	4D77 CALTAB	4CF4
COPS	5077 CCODES	51BA CALLOP	0020 CPPOP	0021
CCFOP	0022 CPLOP	0023 CP1OP	0024 CPIROP	0025
CPDOP	0026 CPDROP	0027 CHKHL	535D CHKXY	547D
CXYZ	539D CHKOPD	53EE CHKNO	543F CKN2	5445
CHKTN0	544B CKTN2	5451 COMMA	54B5 CHKIND	55E5
CHKAREAS	579D CKA2	57A6 CKA3	57C6 DEL	007F
DSTART	40F9 DSTOP	40FB DIP	40FD DRSTART	40FF
DRETOP	4101 DRIP	4103 DEDAP	4105 DDOSP	4107
DEOSP	4109 DOWN	4281 DELAY	4912 DEL1	4215
DJH	4DBB DJ1	4DA4 DJ2	4DA6 DWH	4DAA
DBH	4DD0 DBH1	4DB4 DBH3	4DBE DBH4	4DC5
DEH	4DCD DL1	4F71 DL2	4F74 DL3	4E7P
DL4	4F88 DL5	4F8F DOPS	509A DECOP	0030
DJNZOP	0031 DAADP	0032 DIOP	0033 DZOP	0034
DASM	520E DSM2	5223 DPASS	524A DPG2	5261
DPS3	526D DL1ST	52D0 DLS2	52E0 DLS3	52F4
DINSTR	5318 DBOUND	5457 DBD2	5469 DSYMSCH	546B
DSS2	5476 DS93	548D DLABEL	5490 DLB2	54AC
DOUTOPT	54C2 DOUTOPD	54FA DOPD	5514 DOPDTAB	5E20
DOTR	552E DOPR	553B DOXY	554A DORE	554F
DOCC	555A DC2	555D DC3	555E DOXYD	5553
DXD2	5573 DONO	5579 DN2	5589 DOTNO	5571
DTN2	55A5 DTN3	55AC DOTNOI	55B0 DTN12	53B1
DTN13	55B9 DTN14	55BC DOUTH3	55C0 DHB2	5609
DHB3	55D2 DOUT	55DA DUT2	55E4 DECODE	5626
DCD2	563F DC03	5643 DGC0	5663 DGC07	5685
DGC06	568E DGC04	5692 DGC02	5696 DGC022	5698
DGC00	569C DGC002	569E DGC0135	56A7 DGC01352	564F
DGB0	56B7 DG802	55BB DG803	56CD DG40	54D1
DG402	56DA DG00	56E3 D6006	5705 D6005	5709
DG004	570D DG0042	570F DG003	5718 DG001	5729
DGCB	5737 DGCB1	5743 DGCB3	5750 DGCB4	5763
DGCB5	575A DGED	5770 DGED3	579E DGE04	579A
DGC0TAB1	57D9 DGC01AB3	57F1 DGC0TAB5	5904 DGC0TAB	5221
DG00TAB0	5829 DGC00TAB2	5841 DGC00TAB7	5859 DGC0TAB3	5961
DGCBTAB2	5869 DGEDTAB1	5860 DGEDTAB2	5920 ENTRY	4000
EOFP	40E1 EXIT	414D E0	42A7 ER	42A9
ENTER	42DF EOF	4606 ERR	4614 ERR2	4610
EXTERN	4647 EXT2	4674 E10	47CD E20	4047
EOL	000B E1	4917 E6	4B50 E7	4CA6
E11	4D22 EQUH	4DFF E02	4E04 ENDH	4E0B
EOPS	50C3 EXOP	0040 EXXOP	0041 E10P	0042
E4	5427 FF	000C F1	0000 F2	0001

F3	0002 F4	0003 FS	0004 F6	0005
F7	0006 FLAGS	40C6 FEP	40E9 FILL	44D8
FIL2	44E3 FIELD	4AA8 FD1	4AB4 FD2	4ABD
FD3	4ABC FD4	4ACB FD5	4ACF FD6	4AD3
FD7	4AD9 FD8	4AE1 FIND	4CBB FIN1	4CC1
FIN2	4CC8 FOPS	50D6 GOTO	44B5 GOT2	44B8
GOT3	44AC GETNAME	46DD GETOPTION	491C GOPS	50D7
GETAREAS	5280 GTA2	5285 GETOPD	53DA GD2	53E6
GD22	53EE GD3	53F3 GD4	53FB GD5	5403
GETKEY	54DC GK2	54DF GETREG	57D3 HOWBIG	4406
HOLD	4931 HOPS	50D8 HALTOP	0050 IMAGE	4137
INSERT	4326 IMPORT	45A8 IN2	45B1 INL	0003
IEC	0000 IDE	0002 IHL	0004 IAF	000E
ISP	0006 IB	0000 IC	0001 ID	0002
IE	0003 IH	0004 IL	0005 IA	0007
IIX	000D IIY	00FD IREF	0008 IINT	0000
ICY	0018 INCY	0010 IZ	0008 INZ	0000
IPO	0020 IPE	0028 IMIN	0038 IPOS	0030
IMH	4F28 IM2	4F31 IMTAB	4F39 INCH	4F3C
INC2	4F4C INTAB	4FEB IO1	4FFF I02	5006
IOER	5000 IOPS	50DE INCOP	0060 IMOP	0061
INOP	0062 INIOP	0063 INIROP	0064 INDOP	0065
INDROP	0066 IDFIND	55FA IDF2	55FD IDOUT	5608
IDT2	560A JL	0003 JUMP	4995 JP2	499E
JP3	49CF JPTAB	49D7 JRH	4D7D JMPTAB	4EE5
JMP1	4EEF JMP2	4EF3 JMP21	4EF6 JMP3	4EFE
JOPS	50FB JROP	0070 JPOP	0071 KILL	426A
KEYBOARD	467D KB2	4680 KB22	4689 KB3	469D
KEYTB	5031 KOPS	5102 KEYADDR	54EB KEYTRAN	5617
LF	000A LCT	40D9 LIMIT	40DB LBLP	40ED
LOCATE	4232 LC1	4240 LC2	4250 LINE	4290
LAST	42C4 LINC	48AE LL	0015 LIST	4A0F
LS1	4A20 LS12	4A35 LS2	4A41 LS3	4A50
LS4	4A53 LS5	4A74 LS6	4A81 LS7	4A85
LS8	4A86 LS9	4A8F LITLE	4B44 LITLE2	4B48
LOADH	4DE1 LTAB	4E0D L1	4E4D L2	4E51
L21	4E58 L3	4E5B L30	4E62 L31	4E65
L4	4E68 L5	4E6E L6	4E73 L61	4E74
L62	4E77 L63	4E7A L7	4E7D LER	4E82
L8	4E85 L9	4E97 LA	4E9E LB	4EA6
LC	4EAB LE	4EB4 LE1	4EC2 LOPS	5103
LDOP	0080 LDIOP	0081 LDIROP	0082 LDDOP	0083
LDDROP	0084 M1	4006 M2	400B M4	4010
MS	4015 M7	4019 M9	4021 M11	402D
M12	4036 M14	403F M13	4044 M15	404B
M16	4052 M17	405A M18	4064 M20	4069
M21	4070 M22	4076 M23	407D M24	4083
M25	4089 M27	408F M28	4095 M29	409B
M30	40B3 MDEF	40E3 MODIFY	44EB MOD1	44F1
MOD2	44F4 MOD3	44FA MOD4	4517 MOD5	4522
MEMCHECK	483D MEMTOP	484E MOFMIX	4B55 MOFMX2	4B56
MOFPRE	4B61 MOFLH	4B65 MOFH	4B69 MOFB	4B6C
MOF	4B6D MOF2	4B8A MOF5	4B94 MATH	4C1C
MA2	4C22 MA3	4C29 MA4	4C34 MA5	4C3F
MA50	4C46 MA51	4C4C MA52	4C54 MA6	4C5E
MA61	4C67 MA62	4C6E ML1	4F9B ML11	4FA1
ML12	4FA4 ML2	4FA9 ML3	4FB2 MOPS	511E
NEW	42F8 NEXT	4B52 NX0	4B55 NX1	4B58
NYB	48A0 NO	0003 NOI	0007 NOPs	511F
NOPOP	0090 NEGOP	0091 OBJ	40F1 ONEPAIR	4591

OUTPORT	459E OUTPUT	4630 DL	0003 OPDSCH	4AED
OPTSCH	4AFB ORGH	4DED OUTAB	4FF5 OOPS	5128
OROP	00A0 OUTOP	00A1 OUTIOP	00A2 OTIROP	00A3
OUTDOP	00A4 OTDROP	00A5 OFFSET	542C OFS2	543B
PBUSY	BD2E PSEND	BD31 FAGENO	40D7 PC	40EF
PRINT	42B6 PAIR	4592 PR2	461C PR3	461E
PAGE	4718 PG2	4726 PARAMETER	47A8 PARAM1	47AB
POSITION	4860 POS1	4868 POS2	4877 PASS	48CA
PS1	48CD PS2	4908 PARSER	4B9B PA1	4B9B
PA2	4BB7 PA31	4BE4 PA3	4BE8 PA7	4BEC
PER	4BF9 FA4	4BFC PAS	4C02 PA6	4C1A
PPH	4F10 PP2	4F1F PP21	4F22 POPS	5148
PUSHOP	00B0 POPOP	00B1 QDEF	40E5 QUERY	452A
QU2	4530 QU3	4539 QU4	453F QUS	454C
QU7	4553 QOPS	5152 READCHAR	BB09 REENTRY	4003
READ	439D RD2	43AA RB4	43C4 RSOURCE	43C7
RS2	43CA RS3	43EA RS4	43EE RCHAR	46F3
ROPEN	470A REMOVE	478C RP	0001 RPI	0005
RE	0008 RESOLV	4B35 RSTH	4ECE RST2	4E86
RETH	4EDB ROPS	5153 RPAIRS	51EB RERECS	5207
RETOP	00C0 RSTOP	00C1 RESOP	00C2 RLDP	00C3
RLCOP	00C4 RLCAOP	00C5 RLAOP	00C6 RRDP	00C7
RRCOP	00C8 RRCAOP	00C9 RRAOP	00CA RLDDP	00CB
RRDOP	00CC RETIOP	00CD RETNOP	00CE SYMWIDTH	40CF
SOFP	40DF STK	40EB STACK	41E0 SORT	441B
SRT2	4432 SCAN	443B SCN1	443E SCN2	443F
SCN3	444A SCN31	446B SCN4	4470 SPACE	462E
STRING	46A0 STR1	46A2 STARTSTOP	47B0 SOF	4832
SBL	0002 SYMBOL	4941 SY2	4992 SYMFIELD	4AA4
SYMSCH	4AE8 SEARCH	4B1A SC2	4B20 SC3	4B25
SBCTAB	4F5D SRH	4FD2 SR2	4FE2 SOPS	5192
SBCOP	00D0 SCFOP	00D1 SLAOP	00D2 SRAOP	00D3
SRLOP	00D4 SETOP	00D5 SUBOP	00D6 SWAPHL	536A
SWAPXY	53A0 XY2	53B2 XY3	53BC TXTOUT	BB5A
TEMP	40E7 TBUFF	4154 TOP	4270 TARGET	427D
THIS	42CE TRAP	474E TRAP2	47B4 TL	0010
TR	0000 TRI	0004 TNO	000C TNOI	000D
TALPHA	0030 TLAB	0031 TOPD	0032 TCOM	0033
TIND	0034 TADD	0040 TSUB	00C0 TMUL	0080
TDIV	0081 TAND	0082 TOR	0083 TDEF	0035
TLIT	0036 TERM	4C75 TE2	4C7D TE3	4C87
TYPE	4CAB TYPTAB	4CD9 TOPS	51AF TREGS	51D6
TRIPLET	57CC USTK	410F USP	414E UPC	4152
UP	425E USER	46AF US0	46B3 US1	46B9
US2	46C8 US4	46D8 UPDATE	48AB UOPS	51B0
UNSCRAMBLE	52AF UM2	52B5 UM3	52BA VECTOR	40F6
VIDEO	4636 VID2	4644 VOPS	51B1 WAITCHAR	BB06
WRITE	4346 WBIN	4349 WB3	4365 WB4	436D
WSOURCE	4370 WS2	4384 WS3	4390 WCHAR	46EB
WOPEN	46FB WPE2	4707 WORDSP	488D WOPS	51B2
XAMINE	4563 XL	0004 XY	0002 XYI	0006
XYD	000A XTAB	5010 X1	501D XER	5029
X2	502B X3	502E XOPS	51B3 XYPAIRS	51FF
XOROP	00E0 YOPS	51B8 ZEN	41E0 ZEN2	422E
ZAP	4299 ZOFS	51B9		